

65mm

71mm

无线领夹麦克风

说明书

CE FCC

中国制造

产品介绍

感谢您选择我们产品

本产品为智能无线领夹麦克风，可提供专业级别录音输出，即插即用，无需APP，多种用途：可实现网络直播、视频Vlog拍摄、节目访谈、采访录音、视频教学等场合的使用。

无线领夹麦克风有三部分构成，充电仓，麦克风发射端，接收端。（如下图所示）

（充电仓）

（发射端）

（接收端）

ID图示

① 录音孔

② 电量指示灯

③ 功能指示灯

④ 麦克风夹

⑤ 开关机/功能键

⑥ 苹果接口

⑦ 接收端充电口

⑧ Type-C接口

⑨ 接收端指示灯

⑩ 充电仓电量指示灯

⑪ 充电仓Type-C充电口

*****部分安卓手机因系统原因会出现兼容性问题，详情请咨询经销商*****

使用方法

第一步：首先先把接收端从充电仓拿出来，然后一头插入手机充电的接口。

第二步：接着充电仓拿出发射端麦克风就会自动连接。

第三步：接收端和发射端连接指示灯常亮，即连接成功，可以打开手机相机、直播视频等APP即可使用麦克风收音。

特别说明：
第⑦的使用方法如下：如果直播时，手机电量不足的情况下，\直接通过接收端的接口给予手机充电。

备注：部分型号的接收端不具备此功能，以实际产品为准

UI功能

麦克风发射端

功能/状态	操作	灯效
开机	长按25开机键	连接指示灯闪烁 电量指示灯5秒后熄灭
关机	长按25关机键	指示灯熄灭
与RX配对	开机自动配对	指示灯常亮
断开连接	长按RX或者TX关机 单击开关键开启降噪/关闭降噪	指示灯熄灭 开启绿灯常亮 关闭绿灯熄灭
静音	双击功能键开启静音 再次双击关闭静音	开启红灯常亮 关闭红灯熄灭
混响	三连击功能键开启混响 再次三连击关闭混响	开启黄灯常亮 关闭黄灯熄灭
低电量报警	/	显示电量0
充电	放入充电仓	充电100亮起30秒后熄灭

接收端

功能/状态	操作	灯效
开机	插入手机充电端口即可开机	指示灯微闪
关机	从手机上拔出接收端	指示灯熄灭
与TX配对	开机自动配对	指示灯常亮
断开连接	TX关机或者长按RX键断开	指示灯微闪

使用须知

苹果手机和华为手机即插即用
VIVO/OPPO等部分手机需要手动打开OTG功能！

VIVO手机：打开设置 找到更多设置 找到OTG
点击右边开关开启即可

OPPO手机：打开设置 找到更多设置 找到OTG
点击右边开关开启即可

部分手机：打开设置 找到其他网络与连接进入
找到OTG点击右边开关开启即可

注：OTG在不使用的情况下5-10分钟手机会自动关闭！
录制完视频 不需要拔掉 接收器方可播放视频！

包装清单

包装清单内容

(1) 充电仓
(2) 麦克风发射端
(3) 接收端
(4) 充电线
(5) 用户说明书

65mm

71mm

Wireless Microphone

User Manual

CE FCC

MADE IN CHINA

Introduction

Thank you for choosing our products!

This product is a smart wireless microphone that can provide professional-level recording output, no APP required and multiple uses: it can be used for live streaming, video Vlog shooting and other occasions.

The wireless microphone consists of three parts: power case, microphone transmitter and receiver. (As shown below)

（power case）

（transmitter）

（receiver）

ID Diagram

① microphone port

② battery light

③ Function indicator light

④ Microphone clip

⑤ Power on/off / function key

⑥ receiver iphone port

⑦ Charging interface of the receiver

⑧ Type-C port

⑨ receiver indicator light

⑩ case battery level light

⑪ phone charging port

Note: Some Android devices may experience limited functionality due to System-specific restrictions.

How to use

First Step: plug the receiver into the phone

Second Step: take out the microphone

Third Step: The light of the receiver is remains on, and the phone opens apps such as the camera and live video or other apps to use microphone for recording.

Special Note:
For the use of ⑦ port: If the phone is low power during Live, it can be recharged directly through ⑦ port.

Note: oppo / vivo / iqoo / realm brand mobile phones can be used normally only when they go to the settings (search "OTG" - turn on OTG power supply)

About UI

Microphone Transmitter

Function	How to use	Light
Power on	Long press the power button for 2 seconds	Connection indicator flashes Battery indicator goes out after 5 seconds
Power off	Long press the power button for 2 seconds	off
Connect mic	auto-pairing	remains on
Disconnect	unplug or power off	Indicator flashes slowly
Noise reduction	click 1 time	on: green light and it will stay on. off: green light and it will stay on.
Mute	click 2 times	On: red light stays on Off: red light goes out
Reverberation	click 3 times	On: yellow light stays on Off: yellow light goes out
Low batt alarm	/	Display battery level 0
Charging	put into power case	Charging 100 lights up and goes out after 30 seconds

Receiver

Function	How to use	Light
Power on	plug into phone	flashing
Power off	unplug	off
Connect mic	auto-pairing	remains on
Disconnect	unplug or power off	flashing

Use the information

iPhone and Huawei phones plug and play
VIVO/OPPO and other mobile phones need to manually open the OTG function!

VIVO mobile phone: Open Settings find more
Settings find OTG click on the right switch to open

OPPO mobile phone: Open the Settings to find other
Settings to find OTG and click the switch on the right

Partial phones: Open Settings to find other
networks and connect to find OTG
Click the switch on the right to open it

Note: If OTG is not in use for 5-10 minutes, the phone will automatically shut down!
After recording the video, you do not need to unplug the receiver to play the video!

Packing List

Packaging List Content

(1) Power case
(2) Microphone transmitter
(3) Receiver
(4) Charging cable
(5) User Manual

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.