

User Manual

Magnetic Wireless Keyboard



Table of contents

Technical Support	01
Compatibility	01
Setup/Connection	02
Shortcut Key	03
Touchpad Function	04
Installation and Removal	05
Charging	05
Troubleshooting	06
Product Specification	07
Compliance.....	08

Technical Support


If you have any issues please let us know ASAP! We hope you are taken care of and happy right away! All equipment comes with a 12-month warranty, so you can relax and be comfortable with your purchase. For the fastest and friendliest support, please contact us through Amazon.

Compatibility

Compatible with iPadOS 13 (and newer). We recommend that you upgrade your iPad to 13.4.1 for optimal performance.


Check your iPad system version:

1.  >General>About>Software Version.
2. Upgrade to iPadOS 13.4.1 or higher to use the touchpad function properly.



To upgrade your iPad to the latest version:

1. Open the device's Settings > General > Software Update.
2. Click "Download and Install".




*If you see Resume Download, click it.

Setup/Connection


Pairing with iPad:

1. Switch ON/OFF to ON position.
 2. Press  +  and the blue indicator starts to flash.
 3. Toggle "**Bluetooth On**" in the "**Settings**" app.
 4. Tap "**Bluetooth Keyboard**" in the "**Bluetooth**" section of the "**Settings**" app, under "**My Devices**".
 5. Tap "**Pairing**", when the blue light stops flashing, the device is connected.
- *Repeat steps 1-5 when pairing with a new device.**



If your system is 13.3.1, please follow the steps below to enable the touch-pad function:

1. Go to "Settings" > Accessibility > Touch
2. Make sure the assistive touch option is turned on.




Shortcut Key

When the red light needs to be charged, the charging voltage only supports 5V.

Tips: In any application, you can long press the Command key to view the available shortcuts.

ON/OFF  **Charging Voltage**
5V ONLY



- Command+Tab** = APP switch
- Command+C** = Copy
- Command+A** = Select all
- Command+V** = Paste
- Command+Z** = Redo/Undo
- Command+X** = Cut
-  +  = Bluetooth pairing
-  +  = Backlight brightness adjustment
-  +  = Touchpad switch
-  +  = Switch backlight color

Touchpad Function

Note: Make sure the Bluetooth is connected and the touchpad function is turned on!



Single tap: Press down with one finger until there is a slight click.




Tap and hold: Press and hold with one finger.




Drag: Tap and hold the item, then slide your finger across the trackpad to move it.



Wake up the iPad: Tap the trackpad. Or if you are using an external keyboard, press any key to wake up.




Open the dock: Swipe the pointer across the bottom of the screen with one finger.



Go to the home screen: Swipe the pointer across the bottom of the screen with one finger. After the dock appears, swipe the pointer across the bottom.



Show side pull: With one finger, swipe the pointer across the right edge of the screen. To hide the side pull, swipe right again.



Open the control center: Move the pointer with one finger to select the status icon in the upper right, then tap. Or select the status icon in the upper right and swipe up with one finger.




Open notification center: Move the pointer with one finger to select the status icon in the upper left, then tap. Or use one finger to move the pointer near the top middle of the screen.



Scroll up or down: Swipe up or down with two fingers.



Scroll left or right: Swipe left or right with two fingers.



Zoom: Place two fingers close together. Pinch to zoom in, or pinch to zoom out.



Go to the home screen: Swipe up with three fingers.




Open the App Switcher: Swipe up with three fingers, pause and lift your finger. Or pinch with four fingers, pause and lift your fingers.



Switch between open apps: Swipe left or right with three fingers.



Open the Today view: When the home or lock screen is visible, swipe right with two fingers.



Open search from the home screen: Swipe down with two fingers.



Secondary tap: Two-finger-tap items such as icons on the home screen, messages in your mailbox, and the camera button in control center to display their quick action menu. Or if you're using an external keyboard, you can hold the control key and click the trackpad.

Installation and Removal




Install the tablet into the protective case and then attach it to the holster.



Remove the protective case with the tablet installed from the holster first, then remove the tablet from the case.

Charging

1. Turn on the keyboard. (if the power indicator flashes, please charge the keyboard)



2. Plug the charging cable (included) into the keyboard and the adapter.

- a) The indicator light turns red when the keyboard is charging.
- b) When charging is complete, the battery indicator turns to green.



iPad adapter


Troubleshooting

If the keyboard does not work properly, please check the following:

1. The Bluetooth function of the iPad (or other Bluetooth devices) is turned on;
2. The Bluetooth keyboard is within 33 feet;
3. The Bluetooth keyboard is charged;
4. Confirm that the keyboard is turned on (power indicator light on);
5. Make sure the keyboard has been paired via Bluetooth.

If you have unwanted auto-correction or punctuation, please follow these steps:

1. Open Settings App > General > Keyboard > Hardware Keyboard;
2. Turn off Auto-Capitalization, Auto-Correction and "." Shortcut (see image below).



If Bluetooth pairing fails, please try the following steps:

1. Press and hold "⏏" + "Delete" for more than 3 seconds, the backlight of the keyboard flashes three times, and then the keyboard restores the factory settings;
2. Delete all Bluetooth devices on the iPad;
3. Turn off the Bluetooth on the iPad Bluetooth function;
4. Restart the iPad;
5. Turn on the Bluetooth on the iPad;
6. Repeat the steps described on page 2 and page 3 to pair the keyboard.

Product specification

Operating distance : 10 meters (33 feet)	Backlight dormancy time : 30 seconds
Modulation system : GFSK	Keyboard dormancy time : 10 minutes
Working voltage : 3.0-4.2V	Charging time : <3 hours
Working current : 10mA (without backlight) / 70mA (backlight)	Charging voltage : 5V
Sleep current : <40μA	Key life : 3 million times
Charging current : <300mA	Working temperature : -10+55°C
No backlight working hours : 200 Hours	
Backlight working time : 7 Hours	
Maintenance : Please store at room temperature and charge with normal voltage.	

Compliance

FCC Warning:

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.