SONICAKE

POCKET MASTER

Multi-Effects Processor BT

Specifications

Technical Specifications

A/D/A Converter: 24-bit
Sampling Frequency: 44.1 kHz
SNR: 103dB
Maximum Simultaneous Effects: 9
Preset Memory: 100 Presets Slots,
50 Factory Presets

Digital Connections

USB-C Port: USB 2.0 Type C Port

USB Recording Specification

Sample Rate: 44.1 kHz
Bit Depth: 16-bit

Analog Input Connections

IN: 1/4" (6.35mm) Unbalanced (TS), 1MΩ

Size and Weight

Dimensions: 103.5mm (W) × 85mm (D) × 28.5mm (H)
Unit Weight: 194g

Analog Output Connections


OUT (PHONES): 1/4" (6.35mm) Stereo (TRS), 100Ω

Power

Power Requirements: USB Type-C, DC 5V
Built-in Lithium Battery: 1000mAh

www.sonicake.com

SONICAKE



❶ 1.77" LCD color screen, to display preset information, battery level, BT status, and other operational information

❷ Hold to turn on the device or enter the option menu; turn or press the knob to select or adjusts parameters

❸ Press "◀" / "▶" to switch presets, switch effect modules and various options

In the main menu:
Press "◀" + "▶" at the same time to turn on the TUNER; hold "◀" + "▶" at the same time to enter the loop menu


In a non-main menu:
Press "◀" + "▶" at the same time to return main menu

❹ 1/4" (6.35mm) TS mono input for plugging in your instrument


❺ 1/4" (6.35mm) TRS stereo output for connect headphones, amps, pedals, etc.

❻ USB Type-C to connect to a mobile phone or computer for recording and firmware upgrade

❼ USB Type-C for device power supply and charging



SONICAKE



❶ 1.77" LCD彩色显示屏用于显示预设信息、可调参数、电量、BT开关等

❷ 长按VALUE/VOL旋钮开机或进入选项菜单；转动或按下VALUE/VOL旋钮以选定或者调整参数


❸ 按下"◀" / "▶"键用于上下切换预设 、切换效果模块及各类选项
主界面时： 同时按下"◀" + "▶"键进入调音界面；同时长按"◀" + "▶"键进入乐句循环界面
非主界面时： 同时按下"◀" + "▶"键返回主界面

❹ 6.35mm（1/4"）单声道输入接口，用于连接乐器

❺ 6.35mm（1/4"）立体声输出接口，用于连接耳机或音箱、效果器

❻ Type-C USB接口，连接手机或电脑进行录音及固件升级

❼ Type-C USB接口，用于设备供电与充电



SONICAKE

POCKET MASTER

Multi-Effects Processor BT

规格参数

技术指标

A/D/A转换：24-bit
采样率：44.1kHz
信噪比：103dB
效果模块：最大支持9个效果模块
预设数量：100个预设位置，50个出厂预设

数字连接

USB-C接口：USB2.0 Type-C接口

USB录音规格

采样频率：44.1kHz
采样深度：16位

模拟输入连接

输入：6.35mm（1/4"）非平衡输入（TS）接口，阻抗1MΩ

尺寸及重量

尺寸：103.5mm（长）× 85mm（宽）×28.5mm（高）
重量：194g

模拟输出连接

立体声（耳机）输出：6.35mm（1/4"）TRS接口，阻抗100Ω

电源

电源要求：USB Type-C, DC 5V
内置锂电池：1000mAh

www.sonicake.net

FCC Statement:
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) This device must accept any interference received, including interference that may cause undesired operation. Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-Reorient or relocate the receiving antenna.
-Increase the separation between the equipment and receiver.
-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-Consult the dealer or an experienced radio/TV technician for help.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.

This device has been evaluated to meet general RF exposure. The device can be used in portable exposure condition with restriction

FCC ID: 2A7J4-QME10

Product Name/产品名称：Multi-Effects Processor/综合效果器
Model Number/产品型号：QME-10
FCC ID: 2A7J4-QME10 IC: 30072-QME10
HVIN: QME-10 CMIIT ID: XXXXXXXXXX Made in China

长沙乾音科技有限公司
Changsha Sonicake Technology Co.,Ltd

FC CE RoHS

IC Caution:
Radio Standards Specification RSS-Gen, issue 5 This device contains licence-exempt transmitter (s)/ receiver (s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS (s).

Operation is subject to the following two conditions:
This device may not cause interference.
This device must accept any interference, including interference that may cause undesired operation of the device.

RF exposure statement:

This device has been evaluated to meet general RF exposure. The device can be used in portable exposure condition with restriction

Cet appareil contient des emetteurs/recepteurs exemptes de licence conformes aux RSS (RSS) d'Innovation, Sciences et Developpement economique Canada.

Le fonctionnement est soumis aux deux conditions suivantes:
Cet appareil ne doit pas causer d'interferences.
Cet appareil doit accepter toutes les interferences, y compris celles susceptibles de provoquer un fonctionnement indesirable de l'appareil.

Declaration d'exposition RF:
L'appareil a été évalué pour répondre aux exigences générales d'exposition aux RF. L'appareil peut être utilisé dans des conditions d'exposition portable sans restriction.

IC: 30072-QME10