

15 USB Type-C接口用于连接手机或电脑进行录音或固件升级, 同时此接口可用于设备供电与充电。

规格参数

技术指标

A/D/A转换: 24-bit
采样率: 44.1kHz
信噪比: 103dB
效果模块: 最大支持9个效果模块
预设数量: 100个预设位置, 50个出厂预设

数字连接

USB接口: USB 2.0 Type-C接口

www.sonicake.net

模拟输出连接

STEREO OUT:
6.35mm (1/4") 立体声输出 (TRS) 接口, 阻抗1kΩ
PHONES:
3.5mm (1/8") 立体声耳机输出 (TRS) 接口, 阻抗22Ω

模拟输入连接



IN: 6.35mm (1/4") 非平衡输入 (TS) 接口, 阻抗1MΩ
EXP/FS: 6.35mm (1/4") TRS

尺寸及重量

尺寸: 135mm (长) × 114mm (宽) × 51mm (高)
重量: 378g

电源

DC电源要求: DC 9V外正内负5.5 × 2.1mm接口, ≥700mA (最小工作电流: 160mA, 充电电流: 700mA)
USB电源要求: Type-C, DC 5V, ≥1A (最小工作电流: 300mA, 充电电流: 1A)
内置锂电池: 2000mAh, 3.7V



15 USB Type-C port to connect to a mobile phone or computer for recording and firmware upgrade. It can also be used to power or charge device.

Specifications

Technical Specifications

A/D/A Converter: 24-bit
Sampling Frequency: 44.1 kHz
SNR: 103dB
Maximum Simultaneous Effects: 9
Preset Memory: 100 Presets Slots,
50 Factory Presets

Power

DC Power Requirements: DC 9V center negative, 5.5 x 2.1mm, ≥700mA (Operating Current: 160mA, Charging Current: 700mA)
USB Power Requirements: Type-C, DC 5V, ≥1A (Operating Current: 300mA, Charging Current: 1A)
Built-in Lithium Battery: 2000mAh, 3.7V

- 1.77" LCD color screen, to display preset information, battery level, BT status, and other operational information.
- Turn or press the knob to select or adjusts parameters.
- Press to return to the previous menu.
- Press to enter the Save menu to store changed parameters, rename or move presets; hold to quick saving.
- Press to enter the Global menu.
- Press to turn on/off the drum machine, hold to enter the Drum menu.
- Press to enter this effect module edit menu, hold to turn on/off module.
- To switch presets forward or backward; press together to enter the tuner; long press together to enter the looper.
- 1/4" (6.35mm) TRS for connecting an external expression pedal or footswitch controller.
- 1/4" (6.35mm) TS mono input jack for plugging in your instrument.
- 1/4" (6.35mm) TRS stereo output for connect amps, pedals, etc.
- 1/8" (3.5mm) TRS stereo output for plugging in headphones.
- Hold to power on/off device.
- DC 9V center negative power jack for device power supply and charging.

Analog Output Connections

STEREO OUT: 1/4" (6.35mm) Stereo (TRS), 1kΩ
PHONES: 1/8" (3.5mm) Stereo (TRS), 22Ω

Analog Input Connections

IN: 1/4" (6.35mm) Unbalanced (TS), 1MΩ
EXP/FS: 1/4" (6.35mm) TRS

Size and Weight

Dimensions:
135mm (W) x 114mm (D) x 51mm (H)
Unit Weight: 378g

Digital Connections

USB Port: USB 2.0 Type C Port

www.sonicake.com

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

FCC ID: 2A7J4-QME20

Product Name/产品名称: Multi-Effects Processor/综合效果器

Model Number/产品型号: QME-20

FCC ID: 2A7J4-QME20

HVIN: QME-20

CMIIT ID:

IC: 30072-QME20

Made in China

长沙乾音科技有限公司
Changsha Sonicake Technology Co.,Ltd



IC Caution:

Radio Standards Specification RSS-Gen, issue 5

- English:

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

This device may not cause interference.
This device must accept any interference, including interference that may cause undesired operation of the device.

RF exposure statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

- French:

Cet appareil contient des emetteurs / recepteurs exemptes de licence conformes aux RSS (RSS) d'Innovation, Sciences et Developpement economique Canada. Le fonctionnement est soumis aux deux conditions suivantes:

Cet appareil ne doit pas causer d'interferences.
Cet appareil doit accepter toutes les interferences, y compris celles susceptibles de provoquer un fonctionnement indesirable de l'appareil.

Declaration d'exposition RF:
L'appareil a ete evalue pour repondre aux exigences generales d'exposition aux RF.
L'appareil peut etre utilise dans des conditions d'exposition portable sans restriction.

IC: 30072-QME20

SMART BOX
Multi-Effects Processor BT

SONICAKE