中

英

MONSTER



Airmars XKT22
真无线蓝牙耳机
使用说明书

## 产品参数


- 蓝牙版本 ---------- V5.3
- 传输距离 ---------- ≥10m
- 喇叭直径 ---------- Φ13mm
- 喇叭阻抗 ---------- 32Ω±15%
- 灵敏度 ---------- 104±3dB
- 频响范围 ---------- 20Hz-20KHz
- 电池容量（充电盒） ---------- 320mAh 3.7V
- 电池容量（耳机） ---------- 30mAh 3.7V
- 充电时间（充电盒） ---------- ≈1.5小时
- 播放时间（耳机） ---------- ≈4小时
- 配合充电盒播放时间 ---------- ≈20小时

## 包装清单



- 耳机 *2
- 充电盒 *1
- 使用说明书 *1
- Type-C充电线 *1

## 产品示意说明




## 给充电盒充电

用Type-C充电线连接充电盒到5V电源适配器。



额定输入：5V⎓30mA(耳机)　　额定输入：5V⎓320mA(充电盒)

**温馨提示：当关闭充电盒盖，充电盒指示灯呈冰蓝灯闪烁，请给充电盒充电。**


## 指示灯指南

| 模式 | 描述 | 语音提示 |
|---|---|---|
| 开机 | 耳机冰蓝指示灯2秒3次 | "Power on" |
| 关机 | 耳机红色指示灯长亮1秒熄灭 | "Power off" |
| 配对 | 耳机红蓝色指示灯交替闪烁 | "Pairing" |
| 连接 | 耳机指示灯熄灭 | "Connected" |
| 断开 | 耳机红蓝色指示灯交替闪烁 | "Disconnected" |
| 耳机低电 | 耳机红色指示灯闪烁 | "Battery low" |
| 充电盒给耳机充电 | 耳机红色指示灯长亮 | — |
| 充电盒充电 | 冰蓝指示灯闪烁 | — |
| 充电盒充满 | 红色指示灯长亮 | — |

## 产品操作说明

1. 开机
   方式一：将耳机从充电盒中取出，耳机自动开机。
   方式二：长按左/右耳机的MFB按键约2秒，耳机开机。
2. 关机
   方式一：将耳机放回充电盒中，耳机关机。
   方式二：与蓝牙设备断开连接约3分钟后，自动关机。
3. 配对
   步骤一：将耳机从充电盒中取出，耳机自动开机；
   步骤二：打开智能设备的蓝牙列表，搜索 "Monster Airmars XKT22" 进行配对，连接成功后，会听到提示音 "Connected"。

* 超出距离，仅断开连接3分钟内，回到有效距离，自动连接设备。



**注意：**
* 如果产品长时间不使用，应先充满电，并确保设备处于关机状态。
* 长期存放前，请将充电盒、耳机电池充满电后再存放。

## 触控键操作

视觉模式



- 语音助手：长按2秒左耳MFB
- 音量加：单击右耳MFB
- 音量减：单击左耳MFB

## 音乐播放模式



- 暂停/播放：双击左/右耳机MFB
- 上一曲：三击左耳机MFB
- 下一曲：三击右耳机MFB

## 电话免提



- 接听：双击左/右耳机MFB
- 拒接：长按2秒左/右耳机MFB
- 挂断：双击左/右耳机MFB

## 游戏模式/音乐模式 切换：已连设备



- 长按2秒右耳机MFB进入游戏模式
- 长按2秒右耳机MFB进入音乐模式

## 恢复出厂设置

耳机开机后未与蓝牙设备配对状态下，左/右耳机配对成功，连击左/右耳机5次后左/右耳机关机（播放配对完连接前的所有信息）

## 注意

1.充电及产品前，务必关闭点动开机，配对开连接，耳机进入充电盒后耳机关机。耳机关机。
2.若遇连，有异长，如长期不用，建议3天充电1次，延长电池寿命，如无需要充电前记得将耳机连接蓝牙，避免被电池充电保护。
3.电池充电的温度范围为0℃-45℃，若超出范围不充，影响使用寿命。
4.如不使用产品请将耳机连接充电盒，将耳机放在充电盒内，并关闭盒盖，使用时为保证最佳效果，可能在播放音乐过程中，会出现短暂、轻微的声音干扰等现象。

## 警告

1.长时间以高音量使用耳机可能会损害您的听力。建议只使用适当音量收听，通话和听音乐。
2.请不要将此款产品丢弃入水中，以免造成损害。
3.不要自行拆卸产品及配件，以免导致损坏及保修失效。
4.请勿将产品安放在热源或高温场所。
5.请勿使用非原装充电设备为耳机充电。

| Name of the Parts<br>部件名称 | Hazardous Substances<br>有害物质 | | | | | |
|---|---|---|---|---|---|---|
| | Pb<br>铅 | Hg<br>汞 | Cd<br>镉 | Cr(VI)<br>六价铬 | PBB<br>多溴联苯 | PBDE<br>多溴二苯醚 |
| Housing<br>外壳 | O | O | O | O | O | O |
| Loudspeakers<br>喇叭单元 | O | O | O | O | O | O |
| PCBA<br>电路板组件 | X | O | O | O | O | O |
| Accessories<br>电源线、连接线 | X | O | O | O | O | O |

This table is compiled according to SJ/T 11364.
本表格依据SJ/T 11364的规定编制。

O: Indicates that this hazardous substance contained in all of the homogeneous materials for the part is below the limit requirement in GB/T 26572.
表示该有害物质在该部件所有均质材料中的含量均低于GB/T 26572规定的限量要求以下。

X: Indicates that this hazardous substance contained in at least one of the homogeneous materials used for this part is above the limit requirement in GB/T 26572.
表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572规定的限量要求。

## FCC 声明

根据FCC规则第15部分，本设备经过测试，符合有关数字设备的限制。这些限制旨在提供合理的住宅设施中的有害干扰防护，该设备产生使用并可辐射射频能量，如果未按照规定安装和使用说明可能会对无线电通信造成有害干扰。然而，并不能保证在特定安装中不会发生干扰。如果这个设备有对无线电或电视接收造成有害干扰，可通过将此未确定设备关闭和打开时，鼓励用户尝试通过一个或多个以下更多措施：

- 重新定向或重新定位接收天线。
- 增加设备和接收器之间的间隔。
- 将设备连接到与接收器不同的电路上的插座已连接。
- 请咨询经销商或经验丰富的无线电/电视技术人员以获得帮助。

此设备符合FCC规则的第15部分，操作受以下两个条件限制条件：

（1）本装置不得引起有害干扰。
（2）本装置必须接受任何接收到的干扰，包括可能导致意外操作的干扰。未经合规责任方明确批准的变更或修改可能使用用户对设备的操作权限失效。

FCCID：2ABPV-QSMXKT22

Environment Friendly Use Period (EFUP)
环保使用期限

This logo refers to the period (10 years) during which the hazardous substances in electronic and electrical products will not leak or mutate so that the use of these [substances] will not result in any severe environmental pollution, any bodily injury or damage to any assets.

这标志标识的期间（10年）是电子电气产品中有害物质在正常使用的条件下不会发生外泄或突变，电子电气产品的产中使用者电子电气产品不会对环境造成严重污染或对其人身、财产造成严重损害的期限。

## 保修卡

感谢您的广，无保修卡是您将来申请保修的凭证，请您配合填售后将其保存好妥善保管为荷！

| 用户信息 | | | |
|---|---|---|---|
| 用户姓名 | | 电子邮件 | |
| 联系电话 | | 邮政编码 | |
| 通讯地址 | | | |

| 产品信息 | | | |
|---|---|---|---|
| 产品名称 | | 产品型号 | |
| 产品条码/编号/批号 | | | |

| 销售商信息 | | | |
|---|---|---|---|
| 名　称 | | | |
| 地　址 | | | |
| 联系电话 | | 邮政编码 | |
| 销售日期 | | 发票号码 | |
| 备　注 | | | |

MONSTER 合格证
产品编号
生产日期
检 验 员
QC

Product parameters


- Bluetooth version ---------- V5.3
- Transmission distance ---------- ≥10m
- Driver diameter ---------- Φ13mm
- Driver impedance ---------- 32 Ω ±15%
- Ear sensitivity ---------- 104±3dB
- Frequency response ---------- 20Hz-20KHz
- Battery capacity(Charging case) ---------- 320mAh 3.7V
- Battery capacity(Headphone) ---------- 30mAh 3.7V
- Charging time(Charging case) ---------- ≈1.5 hours
- Music playtime(Headphone) ---------- ≈4 hours
- Music playtime with charging case ---------- ≈20 hours

## Product Schematic Description



- Headphones*2
- Charging case*1
- Instructions Manual*1
- Type-C Charging cable*1

## Product Schematic Description




## Charge the charging case

Connect the charging case to the 5V power adapter with Type-C charging cable.



Rated input: 5V⎓30mA(Headphone)　　Rated input: 5V⎓320mA(Charging case)

**Warm tip: When the charging box cover is closed, the charging box indicator light flashes ice blue, please charge the charging box.**


Indicator guide

| Mode | Describe | Sound prompt |
|---|---|---|
| Power On | The ice blue light of the headset blinks 3 times | "Power on" |
| Power Off | The red indicator of the headset is on for 1 second | "Power off" |
| Pairing | The red and blue indicators on the headset blink alternately | "Pairing" |
| Connected | Headphones LED indicator is off. | "Connected" |
| Disconnected | The red and blue indicators on the headset blink alternately. | "Disconnected" |
| Low Battery | The red indicator on the headset blinks. | "Battery low" |
| Headphones in the charging case | The ice Red indicator light on the headset is bright | — |
| Charging case low power | The ice blue indicator is blinking | — |
| Charging case charged | Red indicator flashing | — |
| Charging case fully charged | The red indicator is on | — |

## Product operating instructions

1. Power on
   Method1: Take the earphones out of the charging case and the earphones turn on automatically.
   Method2: Long press the MFB button of the left/right headset for about 3 seconds to power on the headset.
2. Power off
   Method1: Put the earphones back in the charging case and turn them off.
   Method2: The device automatically shuts down after 3 minutes of disconnection from the Bluetooth device.
3. Pairing
   Step one: Put the earphones back in the charging case and turn them off.
   Step two: Open the Bluetooth list of smart devices, search for "Monster Airmars XKT22" to pair, and the connection is successful After that, you will hear the "Connected" tone

* Headphones will try reconnecting to the device within 3 minutes when connection is lost.



**NOTE:**
* Fully charge the headphones and power off before an intended not-in-use period.
* Unplug the charging cable after charging.

**Operation**

Normal



- Voice assistant: Press and hold left MFB for 2 seconds
- Volume + : Click right MFB
- Volume – : Click left MFB

## Music playback



- Pause/Play: Double click Left/Right MFB
- Last song: Three hits left MFB
- Next song: Three hits left MFB

## Phone



- Answer: Double click the left/right MFB
- Reject: Long press left/right MFB for 2 S
- Hang up: Double click the left/right MFB

## Game/Music switching：Device connected



- Press right MFB for 2 seconds to enter Game mode
- Press right MFB for 2 seconds to enter Music mode

## Restore factory settings

If the headset is not paired with the Bluetooth device after the headset is turned on, the left/right headset is paired successfully. After clicking the left/right headset for 5 times, the left/right ear is turned off (all information about pairing and connection is cleared).

## Precautions

1. Take out the earphone from the charging box, without pressing any button, the earphone will automatically turn on, connect or pair, put the earphone into the charging box, and the charging box will automatically Charge your headphones. Turn them off.
2. Charge once every 15 days to extend battery life, and the charging part of the headset is often used with cotton swabs Alcohol wipe, can help smooth charging, avoid bad contact, affect the use experience.
3. The battery [battery pack or battery combination] shall not be exposed to lighting, baking or similar overheating environment. Do not disassemble, knock, squeeze or throw in the fire, if there is serious swelling, do not continue to use. Do not place in high temperature environment, such as heat source or fire source.
4. Because this product adopts wireless connection mode, it is affected by environment, mobile phone brand, usage behavior and other factors in daily use It may be normal to have a brief, slight sound delay during the playing of music.

Warnings
1. Do not use headphones at high volume for an extended period of time.
2. Keep the headphones away from dust and water.
3. Do not disassemble the headphones and accessories, otherwise warranty will be voided.
4. Keep headphones away from any impact or vibration.
5. Do not use any chemical solvents or cleaning agent on the headphones.

| Name of the Parts | Hazardous Substances | | | | | |
|---|---|---|---|---|---|---|
| | Pb | Hg | Cd | Cr(VI) | PBB | PBDE |
| Housing | O | O | O | O | O | O |
| Loudspeakers | O | O | O | O | O | O |
| PCBA | X | O | O | O | O | O |
| Accessories | X | O | O | O | O | O |

This table is compiled according to SJ/T 11364.
O : Indicates that this hazardous substance contained in all of the homogeneous materials for this part is below the limit requirement in GB/T 26572.
X : Indicates that this hazardous substance contained in at least one of the homogeneous materials used for this part is above the limit requirement in GB/T 26572.

## FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

— Reorient or relocate the receiving antenna.
— Increase the separation between the equipment and receiver.
— Connect the equipment into an outlet on a circuit different from that to which the receiver isconnected.
— Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:

(1) This device may not cause harmful interference.
(2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This equipment should be installed and operated with minimum distance 0cm between the radiator and your body.

FCCID: 2ABPV-QSMXKT22

Environment Friendly Use Period (EFUP)

This logo refers to the period (10 years) during which the hazardous substances in electronic and electrical products will not leak or mutate so that the use of these [substances] will not result in any severe environmental pollution, any bodily injury or damage to any assets.

## Warranty Service

Dear user, this warranty card is the proof of your future warranty application, please cooperate with the seller to fill it out and keep it for future use!

| User info | | | |
|---|---|---|---|
| User name | | Email | |
| Contact number | | Postal code | |
| Mailing address | | | |

| Product information | | | |
|---|---|---|---|
| Product name | | Product number | |
| Product barcode / Serial number / Batch number | | | |

| Vendor information | | | |
|---|---|---|---|
| Name | | | |
| Address | | | |
| Contact number | | Postal code | |
| Sales date | | Invoice number | |
| Remark | | | |

MONSTER Certificate of Approval
Product No
Production Time
QC

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| 文件名称 | 魔声XKT22说明书 | | | 材料 | 全书60g书纸+单黑印刷+骑马钉 | 单位 | mm | 厂商物料编号 | 变更履历 | 修改 | | 日期 | |
| 文件尺寸 | 60X90mm（单P尺寸） | | | 工艺 | 1C印刷　风琴折 | 公差 | ± 0.5mm | XXXXXXXXX | | 审核 | | 日期 | |
| 设计日期 | 2023/08/04 | 文件版本 | 2023V04 | | | 比例 | 1:1 | | | 批准 | | 日期 | |