aigo GT8
使用指南
版本V1.0



01 使用前准备

使用前需保证手表电量充足

将手表无线充电器放于手表底部并自动磁吸吸附，即可开始充电，手表屏幕上显示充电指示。

佩戴方式

1. 手表以尺骨茎突后佩戴最佳；
2. 根据调节孔调好适合手腕的大小；扣上腕带扣；
3. 传感器要紧贴皮肤，避免移动。

安装APP- 为蓝牙配对做好准备

下载"Wearfit Pro"APP到手机上并安装，可在APP商城直接搜索"Wearfit Pro进行下载，也可扫描以下二维码跳转连接下载（浏览器、微信等都可扫码）

手机扫二维码
下载Wearfit Pro

02 手表按键功能介绍

A 表冠
长按5秒可开关机

B 功能键

表冠/功能键

1. 时间界面旋转表冠可左右滑动界面。
2. 时间界面单击表冠跳转功能菜单界面。
3. 其他功能界面旋转表冠可上下滑动。
4. 其他功能界面单击表冠返回上一个界面。
5. 功能菜单界面单击两次表冠可切换功能菜单风格。
6. 时间界面点击功能键可跳转支付宝界面。

03 关联设备

首次使用，需连接APP校准，连接成功后手表会自动同步时间

1）APP搜索连接：手机开启蓝牙后，进入APP直接搜索设备进行手动连接。（需手表正常开机）

1）扫码连接：手表开机后进入菜单界面后，下滑进入设置按钮，点击通用按钮，找到"连接手机"按钮并点击，随后左滑连接二维码，在Wearfit Pro内可直接进行扫码连接。

1. 根据上述步骤找到连接手机按钮
2. 手机端使用APP扫码连接

04 连接音频蓝牙

开启蓝牙功能

配对成功后，需在手表端打开通话功能（此开关只有带拨号功能才有）在手机系统蓝牙搜索找到，如：GT8 audios设备并连接，连接成功后即可接听电话和听音乐（注：此功能与APP绑定同步使用）APP会自动保存手表蓝牙地址，APP打开或在后台运行，都会自动搜索并连接手表；

1. 手表端点击蓝牙广播图标
2. 手机端连接蓝牙

05 连接交通卡NFC

1.手机开通支付宝【交通卡】

1）手机打开支付宝APP，点击进入首页上的【出行】按钮。
2）在公交菜单里点击【前往领取】按钮。
3）进入领卡界面，点击【同意协议并领卡】。
4）点击【立即使用】，即可成功开通支付宝交通卡。

2.手表绑定手机支付宝

1）手表上在功能菜单找到【支付宝】按钮并点击进入（需要手机已连接手表）。
2）根据手表的提示步骤操作。
3）直至显示二维码后，打开手机支付宝【扫一扫】即可绑定成功。

3.手表如何使用支付宝交通卡

1）在手表支付宝界面点击【乘车码】
2）点击对应城市卡片后显示相应乘客码。
3）将手表乘车码对准刷卡机。
4）即可完成乘车支付。

4.如何解绑支付宝【乘车码】

手表端解绑
在手表支付宝界面点击【设置】后点击解除绑定即可。
手机端解绑
1）在支付宝APP搜索框中，搜索【智能设备】点击进入。
2）选择需解绑的目标设备。
3）根据提示解除手表与手机支付宝APP的绑定。

06 手表功能介绍

状态栏
1）时间表盘界面向上滑进入状态栏界面。
2）下面快捷按钮可左右滑动查看更多快捷按钮。

蓝牙通话
音频蓝牙连接状态下，进入主菜单拨号盘界面可输入号码直接拨号，如未连接，则不能拨号。

注意事项
音频蓝牙连接状态下，进入通讯录/最近通话可呼出通话，如未连接，则无法呼出，提示未连接。**（注：使用电话薄，需在APP通讯录中同步联系人信息。）**

时间表盘切换
1）时间界面长按3秒调出表盘切换界面，滑动到心仪的表盘点击即可。
2）左滑到底可点击添加时间表盘。

计步
佩戴手表，记录每天运动步数、距离、卡路里可查看当前实时步数。

心率、血氧、血压界面
功能菜单里找到对应的健康测量界面，测量时请佩戴好手表，防止数据有误，检测到皮肤后等待60秒后即会当前结果，此功能需要手表支持传感器。

锻炼（多运动）
功能菜单找到运动界面，选择对应的运动模式此界面下可以记录跑步消耗的卡路里和持续时间，里程数，心率；10多种运动模式显示：时间，里程，卡路里，心率。

信息显示
连接状态下当手表推送多条提醒消息，主界面下滑进入此界面可查看历史消息记录。

睡眠模式
入睡时，手表会自动进入睡眠监测模式；自动检测您整晚深睡/浅睡/清醒次数，计算您的睡眠质量；手表端只显示深睡/浅睡/睡眠总时长，APP端可查看睡眠数据详情。
佩戴手表入睡才有睡眠数据且从晚上10点开始检测睡眠。

语音助手
功能菜单进入语音助手界面，根据提示输入语音指令，即可通过语音助手操控手机，
（注：此功能需连接手机蓝牙，如未连接蓝牙，则无语音输入提示。）

计算器
功能菜单界面点击计算器图标，进入计算器，即可使用手表计算器功能。

天气
主界面左侧左滑至主菜单，进入天气界面，显示当天天气情况与温度，可查看未来几天的天气情况。
（注：此功能需连接手机APP，如未连接，则无天气信息）。

秒表功能
功能菜单界面点击秒表，点击开始按钮开始计时，点击暂停按钮停止，点击重置按钮清除重新计时。

屏幕亮度调节
设置界面找到显示与亮度界面，进入亮度调节界面，点击"-"，"+"可手动调节屏幕亮度，**屏幕亮度会影响续航**

熄屏时间调节
设置界面找到显示与亮度界面，进入熄屏时间调节，上下滑动可选择息屏时间，点击确认即可完成熄屏时间设置；

呼吸训练
功能菜单进入界面点击开始，跟着震动节奏做呼气、吸气训练。

音乐控制
需连接手机端，功能菜单进入音乐控制界面可控制手机的音乐播放暂停、切换歌曲等功能。

关于本机
设置界面找到通用，点击关于按钮，进入显示本机蓝牙名称，蓝牙MAC地址，TP固件版本。

07 APP端功能介绍

表盘市场：
此功能进入可在手机APP上选择推送的表盘，也可以在手机端编辑图片然后推送到手表上。海量表盘需要先在手机端下载方可推送。

来电提醒：
连接状态下，如果开启了来电提醒功能，当有来电时手表上会震动提醒。

其他提醒：（APP通知、久坐、闹钟、达标、喝水）
连接状态下，如果开启了此功能，则当有微信、QQ,Facebook等消息时，手表会震动提醒，并显示app接收到的内容，其它提醒功能打开后，手表会震动提示。

查找手表：
点击此功能，手表端会震动提示，屏幕亮屏。

自动心率检测：
打开此功能后，手表端会自动检测心率，会大幅降低手表续航时间。

应用市场：
内置应用市场，可下载使用更多有趣功能。

智拍功能
连接状态下，从APP端进入遥控拍照界面，摇一摇后手机自动拍照，拍照前请允许APP访问相册以保存照片。

Android用户温馨提示：
使用提醒功能时需要设置为允许"APP"后台运行；建议在权限管理中添加"APP"为信任并打开所有权限。

08 产品参数

产品类型：智能手表
分辨率：412*412
防水等级：IP68
显示屏：1.45寸TFT彩屏
电池容量：270mAh
同步方式：蓝牙
包装清单：主机、表带、充电器、说明书



09 注意事项

1. 洗澡和游泳时不宜佩戴。
2. 同步数据时请连接手表。
3. 使用自带的充电线充电。
4. 不要把手表长时间暴露在水分较高、温度极高或极低的地方。
5. 此设备心率血氧等数据只做参考，不做医疗依据。
6. 血压测试受外界环境及个人肤色等影响，血压监测只作为监测血压高低变化，无法真正测试或监测高血压患者血压，不可作为医疗器械，测试数据不能作为医疗数据，仅供参考。
7. 为何无法推送来电信息或内容
用户首次打开QQ 微信提醒开关的时候，APP会获取相应的权限，勾选APP中的程序，使其获得对应的权限.IOS（来电，短信，QQ，微信）提醒的开关时，系统会自动弹出配对请求，用户只需选择配对即可

10 限用物质说明

限用物质或元素名称及含量标识

部件名称	限用无物质或元素					
	铅Pb	汞Hg	镉Cd	六价铬(VI)	多溴联苯PBB	多溴二苯醚PBDF
表壳	0	0	0	0	0	0
电池	0	0	0	0	0	0
显示屏	0	0	0	0	0	0
PCB	X	0	0	0	0	0

本表格依据ST/T 11364的规格编织。
0：表示该限用物资物质在部件所有物质材料中的含量均为GB/T 26572-2011 规定的限量要求以下。
X：表示该限用物质至少在该部件的某一物质材料中的含量超出GB/T 26572-2011规定的限量要求。
（企业可以在此处，根据实际情况对表中大"X"的技术原因进一步说明）

aigo GT8
Instruction manual
V1.0



01 Preparation before use

It is required to ensure that the electricity of the meter is fully charged before using the battery

Put the wireless charger at the bottom of the watch and automatically absorb the magnetic magnet to start charging. The charging instruction will be displayed on the screen of the watch.

Wearing type

1. It is best to wear the meter after the styloid process;
2. According to the adjusting hole, adjust the suitable flange; Buckle the wrist strap;
3. The sensor should be close to the skin to avoid moving.

Install APP- Get ready for Bluetooth pairing

Download the "Wear fi tPro" APP to the PC and install it. You can directly search for "Wear fi tPro" in the APP store and download it. You can also scan the following dimension code to jump to the connection and download (browser, WeChat, etc. can scan the code)

Download Wear tPro
by scanning the dimension code

02 Function description of watch keys

A Crown
Long press for 5 seconds to switch on/off

B Function keys

Crown/function key

1. Time screen Rotate the crown to slide the screen left and right.
2. On the Time screen, click the Redirect menu.
3. Other functions: Rotate the crown to slide up and down.
4. Other Functions Click the crown to return to the previous screen.
5. Function Menu interface Click the crown twice to change the menu style.
6. Time interface Click the function key to jump to Alipay interface.

03 Associated Devices

For the first time, connect the APP for calibration. After successful connection, the meter will automatically synchronize the time

1) APP search connection: After the mobile phone is turned on, enter the APP to directly search the device for mobile connection. (The meter shall be started normally)

2) Code scanning connection: After the meter is turned on, enter the menu interface, slide down to enter the setting button, click the "Connect" button, find the "Connect" button and click it, then slide left to connect the "Scan" code, and directly enter the "Scan" code connection in WearfitPro.

1. Follow the above steps to find the connection button
2. Use the APP to scan the code for connection on the mobile phone

04 Connect the audio blue

Enable the blue button function

After the pairing is successful, you need to turn on the call function at the meter end (this switch is only available with the dialing function) and find it in the blue screen of the phone system. For example, the GT8audios device is connected and connected. After the connection is successful, you can answer the call and listen to music (Note: this function is synchronized with the APP binding to enable the blue screen). The APP will automatically save the blue screen address. When the APP is opened or running in the background, it will search and connect the blue screen;

1. Click the blue play icon at the meter end
2. Connect the mobile phone to Bluetooth

05 Connect the traffic card NFC

1. Open Alipay [transportation card] on mobile phone

1) Open the Alipay APP and click the "Travel" button on the home page.
2) Click the "Go to Collect" button in the bus menu.
3) Enter the card interface and click "Agree to the Agreement and accept the Card".
4) Click "Use Now" to successfully open the Alipay transportation card.

2. The watch is bound to mobile Alipay

1) On the watch, find the "Alipay" button in the function menu and click to enter (the phone needs to be connected to the watch)
2) Operate according to the instructions of the watch.
3) Until the two-dimensional code is displayed, open the mobile phone Alipay [scan] can bind successfully.

3. How to use Alipay traffic card for watch

1) Click [Boarding Code] on watch Alipay interface
2) Click the corresponding city card to display the corresponding passenger code.
3) Align the bus code of the watch with the card reader.
4) You can pay by bus.

4. How to unbind Alipay [boarding code]

Unbinding of watch end
Click [Set] on the watch Alipay interface and then click unbind.
Unbinding mobile phone
1) In the Alipay APP search box, search [Smart Device] and click to enter.
2) Select the target device to unbind.
3) Release the binding of the watch and Alipay APP according to the prompt.

06 Watch Function Introduction

status bar
1) The time table interface slides up to enter the status bar interface.
2) The following shortcut buttons can be swipe left and right to view more shortcut buttons.

Bluetooth call
In the audio Bluetooth connection status, enter the dial interface of the main menu to enter the number for direct dialing. If it is not connected, you cannot dial.

matters needing attention
In the audio Bluetooth connection status, you can call out by entering the address book/recent calls. If not connected, you cannot call out, and the prompt is not connected. (Note: To use the phone book, you need to synchronize the contact information in the APP address book.)

Time table switch
1) In the time interface, long press for 3 seconds to call up the dial switch interface, slide to the desired dial and click.
2) Slide left to the bottom to click Add Timetable.

Step counting
Wear a watch and record the steps, distance and calories of daily exercise to view the current real-time steps.

Heart rate, blood oxygen and blood pressure interface
The corresponding health measurement interface is found in the function menu. Please wear your watch when measuring to prevent data errors. After skin detection, wait 60 seconds for the current result. This function requires the watch to support the sensor.

Exercise (more exercise)
Find the sports interface from the function menu, and select the corresponding sports mode. In this interface, you can record the calories consumed and the duration, mileage, and heart rate; 10 kinds of sports modes display: time, mileage, calories, heart rate.

information display
When the watch pushes multiple reminder messages in the connected state, the main interface slides down to this interface to view the history message record.

Sleep mode
When falling asleep, the watch will automatically enter the sleep monitoring mode; Automatically detect your times of deep sleep/shallow sleep/awake throughout the night, and calculate your sleep quality; The watch end only displays the total duration of deep sleep/shallow sleep/sleep, and the APP end can view the details of sleep data.
Sleep data is available only when you wear a watch to sleep, and sleep detection starts at 10 pm.

Voice Assistant
In the function menu, enter the voice assistant interface, and input voice commands according to prompts. You can control your phone through the voice assistant,
(Note: This function needs to be connected to the Bluetooth of the mobile phone. If the Bluetooth is not connected, there will be no voice input prompt.).

Calculator
Click the calculator icon in the function menu interface, enter the calculator, and you can use the watch calculator function.

weather
On the left side of the main interface, slide left to the main menu to enter the weather interface, where the weather conditions and temperature of the day are displayed, and you can view the weather conditions in the next few days.
(Note: This function needs to be connected to the mobile phone APP. If not, there is no weather information).

Stopwatch function
In the function menu interface, click the stopwatch, click the Start button to start timing, click the Pause button to stop, and click the Reset button to clear the re timing.

Screen brightness adjustment
Find the display and brightness interface in the setting interface, enter the brightness adjustment interface, click "", "+" to manually adjust the screen brightness, which will affect the endurance

Screen out time adjustment
Find the display and brightness interface in the setting interface, enter the screen out time adjustment, slide up and down to select the screen out time, and click OK to complete the screen out time setting;

Respiratory training
In the function menu, enter the interface, click Start, and do breath out and breath in training with the vibration rhythm.

Music control
It is required to connect the mobile phone, and the function menu can enter the music control interface to control the functions of the mobile phone, such as music playing pause, switching songs, etc.

About this computer
Find Universal in the setting interface, click the About button, and enter to display the local Bluetooth name, Bluetooth MAC address, and TP firmware version.

07 Function introduction of APP end

Dial Market:
In this function, you can select the dial pushed on the mobile app, or edit the picture on the mobile terminal and then push it to the bracelet. Massive dials need to be downloaded on the mobile terminal before they can be pushed.

Call reminder:
In the connected state, if the incoming call reminder function is enabled, the bracelet will vibrate when there is an incoming call.

Other reminders: (APP notification, sedentary, alarm clock, up to standard, drinking water)
In the connected state, if this function is enabled, when there are wechat, QQ, Facebook and other messages, the watch will shake the reminder and display the content received by the app. When other reminder functions are enabled, the watch will shake the reminder.

Find Watch:
Click this function, the watch end will vibrate and the screen will light up.

Automatic heart rate detection:
After this function is turned on, the watch end will automatically detect the heart rate, which will greatly reduce the life time of the bracelet.

Application market::
Built in application market, you can download and use more interesting functions.

Smart beat function
When connected, enter the remote camera interface from the app end. After shaking, the mobile phone will automatically take photos. Before taking photos, please allow the app to access the album to save the photos.

Tips for Android users:When using the reminder function, it needs to be set to allow "app" to run in the background; It is recommended to add "app" as trust in permission management and open all permissions.

08 Product parameters

Product type: smart Watch
Resolution: 412*412px
Waterproof grade: Ip68
Display screen: 1.45 inch TFT screen
Battery capacity: 270mah
Synchronization mode: Bluetooth
Packing list: host, watch strap and charging line, instructions



09 NOTE

1. It should not be worn when taking a hot bath or swimming for a long time.
2. Please connect the watch when synchronizing data.
3. Use the self-contained charging cable to charge.
4. Do not expose the watch to high moisture, high temperature or low temperature for a long time.
5. The heart rate, blood oxygen and other data of this equipment are only for reference, not for medical reference.
6. The blood pressure test is affected by the external environment and personal skin color. The blood pressure monitoring is only used to monitor the changes of blood pressure, and cannot really test or monitor the blood pressure of hypertensive patients. The test data cannot be used as medical data, and is only for reference
7. Why can't you push the incoming call information or contentWhen the user turns on the QQ wechat reminder switch for the first time, the app will get the corresponding permission. Check the program in the app to get the corresponding permission When IOS (incoming call, SMS, QQ, wechat) reminder is turned on and off, the system will automatically pop up a pairing request, and the user only needs to select pairing.
8. The final interpretation right belongs to the brand,

10 Description of restricted substances

Name and content identification of restricted substances or elements

parts name	Restricted use: no substance or element					
	lead	mercury	cadmium	cr6	PBB	PBDF
watchcase	0	0	0	0	0	0
Battery	0	0	0	0	0	0
display	0	0	0	0	0	0
PCB	X	0	0	0	0	0

This table is woven according to the specification of St / T 11364.
0:indicates that the content of the restricted materials in all materials of the parts is below the limit specified in GB / T 26572-2011。
X:It indicates that the content of the restricted substance in at least onesubstance material of the component exceeds the limit specified in GB / T 26572-2011.
(the enterprise can further explain the technical reasons for the large "X" in the table according to the actual situation here.)

FCC Caution:
This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.
NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.
If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.