

Works with Apple Find My GetsISKON[®] Gets Card Function Button		Getting Started01 1. Power On/ Off: · Locate the button on the front of the Gets Card. Press the button once to tum it on. it should a ringing chime indicating it is powered on · Locate the button on the front of the Gets Card.Press and hold the button for 3 seconds until 2 beeps are heard. 2. Check For Updates: · To use the Apple Find My app to locatel Gets Card the latest version of iOS, iPadOS, or macOS is recommended. The Find items app on Apple Watch requires the latest version of watchOS.	Add Your "Gets Card "02 1. Start the App · Open Find My app on your supported iPhone* or iPad · Allow notifications from the app 2. Connect your Gets Card · Power on your Gets Card · Tap "+" then "Add Other Item" · Once your Gets Card is located, tap "Connect" · Choose a recognizable name and emoji for your Item Locator and tap "Continue" · Find My will ask for confirmation to add your Gets Card to your Apple ID - tap "Continue" · Lap "Finish" and your Gets Card will be set up and ready to be connected to whatever item you wish to locate, e.g., your keys	Locate Your Item03 1. Find Gets Card when it is Nearby · Open Find My app and select the "Items" tab or open the Find Items app on your Apple Watch · Tap on your Gets Card from the list · Tap "Play Sound" to make your Gets Card beep · Tap "Stop Sound" to stop the beeps once you find your item 2. Find Gets Card's Last Known Location · Open Find My app and select the "Items" tab or open the Find Items app on your Apple Watch · Tap on your Gets Card from the list · Our Gets Card's last known location will appear on the map · To navigate to that last known location, tap "Directions" to open the Maps app	Find Item When Out of Range04 1. Enabling "Notify When Left Behind" · Open Find My app and select the "Items" tab or open the Find Items app on your Apple Watch · Tap on your Gets Card from the list · Under "Notifications", enable the "Notify When Left Behind" toggle · You will receive a notification when you leave your Gets Card behind and it's no longer in range of your device. 2. Enabling "Notify When Found" · Under "Notifications", enable the "Notify When Found" toggle · When your Gets Card is seen by another Find My enabled device, you will receive a notification of its updated location · Note: "Notify When Found" can only be activated when your Gets Card is out of range	How to deal with device loss05 1. Enabling lost Mode · Open Find My app and select the "Items" tab or open the Find Items app on your Apple Watch · Lap on your Gets Card from the list · Under "Lost Mode", tap "Enable" · A screen detailing Lost Mode will pop up, tap"Continue" · Enter your phone number or email address and tap "Next" · You may enter a message that will be shared with the person that finds your item · Tap "Activate" to enable "Lost Mode" · Note: When "Lost Mode" is enabled, "Notify When Found" is automatically enabled · Note: When "Lost Mode" is enabled, your Gets Card is locked and cannot be paired to a new device	Resetting Your Gets Card06 1. Remove the Gets Card from Find My app · Open Find My app and select the "Items" tab · Tap on your Gets Card from the list · Please ensure "Lost Mode" is disabled · Scroll to the bottom of the screen and tap "Remove Item" · A summary will open, tap "Remove" to confirm 2. Factory Reset Your Gets Card: · After successfully removing the Gets Card from Find My app, press the button four times rapidly and then hold it a fifth time until you hear a ringing chime. · The Gets Card is now reset and ready to be paired to a new Apple ID.																									
Gets Card Product Specification07 <table><tr><td>1. PPID No</td><td>312215-364550</td></tr><tr><td>2. Product Size</td><td>54 x 85.6 x 1.8mm/2.12 x 3.37 x 0.07 inch</td></tr><tr><td>3. Product Weight</td><td>12.5g / 0.441 oz</td></tr><tr><td>4. Battery</td><td>Built in battery (Li-MnO2 Thin cell (Disposable)</td></tr><tr><td>5. Voltage</td><td>DC 3V</td></tr><tr><td>6.Current</td><td>≤5uA(Standby) / ≤10mA(Max)</td></tr><tr><td>7. Wireless</td><td>BLE 5.2</td></tr><tr><td>8.Wireless range</td><td>≥40m (Line-of-sight)</td></tr><tr><td>9. Buzzer</td><td>100db</td></tr><tr><td>10. Temperature</td><td>-5°C -- 45°C (23°F -- 113°F)</td></tr><tr><td>11. Humidity Range</td><td>≤95% (Non-condensing)</td></tr><tr><td>12.Color Box Size</td><td>75mm x 12mm x 108mm</td></tr><tr><td>13. Product Certification</td><td>FCC / RoHS / CE</td></tr></table>	1. PPID No	312215-364550	2. Product Size	54 x 85.6 x 1.8mm/2.12 x 3.37 x 0.07 inch	3. Product Weight	12.5g / 0.441 oz	4. Battery	Built in battery (Li-MnO2 Thin cell (Disposable)	5. Voltage	DC 3V	6.Current	≤5uA(Standby) / ≤10mA(Max)	7. Wireless	BLE 5.2	8.Wireless range	≥40m (Line-of-sight)	9. Buzzer	100db	10. Temperature	-5°C -- 45°C (23°F -- 113°F)	11. Humidity Range	≤95% (Non-condensing)	12.Color Box Size	75mm x 12mm x 108mm	13. Product Certification	FCC / RoHS / CE	More Information08 Unwanted Tracking Detection: If any Find My network accessory is separated from its owner and moves with you over time, you will be notified in one of these two ways: (1) If you have an Apple device, Find My will send a notification to your Apple device. This feature is available on devices running iOS 14.5 or iPadOS 14.5 or later. (2) If you do not have an Apple device, the Find My network accessory will automatically make a sound after a period of time. These features were created specifically to emit a person from trying to track you without your knowledge.	Warning09 ⚠ CAUTION: The battery used with Gets Card should be kept away from small children. If your kid swallows a battery, promptly see a doctor. In the U.S., have the doctor phone (202) 625-3333 collect (if you want to know more about button battery, please call 1-800-222-122), or, in Canada, have the doctor call your provincial Poison Control Centre. IMPORTANT: BATTERY IMFORMATION Please retain this information for future reference. Batteries should be replaced by an adult.	Warning10 ⚠ CAUTION: · Always follow the instructions carefully. The device is only compatible with CR2032 battery. Use only battery specified and be sure to insert it correctly by matching + and - polarity markings. · Do not mix old battery and new battery. · Always remove exhausted or dead battery from this product. Battery leakage and corrosion can damage this product. · Remove battery during long periods of non-use. · Never short circuit the battery terminals. · Do not recharge, disassemble, hole, heat, burn or damage the battery. · Do not use sharp objects to remove the battery. · Do not dispose the battery in a fire. The battery may explode or leak. · Store the product in cool and dry environment. · The battery should be kept away from children. If swallowed, seek medical attention immediately.	Compliance11 EU Disposal Information: The above symbol indicates that according to local laws and regulations, your product and/or its battery should be disposed of separately from household waste. At the end of the product's service life, take it to the designated collection point authority in the local area. Disposal time will help protect natural resources and ensure that they are recycled in some way to protect human health and the environment. The Apple Find My network provides an easy, secure way to locate compatible personal items using the Find My app on your iPhone, iPad, Mac, or the Find Items app on Apple Watch. Any Changes or modificationsnot expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1)This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.	Compliance12 FCC Statements (United States Only): This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures: -Reorient or relocate the receiving antenna. -Increase the separation between the equipment and receiver. —Connect the equipment into an outlet on a circuit different from that to which the receiver is connected. -Consult the dealer or an experienced radio/TV technician for help. FCC Radiation Exposure Statement: This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment . This transmitter must not be co - located or operating in conjunction with any other antenna or transmitter.	Statements13 Use of the Works with Apple badge means that a product has been designed to work specifically with the technology identified in the badge and has been certified by the product manufacturer to meet Apple Find My network product specifications and requirements. Apple is not responsible for the operation of this device or use of this product or its compliance with safety and regulatory standards. Apple, Apple Find My, Apple Watch, Find My, iPhone, iPad, iPadOS, Mac, macOS and watchOS are the trademarks of Apple Inc. IOS is a trademark or registered trademark of Cisco in the U.S. and other countries and is used under license. The device has been tested and complies with FCC SAR limits. Account ID: 312215 Manufacturer: DongGuan Kensway Photoelectric Technology Co., Ltd. Address: Room 418, Floor 4, Building 6, No. 36, Fuxing Road, Chang'an Town, Dongguan City, Guangdong Province, China
1. PPID No	312215-364550																															
2. Product Size	54 x 85.6 x 1.8mm/2.12 x 3.37 x 0.07 inch																															
3. Product Weight	12.5g / 0.441 oz																															
4. Battery	Built in battery (Li-MnO2 Thin cell (Disposable)																															
5. Voltage	DC 3V																															
6.Current	≤5uA(Standby) / ≤10mA(Max)																															
7. Wireless	BLE 5.2																															
8.Wireless range	≥40m (Line-of-sight)																															
9. Buzzer	100db																															
10. Temperature	-5°C -- 45°C (23°F -- 113°F)																															
11. Humidity Range	≤95% (Non-condensing)																															
12.Color Box Size	75mm x 12mm x 108mm																															
13. Product Certification	FCC / RoHS / CE																															