



Smart Baby Monitor
User Manual



Safety

☐ **WARNING:** Strangulation Hazard—Children have STRANGLED in cords. NEVER attempt to use cord without the protective covering. Check protective covering before each use to ensure that the cord is not exposed to your child. Immediately discontinue use if protective covering is damaged or broken.

- This device is designed to be mounted behind a standard crib and against the wall.
- Adult assembly is required.Keep small parts away from children when assembling.
- This product cannot replace adult supervision. Ensure your child’s health by checking on him/her regularly.
- This device is designed for indoor use only.
- This product and its packaging are not toys. Do not allow children to play with them.
- Falling warning---In order to prevent products fell to hurt, be sure to install the monitor in a stable location, tighten the screws, securely monitor your device.
- Make sure the camera could capture the baby’s facial image clearly after the installation.
- This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful

interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

- NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

- This equipment must be installed and operated in accordance with provided

instructions and the antenna(s) used for this transmitter must be installed to provide a separation distance of at least 8” (20cm) from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. End-users and installers must be provide with antenna installation instructions and transmitter operating conditions for satisfying RF exposure compliance.

- To comply with FCC RF exposure compliance requirements, the antenna used for this transmitter must be installed to provide a separation distance of at least 8” (20cm) from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter.”

Installation

Position your crib against the wall where you will mount Cheego Camera. Be sure to check that there are no studs in the center of the crib and that the power outlet is out of your child's reach.

1. Using the included Mounting Template, find the 20" (50cm) position from the headboard of the crib and mark it (as①) on your wall.

Once complete, move the crib out of your way.

2.Pull straight and vertical the Mounting Template, then align with the mark ①. Once in position, make a mark on your wall at 60" (150cm)(as②).

3. Align the screw holes at the lowest part of the mounting bracket(mark②) then adjust it using the built-in level. Once level, mark the wall through the two top holes in the bracket(as③④).

4.Drill 1/4" (6mm) holes in the three marked spots(②③④).

5.Insert three anchors until flush with wall.

6.Align the mounting bracket with the three anchors, and insert screws into the anchors and screw in halfway.

7.Adjust the Mounting Bracket using the built-in level. Once level, tighten the three screws.

8.Place Cheego Camera over Mounting Bracket and press it down until it clicks.

9.Organize the power cable, peel the tape backing off the Cable Covers, and firmly adhere the bottom of the cable covers to the wall.

Connect the power cable with the DC Power Adapter, plug the power adapter into your outlet. Make sure that the power outlet you use is not within your child's reach.

INSTRUCTIONS

Get start Cheego Smart app

Download the Cheego Smart App from Apple Store or Google Play. Or scan the QR code on the device or in user guide.



Download & Register
“Cheego Smart” APP

Boot

Please connect the camera with the power adapter. And the LED light will be automatically turned on and off.

Please wait about 35 seconds before the device boot up successfully.

GET START CHEEGO SMART APP

- ☐ Cheego Smart APP will upgrade and update. The actual operation may be different from the above description. Please follow the instructions in the current version.
- ☐ When connecting, please keep the network good and the monitor turned on.

**CHEEGO SMART APPLICATION
SETUP GUIDE**

- Download the Cheego Smart App and set up your account.

- Follow the in-app instructions to set up your Cheego Smart Camera. Choose:

Homepage > Add your device > Scan QR code to connect>Pair succeed> Choose installation way> Choose installation position

- You can choose to follow the assembly instructions in-app or in this booklet.

FEATURES INTRODUCTION

Live Video And Two-Way Audio

Cheego 3MP ultra HD camera and high-quality speaker provide a fantastic connection with your baby anywhere and anytime.

Crying Detection& Soothing Music

Cheego baby monitor automatically plays soothing musics& turns on the night lamp (at night), and sends alarm messages to the APP when it detected baby's crying.

Sleep Nanny

Cheego captures and analyzes baby's sleep with AI technology in real time, and sends alarm messages to the APP if your baby wakes up.

Moments

Cheego uses an advanced algorithm to capture photos and videos of baby's wonderful moments. Record your baby's precious time.

Virtual Fence Detection

Cheego sends instant notifications through the APP when the baby is out of the virtual fence.

Danger Zone Detection

Set the electronic area as the danger zone, when baby enters the danger zone, Cheego provides voice warning and sends alarm messages to the APP.

Temperature and Humidity Detection

Embedded high precision temperature& humidity sensor, Cheego checks the room temperature and humidity in real time to make baby more comfortable..

Non-Invasive Night Vision

Non-invasive infrared sensor makes clear vision in the dark.

SPECIFICATIONS

Model	X3 Pro
Resolution	1296P
Lens	f≈3.2mm / F1.6
Field of View	130° (Diagonal)
Connectivity	Wi-Fi 2.4GHz/5GHz 802.11a/b/g/n
Support System	Android 11.0 or IOS 13.0 or above
TF card	32GB
Mounting	Wall Mount (Standard Package)
	Floor Stand Mount (Need to Purchase a Replacement Floor Stand)
Power	DC12V / 1A
Working Temperature	0-40℃
Dimensions	90X90X215mm
Item Weight	420g

FAQ

I don't hear the connection succeeded when I scan QR code

QR code cannot be recognized, the possible reasons are as follows:

- 1). Screen is too dark
- 2). Too far or too close from the lens
- 3). Reflection

Suggestions:

- 1). The phone screen is facing the lens
- 2). Adjust phone screen brightness
- 3). Adjust the distance between the phone and the lens

What should I do if the camera goes offline (device icon gray)?

Suggestions:

- 1). Shut down and reboot your device
- 2). If the Wi-Fi was changed, please follow the RESET instruction to reset your camera.

What should I do if I can't connect my device after the upgrade?

The possible reasons are as follows:

- 1). Check the WiFi network
- 2). Shut down and reboot your device
- 3). Re-setup the device (After the device is powered on, scan reset QR code within ten minutes) , rebind the device.

What should I do if the call has an echo?

When making a call, please try to keep the mobile phone more than 10 meters away from the device. The echo and howling caused by the short distance call is a normal phenomenon.

What should I do if mobile phone cannot receive the notification?

Go to mobile “setting”→“Cheego smart”→“Allow notification”

How to RESET the camera?

press the RESET button on the camera with 5 seconds, click "Reset Device Step by Step" in Cheeg Smart APP, then do it step by step.

GUARANTEE & WARRANTY

**SATISFACTION
GUARANTEE & RETURN
POLICY**

Thank you for purchasing Cheego products. If you are not completely satisfied with your purchase, you may return the product for a full refund within 30 calendar days of setting up a hardware product (icheego.com) or within 15 days of activating an online product (Cheego authorized online reseller). This satisfaction guarantee requires proof of purchase from an authorized seller. Purchases from 3rd party retailers will need to be returned to the original place of purchase.

LIMITED WARRANTY

This limited warranty contains important information about your rights and obligations, as well as limitations and exclusions that may apply to you.

This limited warranty only applies if you are the original purchaser, use and operate the product in the United States or Canada. Please note if you are not resident of the United States or Canada, this Limited Warranty & Return Policy does not apply to you.

**PRODUCTS OBTAINED FROM
UNAUTHORIZED RETAILERS
ARE NOT COVERED BY THIS
LIMITED WARRANTY.**

Please be aware that there are some retailers and websites that claim to be authorized retailers of Cheego when they are not. Note that when you purchase from these

unauthorized retailers, you are taking a risk, including a risk that these products are used or defective, and this limited warranty will not apply.

1. WHAT THIS LIMITED WARRANTY COVERS?
PERIOD OF COVERAGE.

Warrants to the owner of the enclosed product that the product contained in this box (“Product”) will be free from defects in materials and workmanship for a period of one (1) year from the date of delivery following the original retail purchase (the “Warranty Period”). If you believe you have received a defective product, we will either repair or replace the defective product or its defective component part(s) in accordance with the terms of this limited warranty. We warranty replacement for the remaining unexpired period of the original product’s warranty. This limited warranty is the only warranty available for our products.

2. WHAT THIS LIMITED WARRANTY DOES NOT COVER?

- Products marked as “sample” or “Not for Sale”, or sold “AS IS”;
- Ineligible Products that have been subject to:
 - (a) Modifications, alterations, tampering, or improper maintenance or repairs;
 - (b) Handling, storage, installation, testing, or use not in accordance with the Terms of Service or other instructions provided by Cheego;
 - (c) Abuse or misuse of the Product;
 - (d) Damages caused by Acts of God, including but not limited to

lightning, flood, tornado, earthquake, or hurricane;

- Consumables parts, including but not limited to batteries, unless damage is due to defects in materials or workmanship of the product;
- You use unauthorized service providers for maintenance or repair;
- Unauthorized use of the Product or software can impair the Product’s performance;
- This limited warranty does not warrant to covered any software, even if packaged or sold with the Products;
- Refer to the licensing agreement accompanying the software for details of your rights with respect to its use;
- This limited warranty does not warrant that the operation of the product will be uninterrupted or error-free;
- This warranty cannot be transferred from the original end-user to others for any such transfer.

3.NOT A MEDICAL DEVICE.
The products are not medical devices and are not intended to be used as a medical devices.

4.DISCLAIMER OF WARRANTIES.
EXCEPT AS STATED ABOVE IN SECTION 1 OF THIS LIMITED WARRANTY, AND TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, CHEEGO DISCLAIMS ALL EXPRESS, IMPLIED, AND STATUTORY WARRANTIES AND CONDITIONS WITH RESPECT TO THE PRODUCT, INCLUDING THE IMPLIED

WARRANTIES OF
MERCHANTABILITY,
FITNESS FOR A PARTICULAR
PURPOSE AND
NON-INFRINGEMENT. TO THE
MAXIMUM EXTENT
PERMITTED BY APPLICABLE
LAW, CHEEGO ALSO LIMITS
THE DURATION OF ANY
APPLICABLE IMPLIED
WARRANTIES OR
CONDITIONS TO THE
DURATION OF THIS LIMITED
WARRANTY.FOR THE
AVOIDANCE OF DOUBT,
NOTHING IN THIS CLAUSE 6
IS INTENDED TO EXCLUDE
ANY WARRANTIES OR
GUARANTEES WHICH
CANNOT BE EXCLUDED
UNDER APPLICABLE LAWS.

**5.YOUR RIGHTS AND THIS
LIMITED WARRANTY.**
WE LIMIT THE
APPLICABILITY OF IMPLIED
WARRANTIES, INCLUDING
THE IMPLIED WARRANTIES
OF MERCHANTABILITY AND
FITNESS FOR A PARTICULAR
PURPOSE, TO THE DURATION
OF THIS LIMITED
WARRANTY. TO THE EXTENT
PERMITTED BY LAW, WE
DISCLAIM ALL OTHER
WARRANTIES OF ANY KIND.
SOME STATES AND
COUNTRIES DO NOT ALLOW
LIMITATIONS ON IMPLIED
WARRANTIES, SO THE
ABOVE LIMITATION MAY
NOT APPLY TO YOU. OUR
SOLE LIABILITY FOR ANY
DEFECT SHALL BE AS SET
FORTH IN THIS LIMITED
WARRANTY AND EXCLUDES
ANY CLAIMS FOR
INCIDENTAL OR

CONSEQUENTIAL DAMAGES.
SOME STATES AND
COUNTRIES DO NOT ALLOW
THE EXCLUSION OR
LIMITATION OF INCIDENTAL
OR CONSEQUENTIAL
DAMAGES, SO THE ABOVE
LIMITATION OR EXCLUSION
MAY NOT APPLY TO YOU. NO
PERSON OR ENTITY IS
AUTHORIZED TO MAKE ANY
OTHER WARRANTY ON OUR
BEHALF. THIS WARRANTY
GIVES YOU SPECIFIC LEGAL
RIGHTS. YOU MAY ALSO
HAVE OTHER RIGHTS WHICH
VARY FROM STATE TO
STATE AND COUNTRY TO
COUNTRY.

COMPLIANCE

DECLARATION OF CONFORMITY

Hereby, Hangzhou Cheego Technology Co., Ltd. Room 603, Bldg. E2, 3# Xiyuan 8 Road, Hangzhou, 310030, China, declares that the equipment Model CCA3 is in compliance

with Directive 2014/53/EU.

PRODUCT USE WARNING

This product is meant for indoor use only.

RADIO FREQUENCY (RF) EXPOSURE STATEMENT

This equipment should be installed and operated with a minimum distance of 20 cm between the camera and the human body.



This symbol means the product must not be discarded as household waste, and should be delivered to an appropriate collection facility for recycling. Proper disposal and recycling helps protect natural resources, human health and the environment. For more information on disposal and recycling of this product, contact your local municipality, disposal service or the shop where you bought this product.

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment. This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment should be installed and operated with minimum distance 20cm between the radiator&your body.



www.icheego.com
support@icheego.com