



Charging Case Battery Display

L-Battery Display

R-Battery Display

LED Indicator

Earbuds Charging Pins

Type-C Input

LED Indicator

LED Indicator

The diagram illustrates the components of the charging case and earbuds. The top part shows the open charging case with a central digital display showing '100'. On either side of the display are two circular battery level indicators, labeled 'L-Battery Display' and 'R-Battery Display'. Below the display is a small LED indicator. The bottom part shows the earbuds, each with a circular LED indicator and a Type-C input port. The earbuds are labeled 'LED Indicator' and 'Type-C Input'.

1. The earbuds will turn off when they're put into the case, they'll play "power off" sound and the lights will turn red for 1s. Then the earbuds will start charging.
2. In charging status, the LED indicators keep staying red, and when the charging is finished, the LED indicators will turn to blue for 5s and then turn off.

1. At the first time you use the earbuds, please put them into the charging case and then take out, they'll turn on automatically, connect to each other and turn into pairing mode.
2. In the pairing mode, in which the lights flash red and blue alternately, you can find the pairing name [KITONE Freego X01] on the bluetooth devices list, select it to pair with the earbuds.
3. When the pairing with a new device done, the earbuds will play "Pairing succeed" and "Your headset is connected" sounds.
4. Next time when the earbuds turn on, they'll connect the last connected device automatically. If the device won't be found, the earbuds will turn into the pairing mode again.

	Power On	Press and hold (L/R) for 3s. (Not in charging status)
	Power Off	Press and hold (L/R) for 5s. (No calling or music playing)
	Play/Pause	Single tap (L/R)
	Previous Track	Double tap (L)
	Next Track	Double tap (R)
	Volume Up	Press and hold (R). (When music playing or in a call)
	Volume Down	Press and hold (L). (When music playing or in a call)
	Answer Call	Single tap (L/R)
	End Call	Single tap (L/R)
	Reject Call	Press and hold (L/R) for 2s
	Voice Assistant	Triple tap (L/R) (when connected to cellphone)
	Factory Reset	Triple tap (L/R) in pairing mode

Pairing Name	KITONE Freego X01
Bluetooth Version	5.0
Waterproof	IPX6
Play Time	5.5 hours(varies by volume)
Call Time	5 hours
Charging Time(Earbud)	1.5 hours from 0% to 100%
Charging Time(Case)	2 hours from 0% to 100%
Battery(Earbud)	3.7V/60mAh
Battery(Case)	3.7V/500mAh
Type-C Input	5V/0.5A
Connection range	10m/33ft

Do not always use loud volume.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.