

385mm

55mm

95mm

True wireless stereo headset

JT05

JT05 user manual

Getting Started:

Power on

A. Bluetooth headset is automatically turned on when it is removed from the charging box.

B. Under turning off state, long press the Multi-function Button(MFB) for about 3 seconds until the indicator flashes blue for 1 second with the "power on" warning tones.

Ear hook

Charging Case

Fitting and Wiring

Gently push the earbud into your ear and adjust the headsets to get a comfortable fit.

Ear tips in different sizes

S

M

L

Pairing

Two headphones pairing:

After power on, these two headphones will enter automatic pairing mode,(During the pairing period, the two headphones will flash slowly alternately red and blue light,when they are connected successfully, both earphones will flash blue light.

Mobile phone and Bluetooth headset pairing:

Activate the Bluetooth function of your mobile phone, search and select "JT05_L" or "JT05_R" from the devices list to connect.When left or right earbud connect cellphone successfully, the other side earbud will send a pairing massage to cellphone to connect the other earbud.

Charging

The Bluetooth headset is charged with charging box. When charging, the red LED of the Bluetooth headset is always on. When the battery is fully charged, the blue light is on for 30 seconds and then light off.

Front

Back

Charging/discharging of charging box

The charging box has an indication of percentage of charge when charging and discharging

Charging status:

charge the charging box with DC5V

- When the cover of the charging box is pushed away, the indicator light of the charging box is on, and the four lights from left to right correspond to 0-25%, 25%-50%, 50%-75%, 75%-100% of the power;the light is on, that's the battery charge of the corresponding charging box.
- When the cover of the charging box is pushed away, the battery indicator light of the charging box will go out 3 seconds after the headset is taken out .
- Once earbuds were put back to charging case, both earbuds will be charged.

General Function

Answer a call

When there phone call comes, the headset sends out a ringtone. Touch the earphone's surface one timeto answer the call, or use the key on the phone to answer.

Ring off

During phone call,short press the MFB or use the key on the phone to hang up the call.

Power off

Long press any headphone surface for about 7 seconds, and two interconnected devices will be closed at the same time.
Automatic shutdown: put the Bluetooth headset in the charging box, and the earphone will turn off.

Stand-alone (mono audio) :

Streaming music with single-ear wearing or on phone call

TWS(TRUE WIRELESS STEREO):

Playing music without wirele, with stereo hifi sound.

Play/Pause

When playing songs, Touch the earphone once to pause, and touch again to play.

SIRI function

When the SIRI Function is connected, touch the earphone's surface 2 times to activate SIRI Function.

Last song & Next song

Long press the right eaphones 2 seconds to switch to the Previous song.

Long press the left eaphones 2 seconds to switch to the next song.

Factory reset

When the earphone is power on, pressing both side headph-one power on buttons at the same time for 8 seconds until the indicator flashes blue and red for 1 second, then the headset will clear the pairing information and power off. Then turn on the earphones, they will become pairing mode.

Product Featrues

V5.0 bluetooth version,compatible with over 99% of mobile phones and tablets.

Basic parameters

Bluetooth version:V5.0
Charging Time: 1-2 hours
Battery capacity: Lithium battery 60 mAh
Charging case Indicator light: 4 blue lights
Charging cable: Type-C
Bluetooth Profile: A2DP/HFP/AVRCP/SPP
codec:SBC/AAC/aptX
Working Time: 3 hours x 6 times
Sensitivity: 95dB/1mW
Wireless Range: more than10m
Max. input power: 5mW
Input impedance: 32Ω
Rated power: 3mW
Ear hook size: 48*38*30 mm
Charging case size: 76*69*42mm
Earbuds capacity: 60 mAh
Frequency range: 100Hz-10KHz

Notes:

Playtime varies according to volume level and audio content
For after-sales support,please contact our customer service with your order ID.

Warranty Terms & Conditions

- The warranty period of the product is one year. In the warranty period, if the product fails, The company provides free repair and replacement of components due to poor quality or production of components.
- You must be able to demonstrate the purchase of the product, so please keep proof of purchase.
- You will be responsible for packing and shipping the product to us, so please keep the original packing during the warranty period.
- contact us via the platforms where you purchase this product . be sure to include the proof of purchase and description of product of defects. we have the right to reasonably make all warranty claim decisions.
- This warranty does not cover damages caused by alteration of parts,removal of parts tampering, or disassembling.
- This warranty does not cover damages caused by neglect or improper use.

FAQ/Trouble Shooting

Q: I have established connection with my smartphone,but I am not hearing any sound?
A: Please make sure that you turn up the volume of both devices. Some smartphone requires you to setup the bluetooth headset as an audio output device before sound is trasmitted.Please see the instruction of your smartphone of details. If you are using a music player or other bluetooth device, please make it supports A2DP stereo music profile.

Q: Why the connection is not stable and cuts out intermittently?
A: Please make sure there are no objects between the headset and you bluetooth device; please make sure there is no radio or WIFI interference nearby.

Q: Can I use the headset while it is charging?
A: NO, you cannot use the headset while it is charging.

Q: The headset is not responding no matter what I do.
A: Please try to reset the headset.(see the "reset" section)

Q: The sound is not very clear/the caller cannot hear my voice clearly.
A: Please adjust the volume on you phone and headset.Make sure there is no source of interference nearby.Stay close to your smartphone.

Tips

- Before using the headset,please read the manual carefully and keep it for future references.
- The headset need to be fully charged priors to first-time use.
- If the headset is left unused for over two weeks,please recharge it periodically.
- Use only chargers made by qualified manufacturer.
- If the headset cannot be searched by you phone,please check whether it is in pairing mode; if left unconncted for a long while,the headset will exit pairing mode,please re-enter the mode;if a procedure error of your phone occurs, reboot it; if a procedure error of the headset occurs, reboot or reset it.

Safety Rules

- Never disassemble or modify you headset for any reasons to avoid any damages and danger.
- Do not use this headset during a thunderstorm to avoid irreguler function and increased risk of electric shock.
- Do not use harsh chemicals or strong detergents to clean the headset.
- Keep the headset dry.

FCC STATEMENT :

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the

following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

RF warning statement:

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.