1.Bluetooth headphone
User Manual
(Magift5)

2.Pls read the manual before you use the item.

3.Connection Diagram



4.How to use

4.1.General Functions

Desired Result	Required Action
Turn on	Press the "⏻" button for 3 seconds when the device is off, (Blue LED slowly flashes and a tone voice beep)
Enter the pairing mode	In power off mode Press the "⏻" button and hold on for 6 seconds,(Blue LED and Red LED quickly flash alternately with two beep tone voice),
Pairing	In pairing mode, use a bluetooth function mobile phone or other bluethooh master device to perform pairing action. (details refer to the part 4.2)
Play / pause	Press ⏯ to play when the device is pausing and press ⏯ to pause when the device is playing.
Volume up	Long press + < is for volume up

Desired Result	Required Action
Volume down	Long press > - is for volume down
Previous	Press < is for previous music.
Next	Press > is for next music.
Turn off	Press the "⏻" button for 3 seconds when the device is on,(a tone voice beep and all LED is off)
Low battery warning	(The LED flashes)
Charging	Plug the charger to port of the device, (Red LED is on)
Answer call	Press the +> or <-button for 1second while the call coming
End call	Press the +> or <-button for 1second to end call
Reject call	Press the +> or <- button for 2seconds to reject call when the call is ringing
Language switching	Press and hold the volume up and power button 3 seconds boot

4.2.Pairing to Mobile phone or other device

To use your Bluetooth Stereo Headphone, you must first pair your Stereo Headphone with a phone or a computer, Once your Bluetooth Stereo Headphone is paired to a specific mobile phone, they will remain paired and automatically recognize each other whenever they are within range.

Pairing to a phone and Entertainment:

- Turn on your phone and ensure its Bluetooth function is activated
- Turn on the Bluetooth Stereo Headphonego to the paring mode.

- Search your Bluetooth devices on your phone by following the phone's instructions. Refer to your phone's user manual for more information.
- After a few second the phone will list the device as a discover device. Select the " QX-01 " and follow your phone instruction to select this pairing.
- Then your phone will request a passkey or PIN, enter 0000 as your PIN or passkey.
- Your phone will confirm the pairing, and then press Yes/Ok.
- Finally, select to connect with device from your phone. Youcan play music; watch TV/movie and play game with your phone, then you can hear all the sound or music form the device. Also you can control the player by operating the device. Example, volume up and next music.

Pairing to a computer and Entertainment:

- If your laptop doesn't have bluetooth, you can use a bluetooth USB adapter.(Need your own purchase Bluetooth adapter)
- Turn on the device go to the paring mode.
- Open the Bluetooth software (such as BlueSoleil) installed on your computer, and selects "Search your Bluetooth devices" function. Refer to user manual of the Bluetooth software for more information.
- After a few second the " QX-01 " will list in Bluetooth software of your computer as a discover device. Select this icon and click right button of mouse to select "pairing" item,then select "connect with audio device"
- with same operation, Open your media player soft to play music, watch TV/movie and play game, then all the sound will be playback on your device.

4.3.Charging your device

The device is convenient to connect to AC charger or a USB charger with Micro USB port marked with. Make sure that your device is full charged for at least 6 hours before initial use. Insert one terminal of your charger to AC main or USB port of PC and other terminal to Micro USB, While charging, the red LED lights constantly. When charging is completed, the LED turns off.

Warning:

- You must select a qualified charger from a regular manufacturer.
- You must charge the Bluetooth speaker if it has been not used for more than 12 months.

5.Technical specification

Parameter	Value
Bluetooth Specification	4.0
Bluetooth Profile	Support A2DP1.2, AVRCP1.0, HFP1.5,HSP1.0
RF Range	10 m
Frequency Response	80Hz-20KHz
Loudspeaker Output	10mW
Signal-To-Noise	≥80dB

Parameter	Value
Distortion	≤5.0%
Playback Time	10 hours
Charging Time	2.5 hours

6.Service and Support

If your device is not performing as it should,please take it to your local service providers or dealer for service.

7.FAQ

1\ Why is there no power even when the Stereo Headphone is power on?
Ans: Ensure the battery is being charged up to 3 hours for first time use. The LED is lighted when it starts charging.

2\There is no sound when playback.
Ans: Check the connection between your device with phone or computer, if the connection is not established, pleasereconnect again. Make sure the Stereo Headphone device is paired and connected target phone or other master device.

3\How can I know the Bluetooth Stereo Headphone has been fully charged?
Ans: When the indicator LED turns red to blue when it is charging. It has been fully charged.

* Make sure to charge three hours before the firt time you use it.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.