


Baby 11QM

QUICK GUIDE



In the Box

Please consult this checklist for all parts.



Camera X1



Bracket X1



Power cable X1



Screw package X1




Quick guide X1



Power adapter X1

Description



Name	Description
Power supply	DC 5V/2A
Night light	Enjoy a clearer nighttime viewing and soothing your baby when he cries
Call/pair	Press to make a call; long press to pair camera with screen
Status light	● Solid red: Network malfunction ● Blinking red slowly: Waiting for network connection ● Blinking red fast: Connecting the network ● Solid blue: Functioning properly
TF card slot	TF card storage (up to 256GB)
RESET	Press and hold for 5 seconds to reset the device (all settings will be restored to factory defaults)

Get the App

1 Download App

- **If you are new to CloudEdge**

CloudEdge is available for both iOS and Android. Search for "CloudEdge" in App Store or Google Play, or scan the QR Code to download the App.

You can select the App according to needs.



Download App (iOS & Android)

- **If you already have an account**

Skip this section.

Note: Support



iPad



iOS



Android

2 Set up router

The device supports 2.4GHz & 5GHz Wi-Fi.

Ensure you have the SSID and password.



Please keep network available

2.4GHz



5GHz



Note: The length of the Wi-Fi SSID and password should not exceed 24 characters.

If your device has trouble connecting to the Wi-Fi network, or if you wish to switch networks, press and hold the RESET button for 5 seconds to reset the device.


Registration

Note: The App interface may vary due to version updates. Please check the App Store for the latest updates.

1 Sign up



Open the App, and tap **Sign up** to register.

If you already have an account, tap **Log In** to access it.



2 Complete registration

Enter a valid email address, agree to the privacy agreement, then set your nickname and password.




Note: Before creating a new account, please read the Privacy Policy and Terms of Use carefully.


Add Device

1 Power on device

Connect the device to an outlet (DC 5V/2A) using the power cable.



Note: If the device is not in the red slow flashing after 30 seconds of turning on, press and hold the reset button for 5 seconds to reset, and then restart to pair the camera with the App.





2 Enable Bluetooth on your phone


3 Pair device to the App

Pairing method 1

a. In the App, tap + > **Scan Code** or **Scan code to add** to scan the QR code located on the device casing.



b. Reset the device and ensure a stable Wi-Fi connection.



c. Complete the network configuration.

Pairing method 2


- a. In the App, tap **Add Device** or **+ > Add Device**. The device will be searched for via Bluetooth and appear on the screen. Follow the on-screen instructions to complete pairing.




- b. Complete the network configuration.

Pairing method 3


- a. In the App, tap **Add Device** or **+ Add Device**. Select the icon according to actual camera.



- b. Reset the device and ensure a stable Wi-Fi connection.



- c. Use the device to scan the QR code displayed in the App on your phone. Place your router, phone, and device close together for best connectivity.




- d. Complete the network configuration.

Note: The App interface may vary due to version updates. Please check the App Store for the latest updates.

Installation

- **Method 1**

Fix the device to the crib side of the enclosure by using a telescopic bracket.




- **Method 2**


a. Pick a clean and flat surface around the crib.

Note: Make sure the wall is strong enough to withstand 3 times the weight of the device.

- b. Fix the included mounting bracket to a clean surface 0.5m-1.2m above the crib.



- c. Insert the camera to the bracket.




Live View

Note: The App interface may vary due to version updates. Please check the App Store for the latest updates.

1 Live view & general settings

In the live viewing interface, common functions of the device can be enabled directly. Or you can tap  to enter the setting interfaces and set up accordingly.




2 Sleep detection & health monitoring

Radar detection is utilized to help monitor your baby's body movements during sleep, as well as monitor heart rate and breathe.


3 Privacy protection

Tap  in the live viewing interface to turn on/off lens or tap  > **Settings** > **Privacy Protection** to set up privacy schedule.



4 Smart care



Tap  > **Settings** > **Smart Care** to set up various functions which help you take better care of your baby.



5 Night light

Enabling night light function helps to view more clear during nighttime. Different night modes are available to meet customized demands.

Tap  in the live viewing interface. Or you can tap  to set up night light.



Monitor Using Tips

1 Pairing of camera and monitor

Power on the camera and the monitor, and they will automatically connect. If the connection fails, please follow the steps below to pair. The pairing is distance limited, please determine the appropriate distance according to the signal strength of the monitor.

• Bind the monitor and camera

1. Press the **Menu** button on the monitor, and select  > **Camera**.
Select **Camera 1** or **Camera 2** which you need to pair.
2. Long press the camera pairing button until you hear the prompt tone.
3. Press the **OK** button on the monitor to start pairing.
4. If you need pair 2 cameras, please repeat step 2~ step 4.

• Unbind the monitor and camera


1. Press the **Menu** button on the monitor, and select  > **Camera**.
2. Select **Camera 1** or **Camera 2** which you need to unbind.
3. Long press the **OK** button to release the binding.



2 Camera switching method

If you have added 2 cameras, the monitor will display 2 live views at the same time. If you want to set parameters or enable functions of one of the cameras, you need to select and switch to the camera first (the number shown in the  represents the selected camera).

On the home page, press  button and use the **Direction** button to switch the camera between Cam1 or 2 if you have added 2 cameras. Select one camera you need and press the **OK** button on the monitor to enter full-screen viewing mode. And then you can press  button again to zoom in and zoom out. (Zooming function does not work when the screen is not in full screen.)



3 Rotate the camera

You can adjust the monitoring angle for better vision.

The **Direction** buttons on the monitor screen are available when the camera is powered on. Press the **Direction** buttons to rotate the camera horizontally and vertically for better vision.

For more monitor functions, please refer to the kit manual.

FAQs

Q: The device cannot be previewed properly?

A: Check if the Wi-Fi network signal is strong.

If not, it is recommended to place the device closer to the router or reset the device and add it to the App again.

Q: How to change the Wi-Fi or update the Wi-Fi password for the device?

A: Please delete the camera on App, tap **Add** and follow the steps to use the new Wi-Fi network to add the camera again.

Q: Why I can't get the notifications with App?

A: Please confirm that the App has been running on the phone, and the relevant reminder function has been enabled. Also, please confirm the message notification and authority confirmation of the phone system have been enabled.

Q: Cannot find the pairing button?

A: The pairing button is the call button of the camera. Long press the button for 3 seconds, and follow the step instructions of the monitor.

Q: Failed to access the live video, prompts offline?

- A:
- Please ensure the camera is in the power-on status: the camera network indicator should be on.
 - Check the Wi-Fi network is in good condition or restart the router.
 - Try to move the camera closer to the router.
 - Delete the camera from the App and add it again. Confirm the App and camera firmware are the latest versions.

Tech Specs

Model	Baby 11QM
Resolution	2560(H) x 1440(V)
Lens&FOV(H/V/D)	F2.0, 90°/50°/110°
IR Distance	Up to 6m (19.7 ft)
Working temp	0°C to 40°C
Local storage	TF card (up to 256GB)
Input power	DC 5V / 2A
Consumption	Up to 4.5W
Supported phone OS	iOS 9 / Android 5.0 or later
2.4GHz Wi-Fi	2412-2472MHz (Max. power<20dBm) (For CE) 2412-2462MHz (Max. power<30dBm) (For FCC)
5GHz Wi-Fi	5150-5725MHz (Max. power<23dBm) (For CE) 5725-5850MHz (Max. power<14dBm) 5150-5850MHz (Max. power<23dBm) (For FCC)
Wi-Fi Halow	866MHz (Max. power<20dBm) (For CE) 905-925MHz (Max. power<30dBm) (For FCC)
Bluetooth	2400-2483.5MHz (Max. power<20dBm)

Certifications



Don't throw batteries or out of order products with the household waste (garbage). The dangerous substances that they are likely to include may harm health or the environment. Make your retailer take back these products or use the selective collect of garbage proposed by your city.



Hereby, we declare that the radio equipment type **Baby 11QM** are in compliance with the Directive 2014/53/EU.

Specific precautions for EMC

This is a Class B product, in a domestic environment, this product may cause radio interference, in which case the user may be required to take adequate measures.

RF EXPOSURE INFORMATION

This device meets the EU requirements (2014/53/EU) on the limitation of exposure of the general public to electromagnetic fields by way of health protection.

Restrictions declaration in the 5 GHz band

The device for operation in the band 5150–5250 MHz is only for indoor use to reduce the potential for harmful interference to co-channel mobile satellite systems.

Power Adapter Safety

1. The power plug is intended to serve as a disconnect device. Do not drop or cause an impact to the power adapter.
2. If the power cable is damaged (for example, the cord is exposed or broken), or the plug loosens, stop using it at once. Continued use may lead to electric shocks, short circuits, or fire.
3. Do not touch the device or the power adapter with wet hands. Doing so may lead to short circuits, malfunctions, or electric shocks.

Child's Safety

1. Comply with all precautions with regard to child's safety. Letting children play with the device or its accessories may be dangerous.
2. The device and its accessories are not intended for use by children. Children should only use the device with adult supervision.

Operation Requirements

1. Use the device under allowed humidity and temperature conditions.
2. Do not aim the device at strong light sources (such as lamplight, and sunlight) when focusing it, to avoid reducing the lifespan of the CMOS sensor, and causing overbrightness and flickering.
3. Observe local laws and regulations, and respect the privacy and legal rights of others.

Industry Canada (ISED) Compliance Statement

This device complies with Industry Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

- (1) This device may not cause interference; and
- (2) This device must accept any interference, including interference that may cause undesired operation of the device.

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

- (1) l'appareil ne doit pas produire de brouillage;
- (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

The device meets the exemption from the routine evaluation limits in section 2.5 of RSS 102 and compliance with RSS-102 RF exposure, users can obtain Canadian information on RF exposure and compliance.

Le dispositif rencontre l'exemption des limites courantes d'évaluation dans la section 2.5 de RSS 102 et la conformité à l'exposition de RSS-102 rf, utilisateurs peut obtenir l'information canadienne sur l'exposition et la conformité de rf.

This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment should be installed and operated with a minimum distance of 20 centimeters between the radiator and your body.

Cet émetteur ne doit pas être Co-placé ou ne fonctionnant en même temps qu'aucune autre antenne ou émetteur. Cet équipement devrait être installé et actionné avec une distance minimum de 20 centimètres entre le radiateur et votre corps.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

RF EXPOSURE WARNING

FCC Radiation Exposure Statement: This device complies with FCC radiation exposure limits set forth for an uncontrolled environment and it also complies with Part 15 of the FCC RF Rules. This equipment must be installed and operated in accordance with provided instructions and the antenna(s) used for this transmitter must be installed to provide a separation distance of at least 20 cm from all persons and must not be co-located or operating in conjunction with any other antenna or transmitter. End-users and installers must be provided with antenna installation instructions and consider removing the no-collocation statement.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution!

Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

© 2025. All rights reserved. All trade names are registered trademarks of respective companies. Apple, the Apple logo, iPhone are trademarks of Apple Inc. registered in the U.S. and other countries. Google, the Google logo, Android are trademarks of Google Inc. App Store is a service mark of Apple Inc. Google Play is a service mark of Google Inc.

V1.0 202503