

Vendor Stock Nbr: 36021953
October 07, 2025 V1

1. Plug the USB receiver into the device's USB port.
2. Turn on the headset by pressing the power button on the side of the ear cup.
3. Connect the headset cable to the USB receiver.
4. Open the Quick Start Guide for reference.
5. Plug the USB receiver into the device's USB port.

- 1) Wireless PC Headset
- 2) Wireless USB Receiver
- 3) USB-C Charging Cable 3 ft
- 4) Quick Start Guide & User Guide
- 5) USB-A Adppter

- 1) Headset Sensitivity: 102dB±3dB
- 2) Speaker Diameter: 40mm
- 3) USB-C Charging Cable Length: 3ft
- 4) Rechargeable with up to 30 hours of playtime per charge(50% Volume)
- 5) Detachable boom microphone with Environmental Noise Canceling
- 6) Connect via low-latency 2.4Ghz wireless receiver and Bluetooth® wireless technology
- 7) Active Noise Canceling screens out background noise
- 8) On-ear call controls
- 9) Lightweight metal-reinforced frame and headband
- 10) Breathable sponge ear cushions with synthetic leather
- 11) Play while charging
- 12) Compatible with Windows, MacOS, and ChromeOS



SCAN HERE FOR MORE
PRODUCT INFORMATION
AND LEAVE US A REVIEW!

Functional Instructions

- 1) Microphone Mute LED Indicator
- 2) Detachable Boom Mic
- 3) Built-in Microphone
- 4) Adjustable Headband
- 5) Microphone Mute Button, USB / Bluetooth Switch Button
- 6) USB-C Charging Port
- 7) Power ON / Power OFF & Headset LED Indicator & Pairing Mode Button
- 8) Volume Up Button
- 9) Volume Down Button
- 10) USB-A Adapter
- 11) Wireless USB-C Receiver
- 12) USB-C Charging Cable 3ft

CAUTION
Only use a USB
charging device that
is 5V DC output.

- Charging: Red LED is ON.
- Fully charged: Blue LED is ON.
- Charging time: About 2 hours (from empty battery).
- Device searching / pairing mode: Blue LED flashing.
- Successfully paired: Solid blue LED for a few seconds, then turns off.
- When the headset is powered OFF: Red LED flashes twice.

- USB dongle / receiver (LED behavior)
- Pairing: USB dongle flashes red and blue.
 - Paired — Microphone unmuted: Solid blue
 - Paired — Microphone muted: Solid red.

Notes:

- It takes about 2 hours to fully charge the headset from an empty battery
- The device may need to be charged before first use.

- Lithium-ion batteries, if used improperly, can be dangerous to users. Exercise caution when handling them, especially in adverse environments.

This symbol on the product or its packaging indicates that this product must not be disposed of with your other household waste.

Instead, it is your responsibility to dispose of your waste equipment by handing it over to a designated collection point for the recycling of waste electrical and electronic equipment.

The separate collection and recycling of your waste equipment at the time of disposal will help conserve natural resources and ensure that it is recycled in a manner that protects human health and the environment. For more information about where you can drop off your waste for recycling, please contact your local authority, or where you purchased your product.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Important: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Insert USB Receiver

Charge your headset

1. Insert the USB receiver into your device's USB port.
 - If the device only has a USB-A port, use the included USB-C → USB-A adapter.
 - Make sure the headset is charged before use.
2. When you plug in the receiver, its LED will flash red and blue. After successful connection, the receiver LED will turn solid blue and you will hear "USB Connected" from the headset.
3. Power ON the headset: Press and hold the power button for 3 seconds.
 - You will hear "Power ON" and the headset LED will alternate flashing red and blue.
4. If the USB receiver does not automatically connect to the headset, enter pairing mode manually by pressing the Power button 3 times.

Important: Make sure the headset is in USB MODE to use the USB receiver as the audio source.

1. Go to PC Settings, then select System.

The screenshot shows the Windows Settings application. The 'Settings' app icon is on the left, and the 'System' category is highlighted in blue on the right.
2. When the USB Dongle Receiver Plugged into the Device, go to PC Setting > Sound > Volume Mixer.

The screenshot shows the Windows Settings application, specifically the 'Sound' settings page. The 'Volume mixer' tab is selected, and the 'Output device' is set to 'onn PC Wireless Headset'.
3. Select both the Output Device and Input Device as "onn PC Wireless Headset "

Using ANC / Ambient Mode

Double-press the Mode button to switch between sound modes

When powered on, the headset defaults to ANC Off.

- Double-press once to turn ANC On — you will hear the pro
- Double-press again to enter Ambient Sound Mode — you
- Double-press once more to turn ANC Off — you will hear

Mobile Device setup for headset

Step 1:
Switch to Bluetooth Mode: Press and hold the Mode Button for 3 seconds to Bluetooth Mode.
The LED will alternatively flash blue and red.

Step 2:
Open Bluetooth settings on your device and select "onn PC Wireless Headset" to get it connected.
After successful connection, you will hear "Bluetooth Connected" from the headset. This process can also be applied to connect with other Bluetooth enabled devices, such as a PC, mobile phone, or console.

Connecting to a New Device:
Press the Power button three times to enter Pairing Mode.
You will hear a Bluetooth pairing voice prompt. The LED indicator will flash blue rapidly while pairing. Once the pairing is successful, the Power LED will stay on for 3 seconds and then turn off.

Microphone Mute Function

Press the Mode button once to mute the microphone — you will hear the voice prompt "Microphone muted."

Press the Mode button again to unmute — you will hear "Microphone on."

The microphone mute indicator light is located on the microphone boom

- When the microphone is muted, the red light turns on.
- When the microphone is on, the red light turns off.

The headset is equipped with two microphones.

When the detachable boom microphone is unplugged, the built-in microphone automatically activates, allowing you to continue using the headset for calls or gaming without the boom mic.

The diagram illustrates the headset's microphone configuration. On the left, a close-up of the earcup shows the boom microphone detached and the built-in microphone (labeled '1 Press') activated. On the right, a full view of the headset shows the boom microphone unplugged. A callout box with a microphone icon points to the built-in mic on the earcup.

This design provides two usage scenarios — one with the boom mic attached and one using the built-in mic for a cleaner look.

The built-in microphone can also be muted or unmuted using the microphone mute control button.

1 YEAR LIMITED WARRANTY
COVERING DEFECTIVE PARTS

Product Manufacturer for Additional Information

Warranty is non-transferable and void if misused or installed incorrectly.

All warranty coverage applies only if barricade is used in the United States.

For product assistance & missing or replacement part s: WE CAN HELP	THIS GUIDE CONTAINS IMPORTANT SAFETY INFORMATION.
1-888-516-2630 7 DAYS/WEEK 7:00am - 9:00pm CST	PLEASE READ AND KEEP FOR FUTURE REFERENCE.

Find more at Walmart.com