

 STEREO Bluetooth Headset USER GUIDE	Answering a Call When you hear the ring tone, press the Multifunction Button or press the button on your phone's keypad, but you may need to transfer the call to your headset by pressing and releasing the Multifunction Button (depending on your phone). Ending a Call Press and release the Multifunction Button once or end call from phone keypad. Answering or Rejecting a Call when Listening to Music: If there is ring tone of incoming call when you are listening to music, in your phone or PC or other Bluetooth enabled devices, press still either "Power ON / OFF / Answer a call" button for 2 second to reject the call or press the Multifunction Button to answer the call. Multimedia Feature: If the pairing is successful with the phone which supports 1.2 ,A2DP profile,it allows you to enjoy the real stereo sound music from your phone. When there is an incoming call, the headset will automatically switch to phone mode and resume to music mode when the call ends. This feature works same with PC. 5																		
Introduction Bluetooth Wireless Technology Bluetooth wireless technology propels you into a new dimension in connectivity. Your Bluetooth Headset can communicate with other Bluetooth devices with in a range of distance 10 meters (30 feet) . How to use your Wireless Headset? Your Wireless Headset equipped with Bluetooth technology, lets you connect with other similarly equipped devices. * Handle incoming and outgoing calls with the headset call handing button. * Use voice dialing to make calls. Product Features: Name of Product: Multimedia STEREO Bluetooth Headset – e6 Type: STEREO Bluetooth Headset 1	Redialing the Previous Call: Press still the Multifunctional Button for double click, and then it will make a call to the previous number you called. Playing Music: When you are listening to the music from PC (Music format recommended: Windows Media Player),you can press Play,Pause,Previous Song,Next Song.(refer to the"Button's Feature") to select your optimal performance. Volume Control: Volume will be up when press the Volume Control (+)3seconds,and will be down when press the volume Control (-)3seconds. Pairing 2 mobile phones Step 1 : Pair the first mobile phone with the Bluetooth headset A: In the power off status, press the power button 3-10 seconds, in which the light in red and green flashing. B: Open the Bluetooth of mobile phone, searching the corresponding Bluetooth headset, pairing. 6																		
STEREO Bluetooth headset Constituent Part: 1. The indicator light 2. Power Button 3. Speaker 4. Charger connector 5. ear hook Noted: Some Bluetooth headset part have magnetic, don't put it with your credit card or other storage medium. Prevent information to be deleted. Means of Charging: . Travel Charger DC5V 300mA . USB Charger USB +5V Battery Standard: . High-capability Rechargeable Lithium Polymer Battery0 Battery Voltage:3.7V Additional Function to Protect Battery Product Standard: . Class 2 Operation . Talk Time: 2`3 hours. . Standby Time: 45`50 hours Charging time: 2 hours 2	Step 2: Pair the first mobile phone with the Bluetooth headset C: Press the power button 3-5 seconds, close the Bluetooth headset, and keep the status of first mobile phone. D: Press the power button for 8-10 seconds, in which the light in red and green flashing. E: Open the Bluetooth of the second mobile phone, searching and pairing. Step3: The first mobile phone connect to the Bluetooth headset F: In which the first mobile disconnect with the Bluetooth headset G: Keep the status of Bluetooth headset; search the Bluetooth headset in the first mobile phone H: Connect the Bluetooth headset directly, dual pairing done. Important: Please kindly note that the functions or operations stated in this User Manual is only applicable to mobile phones which support Bluetooth . Please carefully read your phone's instruction guide because the operation might be different. 7																		
NOTED: *Standby time and talking time may be different subject to network situation* Light Description: . The indicator light turn to blue and red when pairing . Flashing once rapidly in 2 second when connecting . Flashing once slowly every 2 second when waiting for connection . The red indicator flashing 3 times every 2 second when power status is low. . The light is red when charging. Bluetooth headset is closed. . The red light turn to Blue when charging completed Pair to your Mobile Phone : 1. The distance between the Bluetooth headset and your mobile phone would be better within 1 meter when pairing, the closer is better. 2. Ensuring the headset is off. 3	Correct disposal of this product (Waste Electrical & Electronics Equipment) This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources. Household user should contact either the retailer where they purchased this product, or their local government office, for- detail of where and how they can take this item for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal. 8																		
3.Pressing still the Multifunctional Button , sustain 6 seconds , frist the blue light glimmer, until you see the blue light and red light glimmers , then release the button. 4. Set your Bluetooth phone to "discover" the headset by following your phone's instruction guide. The steps involve going to a " setup ", " connect ",or "Bluetooth" menu on your phone and then selecting the option to "discover" a Bluetooth device. 5. Your phone will find the "veva e6" headset and ask if you want to pair with it. Confirming this by pressing " yes " or "ok". 6. Enter password "0000", then press "yes" or "ok". Note: The pairing generally takes about 60 seconds. If unsuccessful, the blue indicator light flashes slowly, and then you need to reattempt pairing (see steps 4-6). Turning off the headset by pressing the button sustain 4 seconds. Important and Noted: 1. Before charging, please check the charger suit for Bluetooth headset. 2. Please used original battery and original charger, if you used other charger and charging, maybe you will damage headset. That is DANGEROUS and You have violate the plan regulation. 3. Bluetooth headset 's battery is built-in Li-ion battery . Don't take it out. Protect the goods against spoilage. 4. Keep your headset off when you don't use it. You need to charging each month, if you don't use 5. Don't throw it into fire. 4	Shenzhen VEVA Technology Co.,Ltd Product Quality Warranty Card VEVA company offer a one-year warranty(from the day of purchase) <table border="1"> <tr> <td>Product No.</td><td></td></tr> <tr> <td>Commodity product</td><td>Shenzhen China</td></tr> <tr> <td>User name</td><td></td></tr> <tr> <td>User's phone number</td><td></td></tr> <tr> <td>Sale Site</td><td></td></tr> <tr> <td>Sales date</td><td></td></tr> <tr> <td>Seller name</td><td></td></tr> <tr> <td>Seller name</td><td></td></tr> <tr> <td>Maintenance Record</td><td></td></tr> </table> 9	Product No.		Commodity product	Shenzhen China	User name		User's phone number		Sale Site		Sales date		Seller name		Seller name		Maintenance Record	
Product No.																			
Commodity product	Shenzhen China																		
User name																			
User's phone number																			
Sale Site																			
Sales date																			
Seller name																			
Seller name																			
Maintenance Record																			

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference, and
- (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.