


FRONT

DONUT SPEAKER

Model NO.:WM-BTSP-CDNT



SPECIFICATIONS

Product Size: 88 x 88 x 45mm
Weight: 137g
Loudspeaker: 40mm
Rated Power: 3W
Interface: Micro USB


Bluetooth® Specifications:
Operation Frequency: 2.400GHz-2.480GHz
Power Output (Peak): Class 2/4 dbm
Receiving Sensitivity: -88db, @ 0.1% BER
Operating Range: Up to 10m

Battery Specifications:
Capacity: 600mA, 3.7V, Polymer Li-ion Battery
Music Playback Time: 3-4hours at 70% volume
Charging Standard: DC 5V, 500mA
Charging Time: 2-3 hours

Accessories:
USB Cable: 1pc
User Guide: 1pc
Speaker: 1pc

OPERATION

1. Dust Cover: protects switch and Micro USB port
2. Power switch: Press ► for 3 seconds On/Off
3. Micro USB: Charging port
4. Press ► for the next song, hold to increase volume
5. Press ◀ for the previous song, hold to decrease volume
6. Press ► to play or pause under playback mode
7. Press ► to answer or hang up during phone calls while in Bluetooth® mode. Press and hold this button to disconnect the Bluetooth® connection
8. Microphone: for use during hands-free calling
9. Suction Cup: Capable of sticking to any smooth surface (glass, glossy areas, flat walls, flat ceramic, etc.)
10. LED indicator: Built-in battery indicator
 - *Red light on: in charging mode
 - *Red light off: fully charged
 - *Yellow light flashing quickly: in Bluetooth® pairing mode
 - *Yellow light flashing slowly: Bluetooth® pairing successfully



6.5 CM / 2.5 IN

6.5 CM / 2.5 IN

BACK

USAGE

- Turn on the speaker
- Activate the connecting devices' Bluetooth® connection
- Switch the speaker into pairing mode (blue light flashing quickly)
- Search "DONUT SPEAKER" and pair
- Connect and play

NOTES

1. Hands-free call is only available when in Bluetooth® connection. Phone calls can be interfered with high frequency electromagnetism. People should not try to use this product in high frequency environments.
2. Bluetooth® transmits bi-directionally, the transmitting distance is related to the audio player. Use only compatible Bluetooth® devices is recommended.

3. When Bluetooth® transmitting devices cannot be connected, please delete the last Bluetooth® receiving devices named on the Bluetooth® devices list. Re-activate the speaker, then try re-searching and re-pairing.

4. Audio quality can be affected when the Bluetooth® transmitting devices have a poor signal or low battery capacity.

5. Waterproof: only the silicone gel housing is waterproof. Do NOT expose the inner structure and components to water, liquid or dampness.

WARNING: This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the

instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help

NOTE: This device and its antenna(s) must not be co-located or operation in conjunction with any other antenna or transmitter. The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.