

Operation Manual


Wireless Bluetooth Headset TWS-K2

OPERATIONS GUIDE

Inside the box

1. Bluetooth Headset	× 2PCS
2. Charging Case	× 1PCS
3. Micro USB Cable	× 1PCS
4. Operations Guide	× 1PCS

Functional Diagram



Specification

- 1. Version: BT4.1+EDR
- 2. Supports: HSP/HFP/A2DP/AVRCP
- 3. Charging Interface: Point-contact
- 4. Size: 28*20*28mm
- 5. Standby Time: About 40hours
- 6. Call Time: About 2hrs
- 7. Play Time: About 2hrs
- 8. Net Weight: 5.0g
- 9. Charging Case Size: 80*60*30mm
- 10. Charging Case Weight: 45g

How to Use

- ◆Charging
 - 1. Placed the earphones on the slots of the charging case correctly
 - 2. Connect the charge cable to Micro Jack on the charging case
 - 3. Plug the charge cable to a Charger(3.5V) or USB output of PC
 - 3. Indicator light shows red, when fully charged the blue lights up
 - 4. Charging Case should be charged 2hrs at least
- ◆To Switch the Headset On/Off
 - 1. To turn on: Press and hold the Multi-function key for 4s then the blue lights up
 - 2. To turn off: Press and hold the Multi-function key for 3s then the red lights up while they’re working.

- ◆True Wireless Mode Pairing
 - 1. Press and hold the Multi-function keys for 7 seconds of the two headsets simultaneous, then they will be paired and connected automatically
 - 2. The headsets will be specified as Left channel and Right channel relatively, then the left headset will enter pairing mode again, enable your phone’s Bluetooth and search, click the model “TWS-K2” to pairing and connect.
- ◆To Pair the Headset Single with Your Phone
 - a. Press and hold the Multi-function key for 7 seconds, release when the red light and blue light flash alternatively, the Bluetooth headset enters pairing state;
 - b. Open the Bluetooth of your mobile phone and search, click the model “TWS-K2” to pairing
 - c. If asked to enter the password, please enter 0000.
- ◆To Answer A Call
 - Click the Multi-function key of the host headset shortly
- ◆To End A Call
 - Press the Multi-function key of the host headset shortly while your phone is online
- ◆To Reject A Call
 - Press the Multi-function key of the host headset and hold for about 1 seconds while there is a incoming call on your phone
- ◆To Redial the Last Number
 - Press and hold the Multi-function key of the host headset

- ◆To Activate Voice Dialing
 - As long as your phone support for voice dialing, double click the Left Multi-function key during standby mode for 1second then the last number you have called will be redial out.
- ◆To Play or Pause
 - Click the Multi-function Key of host headset to control pause and play the music.
- ◆To Play Next Song
 - Click the Multi-function Key of vice headset to play the next song.

Safety Precautions

- Please read follow and keep these instructions
- 1.Keep the device out of extreme heat and humid
 - 2.Power time may different depending on personal habits
 - 3.Heed all warnings on the product and in the operation instructions
 - 4.Do not listen at high volume level for long period to protect hearing
 - 5.Stop ushing this product immediately if it causes discomfort or pain.

⚠ Kindly Remind: We strongly recommend that you use for the first time a full battery, please!



FCC Warning:
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- o Reorient or relocate the receiving antenna.
- o Increase the separation between the equipment and receiver.
- o Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- o Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications to this device not explicitly approved by manufacturer could void your authority to operate this equipment.

Operation Instructions & Statements

KEY	ACT	FUNCTION OF EVENT						
		PAIRING	AVAILABLE FOR CONNECTIONS	CONNECTED	INCOMING CALL	DIALING	CALLING	CALL WAITING
	Short Press	Connect	Connect	Play / Pause	Answer	Cancel	Hang-up	Hang up and answer incoming call
	Double-Press		Pairing	Voice dialing				
	Press & hold for 1second			Redialing	Refuse			Hold on and answer incoming call

STATUS	RED LED	BLUE LED	COMMENTS
Charging	ON	OFF	
Charge complete	OFF	ON	
Power on	Remains 1sencond		
Power off	Remains 1sencond		
True Wireless Pairing	Red & Blue LED flash alternately		Default time remains 64seconds
Left channel		Flash once every 5 seconds	
Right channel		Flash once every 5 seconds	
Pairing	Red & Blue LED flash alternately		Default time remains 5minutes
Standby with no connection	Flash once every 5 seconds		Default time remains 10minutes
Standby connected	-	Flash once every 5 seconds	
Low Battery	3times flash once every 20 seconds	-	The battery is low
Incoming call / Dialing		Flash once every 5 seconds	
Phone is online		Flash once every 5 seconds	

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.