

Bluetooth Headphone

EB-002

Please keep and read this manual carefully before use the headphone.

Note the following items:

- 1.Please use the reasonable control of the time and the volume of the headphone.
- 2.If the environment（such as thrunder storm）are potentially dangerous, please stop using to ensure safety.
- 3.Don't use the headphones to listen to music or calling or while driving in potentially dangerous environment, in order to avoid distracting.
- 4.Place the headphone out of the reach of children to avoid improper use may caused deadly danger.
- 5.Do not watering inside the headphone, to avoid sound or electronic damage.
- 6.Continue to increase the volume should be avoided cause you do not hear the sound around,such as tinnitus or turn up the volume to high ,please transferred to the appropriate volume.
- 7.Feels obvious discomfort, irritation or other adverse reactions, should stop using immediately.

Warning:

- 1.While in charging process please don't use ,to avoid electrocuted
- 2.Built-in rechargeable battery is not removable. Do not try to remove battery from headphone, otherwise it could be damaged.

Charging:

- 1.While charging ,the headphone power will be shuted down.
- 2.Plug micro usb in the headphone USB Jack, then connect with computer usb hub or adaptor. red led will flash slowly like brease
- 3.Charging time is 2.5 hours; Red led be lighted on when charge complete

Frequently question

Button have no function:Please use the palyer witch is the smart phone's player .Can't start : take off the USB charging and 3.5mm plug.1...

蓝牙耳机 EB-002

为正确而安全地使用本耳机，请在使用前详细阅读本手册。

使用耳机时应注意以下事项：

- 1. 请合理控制使用耳机的时间和音量。
- 2. 请勿在有潜在危险（如雷雨天）的环境中使用耳机，以确保安全
- 3. 应尽量避免在驾驶途中使用耳机聆听音乐，拨打或接听电话，分散注意力造成危险。
- 4. 请将耳机置于儿童无法接触到的地方，避免儿童使用不当造成致命危险。
- 5. 避免耳机进水，以免损坏耳机功能。
- 6. 避免持续调高音量，导致你听不到四周声音，如出现耳鸣或音量调节过高时，请将音量调低
- 7. 如果使用耳机感觉明显不适，有刺激感或其它不良反应，应立即停止使用。

警告：

- 1. 充电时请勿佩戴，以免造成触电危险。
- 2. 本耳机使用内置式不可拆卸充电电池。不要从耳机中取出电池，以免损坏耳机。

耳机充电：


- 1. 充电时耳机会强制自动关机，充电区间无法开机；
- 2. 将USB充电线插入耳机充电接口，另一端的USB端口插到USB充电器或电脑的USB端口上，充电时红色LED呼吸灯方式闪烁；
- 3. 充电时间2.5小时左右，充电完成后红灯常亮

常见问题

按键无作用：请使用手机自带的播放器
无法开机：拔出3.5mm音频线和移除USB充电

.....1.....

Function Buttons:



bluetooth headphone package list
Stereo Bluetooth Headphone 1PC 3.5mm Audio Cable 1PC
USB Charging Cable 1PC User Manual 1PC

ON & OFF:

- 1. In the OFF state, press MF button for 2 seconds (White LED flash while "POWER ON" voice prompts).
- 2. In the ON state, press MF button for 3 seconds (red LED lighted on 1.5 second while "POWER OFF" voice prompts).


Bluetooth pairing steps:

- 1.Connect Bluetooth headphone to your mobile (or other device used for connection) in the range of 1m
- 2. In the OFF state, press MF button for 5 seconds ,noted "POWER ON" and "Pairing" then open the Bluetooth function of your mobile.
- 3.Search and choose "RB-500HB" to connect

PS. NOTE:

- 1.If headphone had paired ,under the off states press MF button" for 2 seconds to power on it will reconnect the last used device automatically, also if the headphone have no device to reconnect ,after 10 seconds it enter the pairing mode automatically ,it good at use a new device to pair, absolutely you can press MF button" for 5 seconds to enter the pairing mode directly then repeat the up2...

按键功能



RB-500HB 立体声耳机包装清单
耳机成品 1个 3.5mm音频线 1条
USB充电线 1条 RB-500HB使用说明书 1份

开机机操作:

- 1. 关机状态下，常按MF键2秒白灯闪烁同时听到“开机”提示音即开机
- 2. 开机机状态下，常按MF键3秒红灯常亮同时听到“关机”提示音即关机

蓝牙连接步骤：

- 1. 请将蓝牙耳机和手机（或其它用作连接的装置）的距离控制在1米范围内。
- 2. 关机状态下，常按MF键5秒先后听到提示音“开机”和“配对模式”同时白灯LED快速闪烁，即进入配对模式
- 3. 打开手机蓝牙搜索“RB-500HB”点击即自动连接

注意事项:

- 1. 如果耳机已经有连接过手机,常按2秒再次开机，会自动连接到最后一次连接的设备上，次外如果耳机开机后周围无已连接过的设备，10秒后自动进入配对模式，方便用户用新设备（未连接过的设备）配对，当然耳机也支持长按5秒开机后直接进入配对模式，开机直接进入配对模式后重复上述蓝牙连接步骤即可配对成功

.....2.....

- "bluetooth pairing steps".
- 2. Pairing time lasts for 3 minutes, if time out it will power off automatically, repeat use it please restart.

Disconnected and reconnecting:

- 1. When the connect distance out of rang ,a “du du” voice prompt every 10 seconds and white lights flash 2 times, if the headphone near the mobile back within 3 minutes,it will be reconnected ,otherwise it will be shut down automatically .
- 2. If select shut down the mobile bluetooth function to disconnect , the headphone will enter the pairing mode automatically.

Phone Call Pick-up:

Click the MF button" to answer the call.

Phone Call Hang-up:

During a call, short press the MF button" to end the call

Phone Call Reject:

Press and hold MF button" 1 second to reject the call.

Call Waiting:

During a call, when a second incoming calls, double-click the MF once to hold the first call and answer the second call , Then double-click the MF button" again to hold the second call and answer the first call. Click the MF button" to end the current call and turn call to the second party.

Connect Two Mobiles:

- 1.After connected with the first mobile, turn off the headset , then long press MF button" for 5 seconds until enter the paiting mode, open blue function of the second phone, search for blue devices and click "RB-500HB" to complete the connection; find "RB-500HB" on the firstmobile and click to connect .
- 2. When the first mobile calls, press the MF button" to answer the phone call; When the second mobile calls, double-click the MF button to hold the first phone call and answer the second call.
- 3.Double-click MF button" to switch calls between two mobile3...

- 2. 进入配对模式的时间只有3分钟，超时后耳机自动关机，再次使用请重新开机

蓝牙耳机断开连接后，重新连接：

- 1. 当使用距离超出蓝牙接收范围时，蓝牙会断开连接，此时白色LED每10秒以呼吸灯方式闪烁两次，并重复出现两声“嘟 嘟”提示音，断开时间超过3分钟后耳机会自动关机，3分钟内耳机重新靠近手机后可以自动回连
- 2. 如果直接操作手机，关闭手机蓝牙的情况下，蓝牙耳机自动进入配对模式

接听电话：

来电时短按MF按键一次

结束通话：

通话区间短按MF按键一次

拒接来电：

来电时长按MF按键1秒，听到“嘟”声后松手。

来电等候：

通话时，有第二个来电时，双击“MF按键”一次，可保留第一个通话，即接听第二个通话。再双击“MF按键”一次，可保留第二个通话，接听第一个通话。单击“MF按键”可挂断当前通话并接通第二方通话。

连接两台手机：

- 1. 蓝牙耳机与第一部手机连接完毕后，关闭蓝牙耳机，再持续按住“多功能键”5秒至蓝灯快闪，进入搜索状态，开启第二部手机蓝牙功能，搜索蓝牙设备，点击“RB-500HB”，完成连接；从第一部手机的蓝牙连接列表里，找到“RB-500HB”型号，点击连接，即可完成连接两台手机。
- 2. 当第一台手机来电时，按一下“MF按键”接听电话进行通话，另一台手机再次来电时，双击“MF按键”保持上一台手机的通话，进行第二台手机的通话。
- 3. 切换通话，双击“MF按键”可以随意切换两台手机间的通话。
- 4. 按一下“MF按键”，挂断当前通话并恢复被保留通话

.....3.....

- 4.Short press the MF button" one time to hang up the current call and recover a call on hold.

Last number redial:

In any mode, double-click MF button" to redial the last number.

Voice Dialing:

Press and hold MF button" 1 second to reject the call. (Option)

Playing/Pause:

Playing music mode, click the MF button" for playing or pause.

Music Selections:

Playing music mode, short press “volume -” to jump to the next song , double-click the “volume +” to jump to the previous one.

Volume Control:

Call or playing music mode, press and hold “volume +” and “volume -” to adjust the volume.

LINE-IN Playing:

Connect the 3.5mm audio plug to the headphone and mobile or other audio device, headphone shutdown immediately and use the audio cable to listen to music.

Reset

After power on (Except for playing mode),Press an hold“VOL-“4“VOL-“3S to reset ,then the headphone enter the pairing mode automatically.

Change the prompt language

Under the pairing mode,press and hold MF & V- button 3 seconds until the LED be lighted 2 seconds ,it indicator change successfull.

Low volume alarm:

“Battery low” warning note when the battery voltage is less then 3.4V.

Specification:

Working Range: 10 M	Frequency: 20Hz-20KHz
Playing/Call Time: 16 hours	Impedance: 32Ω Speaker: ϕ40mm
Battery: 3.7V/400mAh	Support: A2DP/AVRCP/HSP/HFP
Charge Temperature:0 -45℃	Working Temperature: -10 -60℃
Bypass cable: 3.5mm cable	Bluetooth version:4.1 Net Weight: 218g
	4....

末号重拨：

任何模式下双击“MF按键”重拨最后一个电话号码。

启动手机语音功能：

长按MF按键1秒，听到“嘟”声后松手（需手机支持）

播放暂停：

播放音乐时，单击MF按键

歌曲选择：

播放音乐时，单击音量加按键跳到上一曲，单击音量减按键跳到下一曲

音量调节：

听音乐或通话时，长按音量减按键音量逐渐减小，同样的长按音量加按键音量逐渐增加，最大音量时出现“滴”一声提示音

3.5mm音频线使用：

插入3.5mm音频线后耳机蓝牙功能自动关闭，此时耳机可当有线耳机使用

复位

开机后同时按下音量加和音量减按键保持3秒，白色红色LED同时闪烁3次后表示复位成功重新进入配对模式，同时可听到“配对模式”提示音，此时耳机已经清除了之前的配对记录，自动进入配对状态。

切换提示音

耳机设置了中英文提示音，开机配对模式下，长按“MF”和“VOL-”键3秒(MF优先先按下)，红白LED长亮2秒，切换中英文提示音，2秒后自动回到配对模式下

低电量报警提示：

当耳机电量低于3.4V时红色LED会快速闪烁，重复出现“电量低”提示音继续使用，电量过低时则会自动关机。

规格：

工作范围: 10 米	频响范围: 20Hz-20KHz
播放音乐/通话时间: 16小时	喇叭直径及阻抗: 直径40mm & 32欧
电池: 锂离子 3.7V/400mAh	支持: A2DP/AVRCP/HSP/HFP
充电环境温度: 0 -45℃	使用环境温度: -10-60° C
音频输入线: 3.5mm插头音频线	蓝牙版本: 4.1 净重: 218g
	4....

