X5
Riding Bluetooth headset
instruction manual

1.Product introduction

1. Switch on and off：
   Press and hold the "function button" and "mode button" at the same time for 2S to turn on/off.
2. Function button:
   In the power on state, short press twice to turn off the colorful light (the default light is turned off when shipping).
   When connected to Bluetooth, press and hold for 1.5S to start the mobile phone voice assistant；
   Long press the function button for 10S to reset.
3. Mode button：
   short press 1 time to turn on/off intercom mode，
   Double tap to enable/disable music sharing.
   long press 2S in intercom mode to start intercom pairing.
4. Volume+button：
   short press volume increase, Long press the next song
5. Volume-button：
   short press volume reduction, long press the last song.
6. Simultaneously short press the Volume + and Volume - button to disconnect the current Bluetooth connection; Simultaneously press and hold the Volume + and Volume - button for 2S to turn off/on the microphone.

2. Indicator light description



1. Mode button light：
   Searching for Bluetooth: blue light flash
   Connection successful: lights are always on
2. Indicator light：
   Power-on status： RGB light gradient
   Charging status: green light is steady on
   Fully charged: Lights off
3. Charging port：
   Type-c charging port for product charging
4. Microphone jack：
   For connecting a microphone

3. Helmet-mounted

3-1 3M adhesive installation

1.Tear off the release paper from the adhesive tape of the mounting seat and attach it to the left side of the helmet .

2. Slide the earphone in and hear the sound of fixation. At this time, the earphone has been fixed on the bracket .

3-2 Clip-on base mount

1. Clip the clip-type base to the left side of the helmet, note that the clip needs to be snapped into the inside of the helmet.

2. Slide the earphone in and hear the sound of fixation. At this time, the earphone has been fixed on the bracket .

4. Headset installed

4-1 Half helmet mounting

You can choose the microphone you need (full helmet/ half helmet) for replacement and installation.

1.Tear off the deform paper of the horn magic sticker, stick the magic sticker in the ear pocket of the helmet, and fix the horn on the newly attached Velcro sticker .



2.(Half helmet) Remove the deform paper from the microphone and attach the magic sticker to the left side of the helmet .

3.Install the microphone at a distance of 1-2cm from the user's mouth.

4.Plug the microphone cable into the product .

4-2 Full helmet mounting

You can choose the microphone you need (full helmet/ half helmet) for replacement and installation.

1.Tear off the deform paper of the horn magic sticker, attach the magic sticker to the ear pocket of the helmet, and attach the horn to the newly attached Velcro.



2.(Full cover) Remove the deform paper from the microphone and attach the magic sticker to the center front of the helmet.

3. Place the Velcro over the user's mouth .

4.Plug the microphone cable into the product .



5. Main Function

5-1 Phone function

1. Connect the phone

2. Answer/hang up the phone

3. Reject a call

4.Mobile phone voice assistant

5. Volume increase

6. Volume decrease

5-2 Music function

1.Play/pause

2.Next song

3.Previous track

4.Disconnect Bluetooth: Press volume + and volume - at the same time to disconnect the current Bluetooth connection.

5-3 Music sharing feature

1. After powering on, short press one of the mode button 2 times to start music sharing, and the other one can wait for the connection (the connected one needs to be in a state of not connected to Bluetooth) .

5-4.Intercom model

1. Short press the M button to enter the intercom mode.
   Note: Both machines must enter the intercom mode.

2. After entering the intercom mode, long press the M key of one of them to start the search and pairing, and there will be a prompt sound after the pairing is successful.

3. In the intercom mode, long press the volume up and volume down at the same time to turn off the microphone; after the microphone is turned off, the other party cannot hear your voice, but you can hear the other party's voice.



Note: In the intercom mode, you can connect Bluetooth to play music (or navigation, call) at the same time, and the music (or navigation, call) sound will leak in and out when the intercom is turned off.

In the intercom mode, when answering a call, press and hold the plus and minus keys at the same time to turn off the one-way mute function microphone. At this time, a private call can be made, and the intercom party cannot hear the content of the call.

5-5 Connect with other brands

1. X5 initiates pairing
Power on (X5)， short press the mode button to enter the intercom mode， long press the mode button to search (other brand machines need to enter the intercom mode)

2. Other brands of machines initiate pairing
Power on (other brands machines)， turn on the intercom mode， search for pairing (X5 needs to enter the intercom mode)

6. Product specifications

Name	Riding Bluetooth headset
Model	X5
Bluetooth version	5.0
Weight	50g (± 3g)
Size	90X50X25mm
Battery type	Lithium ion battery
Battery capacity	3.7V/1000mAh
Charging time	< 2H
Work time	40H
Waterproof level	IPX6
Bluetooth distance	30m
Intercom distance	1000m MAX
Music sharing distance	50m

X5 骑行蓝牙耳机
说明书

1.产品介绍



1. 开关机：按住功能"和"音量减"2S开机/关机。
2. 功能键：开机状态下，按住该键可开启/关闭蓝牙连接。
   长按开机：
   长按该键设定至少10S后，长按1.5S唤醒手机语音助手。
3. 音量+键：按住该键1S，长按下一曲。
4. 音量-键：按住该键1S，长按上一曲。
5. 音量键：按住该键2S，长按关机。
6. 长按音量+键+音量-键将开启或关闭麦克风。
7. 关闭/打开麦克风：同时长按音量+键2S关闭/打开麦克风。

2. 指示灯说明



1. 开机状态：蓝牙连接时：蓝灯常亮闪烁
   蓝牙连接成功：灭
2. 充电灯：开机状态：灯常亮；关机状态：灯常亮
3. 指示灯：开机状态：RGB灯光渐变
   充电状态：绿灯常亮
   充满电状态：灯灭
4. 麦克风插口：用于外接麦克风
5. 充电口：Type-C充电口，用于产品充电

3. 头盔安装

3-1 3M胶安装

1.将胶座安装底座撕下"胶粘面"，粘在头盔侧

2.将耳机滑入卡槽听到固定声，检查牢固度，无松动

3-2 夹式底座安装

1.将耳机滑入卡槽听到固定声，注意牢固度，无松动

2.将耳机滑入卡槽听到固定声，检查牢固度，无松动

4. 耳麦安装

4-1 半盔头盔安装

选择自己需要的麦克风（全盔/半盔）来更换安装

1.将下侧胶条粘贴在头盔内耳朵位置，

将魔术贴粘在头盔内耳朵位置上，

将魔术贴粘在头盔内耳朵位置中间偏前位置粘贴好喇叭魔术贴上

2.（半盔）将麦克风上的魔术贴撕下，将麦克风粘贴在头盔安装



3.（全盔）将麦克风上的魔术贴撕下，将麦克风粘贴在头盔安装中间

4.将麦克风插入喇叭产品上

4-2 全盔头盔安装

1.撕下侧面魔术贴背面胶条，将麦克风粘贴在侧面魔术贴上

2.（全盔）将麦克风上的魔术贴撕下，将麦克风粘贴在头盔安装中间

3.将麦克风粘贴在头盔上

4.将麦克风插入喇叭产品上

5. 主要功能

5-1 手机功能

1.连接手机

2.接听/挂断电话



3.拒绝电话



4.手机语音助手

5.音量调节

6.减小音量

5-2 音乐功能

1.上一曲

2.下一曲

3.上一曲

4.暂停播放/开始播放

5.音量调节

6.减小音量

5-3 音乐分享功能

1.开机后，短按某一台机器2下启动音乐分享，

另一台机器等待连接即可（另一台机器连接蓝牙后方

可连（Connection）。

5-4对讲功能

1. 开机后短按两下启动麦克风分享模式，

长按（2S）进入对讲模式

2. 入对讲模式后长按两下一台开始搜索，

此时搜索到对讲机后会有提示音

3. 对讲机下，同时长按音量加和音量减开启/关闭麦克风，

关闭麦克风后另方无法听到对方，但可以听见对方声音

4. 在对讲机下，同时按音量加和音量减可以单独关闭麦克风，

关闭麦克风后对方无法听见自己说话，但可以听见对方声音

5. 对讲机下，同时长按音量加和音量减开启/关闭麦克风，

关闭麦克风后对方无法听见自己说话，但可以听见对方声音

6. 对讲机下，短按两下音量+和音量-可单独开启或关闭麦克风

5-5 与其他品牌连接

1. X5主动连接

开机（X5）， 短按两下启动麦克风分享模式，长按两下启动

（其他品牌机需要进入对讲模式）

2.其他品牌机连接X5对讲模式

（其他品牌机需要进入对讲模式）

开机（其他品牌）， 打开对讲模式，进行搜索配对

（X5需要进入对讲模式）

6. 产品规格

名称	骑行蓝牙耳机
型号	X5
蓝牙版本	5.0
产品重量	50g（± 3g）
产品尺寸	90X50X25mm
电池类型	锂离子电池
电池容量	3.7V/1000mAh
充电时长	< 2H
工作时长	40H
防水级别	IPX6
蓝牙距离	30m
对讲距离	1000 米 MAX
音乐分享距离	50m

FCC Statement

This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.