



Bone Conduction BT Headphones R18 User Manual

Function Guidance



You can hear outside voice while listening music. Release the ears, free enjoy!

Wearing Way

As show in the picture, hang the earphone on the back of the neck, and at the same time, the earphone should stick on the cheekbone in front of the ear rather than on the ear.



Pairing Method

- Long press the MFB(power button) for 2 seconds to power on the headphones.
- When the blue lights flash slowly, the Headphones search for the last connected device and automatically paired
- The red and blue lights flash alternately when entering a new pairing mode after headphones power on (if it doesn't enter pairing mode, please power off, then press the "MFB(power Button)" for 5 seconds power on and until the red and blue lights flash alternately).
- Open the BT set, Then search the BT devices and choose pairing name "R18" headphones. Enter "0000" pin code if needed.
- The blue LED flash slowly when it's paired successfully.

Note:

When the connection distance with the device exceeds the effective distance of Bluetooth(10 meters/33 feet), the BT headphones will disconnect from the devices. After that, once they are in the range of 33 feet, they will automatically reconnect. However, if the headphones have disconnected more than 5 minutes, you may need to double click the "MFB(Power Button)" to reconnect the devices.

1. If you turn off the device connected to the BT headset, it will automatically disconnect. When turned on again, the BT headset will automatically connect back to the last BT device.

2. In the off state, press and hold the MFB (power) button for 5 seconds to turn on the headset, Enter the pairing mode, at this time other mobile phones can search for and connect to this BT

Connect Two Devices Fuctions

Press MFB(Power)Button 5 seconds to power on, let the headset re-enter the pairing mode, After pair the second BT phone. please enter the BT of the first mobile phone, connect again to the "R18" that was disconnected just now

Multi-way calls

- During a call, the second call is incoming, double-click the MFB (power) button to connect Listen to the second call and hang up the first call, press and hold MFB(power)Press is to reject a new call.
- During a call, the second call is incoming, triple-click the MFB (power) button to connect Listen to the second call, hang up the first call.
- During a multi-way call, Short press the MFB (power) key for 1s to Switch the call, short press the MFB (power) key to hang up the current call, and then Short press the MFB (power) key once to hang up the last call.

Charging Method

With a standard USB to Micro USB charging cable (attach with the package) to connect the headphones and the USB port of your PC or charging source. the headphones will be charged. it takes 2 hours for full charging. When charging, the LED indicator is in RED, after charging finished, the LED indicator will turn to BLUE.

Note:

1. Because the battery may lose some power in the storage, here kindly suggest charging your headphones full before the first time you use it.

2. When charging, the headphones can not be used.

3. If not use headphones for a long time, suggest charging it once a month to keep battery life.

4. The BT headphones exceeds 5 minutes without connecting the device, The blue headphones automatically turns off..

LED Indicator

Red light keep flashing each 3 seconds: low power

Red led lighting: charging

Blue led lighting: charging complete

Blue and red led flash alternately: pairing mode

Blue light flash slowly: connected/calling/playing music

Blue light flash quickly: incoming call

Blue led double flash slowly: Unconnected

Product accessories

USB Cable(USB to Micro USB)

Earplug



Specification

The speaker type: Bone conduction technology speakers

Standby time: Up to 10 days

Play time: Up to 5 hours(Test data at medium volume, the volume changes Large, shortened time)

Effective range: 10 meters/33 feet(no obstacle)

Charging time: 2 hours

BT : 5.0

Operation Tips

Operation	Headset button controller	Warning tone
Power on	Long press MFB (power) button for 2 seconds	Power on
Power off	Long press MFB (power) button for 2 seconds	Power off
Answer a call	Click the MFB (power) button	No
End a call	Click the MFB (power) button	du du
Reject a call	Double-click the MFB (power) button	No
Pause/ Play the music	Click the MFB (power) button	No
The previous song (*)	Triple-click the MFB (power) button	No
The next song (★)	Double-click the MFB (power) button	No
BT is connected	/	paired
BT disconnected	/	dingdong
Enter pairing mode	Long press in the off state to enter the pairing mode and wait for the MFB (power) button to connect for 5 seconds	Ready to pair
Low battery	/	Battery low

*For different types of Bluetooth devices, because of different operating systems or music player, this function may be different.

Fault Diagnosis and Solution

Fault	Possible reasons	Solutions
Can not power on	Check whether the battery is low	Full charging it
Can not automatic connection	Click if enters standby mode	Double click on the multifunction button to reconnect or power on once time
Can not discover BT headphones	Not enter BT pairing mode	Long press the MFB (power) button in the off state for 5 seconds

Storage & Maintenance

- Please put the BT headphones in a cool and dry place. The working temperature is 0-45 ° C(32~113° F). In cold or hot highly humid place will reduce the battery life. After long storage, please charge before use
- Headphones resistance to water, but not waterproof. please don't put the headphones into water. If there is water on it, please use soft cloth to wipe dry.
- Use soft dry cloth to clean headphones.
- Do not use any sharp objects in connect with headphones.
- Do not put headphones at a too high or too low temperature.
- Do not charge the headphones in a humid environment.

FCC Caution.

(1)§ 15.15 Labelling requirements.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

§ 15.21 Changes or modification warning

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

§ 15.105 Information to the user

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures.

-Reorient or relocate the receiving antenna.

-Increase the separation between the equipment and receiver.

-Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.



骨传导耳机 R18 使用说明书

功能指示



释放双耳，听音乐的同时还能聆听外面的声音，自由、安全。

佩戴方式

如图示，把耳机挂在脖子后面，同时扬声器贴在耳朵前的颞骨上，而不是放在耳朵上。



蓝牙配对步骤

- 长按MFB(power)键2s, 开启耳机
- 蓝灯闪烁时，耳机蓝牙搜索上一次连接过的设备，并自动配对
- 红蓝灯交替闪烁时，进入新的配对模式(如果没有出现，请关机，并长按MFB(power)键5秒开机进入配对模式)
- 开放手机的蓝牙功能，搜索蓝牙设备，选择“R18”耳机，如果需要输入配对码，请输入“0000”
- 配对成功后，蓝灯慢闪

注意：

当与设备的连接距离超出蓝牙的有效距离(10米或33英尺)时，蓝牙耳机将与设备断开连接。此后，一旦它们再次处于蓝牙有效距离范围内，它们会自动重新连接，但是，如果蓝牙耳机与所连设备断开很长一段时间(超过5分钟)，您可能需要双击MFB(power)键，以重新连接设备。

1、如果关闭与蓝牙耳机连接的设备，蓝牙耳机会自动断开。再次打开时，蓝牙耳机会自动回连上一次的蓝牙设备。

2、关机状态下，长按MFB(power)键5秒开机，耳机进入配对模式，此时别的手机可以搜索并连接上此蓝牙耳机。

多点连接一拖二功能

按配对步骤，配对第一个手机后，关闭耳机，然后长按MFB(power)键5s开机，让耳机重新进入配对模式，再配对第二个蓝牙耳机。此时进入第一个手机的蓝牙设置界面，再次连接刚才断开的“R18”。

多路通话

● 通话中，第二路通话呼进，双击MFB(power)键接听第二路通话挂断第一路通话，长按MFB(power)键1s拒接新的一路通话

● 通话中，第二路通话呼进，三击MFB(power)键接听第二路通话，挂起第一路通话

● 多路通话过程中，长按MFB(power)键1s在两路通话中切换，短按MFB(power)键挂断当前通话，再次短按MFB(power)键挂断最后一路通话

充电方式

用标准的 USB 转 Micro USB 充电线(随包装附送一条)将蓝牙耳机和你的个人电脑或墙充电电源插座的USB口连接即可充电。大约2小时可以充满，充电的时候LED指示灯为红色，充电完成后即变成蓝色。

注意：

1、由于电池在储存的过程中有可能损失电量，建议在第一次使用前先给耳机充电。

2、在充电的过程中蓝牙耳机是不可使用的

3、长时间不使用，建议每个月充电一次，以保持电池寿命。

4、蓝牙耳机在没有连接设备的情况下超过5分钟，蓝牙耳机自动关机。

LED灯提示

红色每隔3S闪烁1次: 电量不足

红色常亮: 正在充电

蓝色常亮: 完成充电

蓝色与红色交替闪烁: 配对模式

蓝色慢速闪烁: 已连接/正在拨打电话/正在播放音频

蓝色快速闪烁: 接到来电

蓝色慢速双闪: 蓝牙耳机与配对收没有配对上

产品配件图

USB充电线(USB转Micro USB)

耳塞



规格参数

扬声器类型: 骨传导技术扬声器

待机时间: 长达10天

播放时间: 长达5小时(中等音量下测试数据, 音量变大, 时间缩短)

有效距离: 10米

充电时间: 2小时

蓝牙版本: 5.0

故障诊断及解决措施

问题	故障原因	解决措施
不能开机	检查电池是否充满电	给电池充满电
不能自动连接	蓝牙耳机是否进入待机模式	双击多功能键或者重新开机
无法配对蓝牙耳机	没有进入配对模式	关机状态长按MFB键5秒

存储与维护

- 请将蓝牙耳机存放在阴凉，干燥的地方。工作温度 0~45°C (32~113°F)。在冷/热环境或高度潮湿的地方工作会降低电池的寿命。长时间存储后，请在使用前先充电。
- 蓝牙耳机抗水，但是不防水。请勿将耳机放入水里。假如有水，请使用干净的软布擦拭干净。
- 请使用柔软的干布清洁耳机。
- 请勿将任何尖锐物体接触耳机
- 请勿将耳机置于温度极高或极低的环境下。
- 请勿在潮湿的环境下给耳机充电。

产品保修单

用户姓名: _____ 联系电话: _____
购买日期: _____ 购买渠道: _____
联系地址: _____

保修条款

- 用户购机时，随机附带有一本说明书及保修卡。用户填好后妥善保管，作为保修凭证。
- 自购机之日起，一年之内耳机在正常使用下出现问题，持卡用户可免费享受维修服务。
- 以下不属于保修范围：
A - 保修卡无销售单位签字或盖章；
B - 人为或不可抗拒因素造成损坏；
C - 机器正常磨损；
- 若因人为，超过保修期及不可抗拒因素造成的故障，我们将收取维修成本。
- 产品出现故障需要返厂保修时，请联系我司。并填好具体的姓名、地址、电话及故障现象。