

LOGO PN: 710-000190-001


Technical drawing of the back of the LV-AT3-172 device, showing dimensions and labels. The drawing includes a callout box labeled '4b' pointing to the top-left corner of the device's mounting area.

Dimensions:

- Overall width: 51,5
- Overall height: 33
- Mounting hole diameter: 8
- Mounting hole offset from top edge: 15
- Mounting hole offset from left edge: 20
- Mounting hole offset from bottom edge: 27
- Mounting hole offset from right edge: 40
- Mounting hole offset from top edge (inner): 22
- Mounting hole offset from bottom edge (inner): 21
- Overall width (inner): 52
- Overall width (inner): 60

Labels and Text:

- Carnegie Technologies, LLC
- WARNING - EXPLOSION HAZARD - BATTERIES MUST ONLY BE CHANGED IN AN AREA FREE OF IGNITABLE CONCENTRATIONS.
- REPLACE BATTERY WITH LITHIUM CR123 ONLY
- TEMP: -20C TO +55C
- IP67
- MODEL: LV-AT3-172
- CL I, DIV 2, GRP A,B,C,D, F14
- FCC ID: 2ARIP-0002
- IC: 24612-0002
- COO: USA
- support.longviewiot.com
- MET (Marking)
- E114733 (Marking)
- ELECTRICAL AND HAZARDOUS LOCATIONS

DRAWN BY	DATE	UNLESS OTHERIWSE SPECIFIED DIMENSIONS ARE IN MILLIMETERS DIMENSION TOLERANCES .X ± .5 .XX ± .10 ANGLE ± 1/2° 3.2  FINISH IN MICRONS	 THIRD ANGLE PROJECTION	 CARNEGIE TECHNOLOGIES				
			THESE DRAWINGS AND SPECIFICATIONS AR E THE EXCLUSIVE PROPERTY OF CARNEGIE TECHNOLOGIES. ISSUED IN STRICT CONF IDENCE AND SHALL NOT, WITHOUT PRIOR WRITTEN PERMISSION OF CARNEGIE TECHN OLOGIES, BE REPRODUCED, COPIED OR US ED FOR ANY PURPOSE WHATSOEVER, EXCEP T THE MANUFACTURE OF ARTICLES FOR CA RNEGIE TECHNOLOGIES.	Title ASSET TRACKER, CR123 SPEC, LASER ETCHING				
TH				Scale: 1.000	Size B	Drawing No. 790-000031-101	Rev	Sheet 1 of 1

Carnegie Technologies, LLC

WARNING - EXPLOSION HAZARD -
BATTERIES MUST ONLY BE CHANGED
IN AN AREA FREE OF IGNITABLE
CONCENTRATIONS.

REPLACE BATTERY WITH LITHIUM CR123 ONLY

TEMP: -30C TO +55C

IP67

MODEL: LV-AT3-172

CL I, DIV II, GRP A,B,C,D, T4

FCC ID: 2ARIP-0002

IC: 24612-0002

COO: USA



E154733

ELECTRICAL
AND HAZARDOUS
LOCATIONS



support.longviewiot.com

