XG-31

真分离式无线蓝牙耳机

BLUETOOTH 5.0

用户使用手册

双耳机使用模式-自动匹配

（此模式适合初次使用）

耳机放入充电仓

1.(1)耳机放在充电仓内：耳机放于充电仓合盖之后，打开充电仓盖子之后，耳机（左右两边）自动开机，红蓝灯对闪，提示音“开机”两耳机进入配对状态，配对成功后提示音“配对完成”，只留一边耳机灯对闪，手机打开蓝牙，搜索配对名称“XG-5.0”配对完成提示音“配对完成”后蓝灯慢闪；

(2)开盖后马上取出两只耳机：耳机（左右两边）自动开机，红蓝灯对闪，提示音“开机”两耳机进入配对状态，配对成功后提示音“配对完成”，只留一边耳机灯对闪，手机打开蓝牙，搜索配对名称“XG-5.0”对完成提示音“配对完成”后蓝灯慢闪；

充电仓开盖

开盖耳机红蓝双闪自动配对

2.双耳模式连接成功后是不是特别简单，之后每次充电完成之后打开充电仓，耳机秒开机后回连您的手机设备，不需要多余重复的操作

双耳机使用模式-手动匹配

（当自动匹配失效时使用）

1.双耳机分别开机键3秒（此时两耳机蓝灯慢闪，提示音为：开机），然后进入配对模式，会在7-10秒后双耳配对完成，提示音“配对完成”，然后主耳进入红蓝对闪进入配对模式，打开手机蓝牙功能界面搜索，找到配对名称：XG-5.0，然后点击配对，提示音“配对完成 ”，则完成配对进入使用状态。



轻触耳机面盖3秒开机

2.如果有曾经连接过本手机蓝牙设备的耳机，同时开机后则会秒回连接你的蓝牙设备，不需要多余重复操作

双耳机-神操作功能讲解



关机

轻触5秒任意一边耳机（R或者L）即可关机

播放/暂停

轻触任意一边耳机（R或者L）即可实现播放暂停



拒接电话

轻触1S拒接,通话时轻触主耳机（L耳机)即可以接通或者挂断电话



双击上一曲
三击音量减



双击下一曲
三击音量加

上一曲下一曲

播放状态时，左耳双击即可切换上一曲，右耳双击即可切换下一曲

三击L边音量减，三击R边音量加

音量加“+”和音量减“-”

使用状态下，L边三击即可音量减“-”，R边三击即可调节音量加“+”

呼叫智能语音助手（如Siri）

使用或者待机时，轻触1.5秒左右主耳机（L耳机）即可唤醒

关闭智能语音助手（如Siri）

使用Siri时轻触1.5秒左右主耳机（L耳机）即可关闭

注意：双耳机模式下，接听电话/通话/语音模式/下只有主耳机(L耳机)，有声音支持收音，副耳机（R耳机）暂时封闭，无声状态，要结束语音状态，自动恢复双耳正常模式

你需要单独使用一只耳机（单耳模式）请看这里

1.单独使用主耳机（L耳机）从充电舱充电状态拿出后，将自动进入搜索配对状态，您可以直接在手机蓝牙功能界面上搜索XG-5.0,并点击连接该设备，并且进入使用。此时副耳机（R耳机）请放回充电舱里面进入充电关机状态。

2.1单独使用副耳机（R耳机）从充电舱充电状态拿出后，请开机轻触5秒，将耳机进入搜索配对状态您可以直接在手机蓝牙功能界面上搜索XG-5.0并点击连接该设备，并且进入使用.

如何给耳机进行充电？

1.左右耳机放入充电舱，耳机电量显示窗口亮绿灯，电量分别一格一格同步递增到四格，然后退到一格，循环跑动则表示充电状态，直到四格绿灯跑满之后则表示耳机电量充满，最后最后耳机和仓电舱显示分别灯灭。

如何给充电舱进行充电?

1.使用正常5V充电器给充电舱进行充电，充电舱充满电时，蓝灯常亮状态

耳机使用时请留意一下信号注意事项：

1.佩戴方法很重要，避免信号天线被耳朵内部所阻挡住，请根据介绍页佩戴方法进行佩戴;
2.双耳模式下任何一边耳机用手捂住都会导致信号不良情况，目前此类技术耳机均有这个情况，因为用手相当于阻断了两个耳机之间的信号连接;
3.双耳模式下耳机与主耳机（L耳机）中间一定不能有太多干扰性强的障碍物，并且需要确保两者之间的距离，莫影响了手机与主耳机（L耳机）间的信号传输;
4.双耳模式下，若副耳机（R耳机）有偶尔断连问题，属于正常现象，毕竟蓝牙属于无线信号传输，就跟WiFi网络一样，有时候不稳定属于正常可能，此时刚好信号传输受到干扰，请稍等片刻或者换一下位置即可解决

耳机佩戴方式



如何给耳机充电舱充电?

- 使用厂家合格的充电线或充电器（输出电压为DC5V/1A）给产品充电
- 充电仓充电的过程中根据电量的多少分为4个等级来显示电量的容量，比如显示25则表示充电仓剩余25%电量，50则表示充电仓剩余50%电量，75则表示充电仓剩余75%电量，100则表示充电仓满电。



产品参数

耳机产品参数：

型号：XG-31	耳机通话时间：4h
版本：5.0+BLE	耳机音乐时间：4h
充电电压：DC 5V	通讯距离：10m
电池电压：3.7V	电池容量：40mAH
耳机充电时间：0.8h	耳机待机时间：120h

充电仓参数：

输入电流：5V/1000mA
输入耳机电流：5V/100mA
充电仓电池容量：400mAH
充电仓可以充电耳机次数：2.5次

警告

1.请勿以任何理由拆除或维修改装耳机，否则可能会导致起火电子击穿，甚至彻底损坏本产品。

2.请勿将设备置于温度过低或者过高（0℃以下或45℃以上）的环境下。
3.请避免靠近儿童或者动物的眼睛使用设备指示灯。
4.请勿在雷暴天气下使用该设备，雷暴可能导致设备工作不正常并增加触点的危险。
5.请勿用油以及其他挥发的液体擦拭本产品。
6.请勿将设备接触液体弄湿。

注意

长时间使用耳机可能会造成听力损害，请合理安排使用时间

XG-31

TWS wireless earphones



TWS wireless earphones
Model: XG-31
Input: 5V ⎓, 1000mA
FCC ID: 2AS2T-XG-31
Shenzhen Xintu Century Technology Co.,Ltd
Importer: xxxx Address:xxxx Made In China

User manual

Dual earbuds mode- automatic pairing

(This mode is suitable for the first-time use)

1. (1) The earphones were putted in the charging case and close the case: After opening the cover of the charging case, the two earphones will power on automatically and not need to take them out. The red and blue lights of the earphone flash, and the prompt tone "power on" for pairing status. The prompt tone "pairing" after the two earphones pairing is successful, only one earphone's light flash. Turn on Bluetooth function of your phone, and search and click the bluetooth name "XG-5.0" . Pairing completion prompt tone "Connected" and the blue light flash slowly.

(2) Open the case and take two earphones out immediately: the two earphones also will power on automatically. The red and blue lights of the earphone flash, and the prompt tone "power on" for pairing status. The prompt tone "pairing" after the two earphones pairing is successful, only one earphone's light flash. Turn on Bluetooth function of your phone, and search and click the bluetooth name "XG-5.0" . Pairing completion prompt tone "Connected" and the blue light flash slowly.

Open the charging compartment

Open the headset red and blue double flash automatic pairing

device
XG-5.0

3. Is it particularly simple after successful connection in binaural mode? After the charging is completed, open the charging compartment, and connect the headset after turning on the phone in seconds Your mobile device, no need for redundant operations

Dual earbuds mode - manual pairing

(used when automatic pairing fails)

1.Press the multi-function button of the earphone for about 3 seconds until the led flashes in blue slowly and the earphone will say "turn on Pairing" . The earbuds will enter into the pairing mode ,they will finish pairing after 7-10 seconds. The earphones will say. "pairing sucess" .The led of the left earphone flashes in red and blue alternately to enter into the the connection mode,then turn on the function on your phone and select : XG-5.0 on your list. The earphone will say "Connected" once they are paired. Start enjoying music or making phone calls.



Light touch the earphone case for 3 seconds to turn on the earphones.

2. If there the earbuds have connected to the device of this mobile phone before, it will connect to your device in seconds after turned on, without repetitive operation.

Setting
Bluetooth
device
XG-5.0

Basic function opertation of TWS earbuds



Turn off

Light touch 5 seconds any side of the earbuds (R or L) to turn it off

play / Pause

Light touch any side of the earbuds (R or L) to play / Pause



Reject the phone call

Light touch the earbuds for 1 second to reject the phone call. Light touch the main earbud (Left earbud) to answer the phone call or hang up the phone call.



Double click to switch to the previous song.Triple click to decrease the sound volume.



Double click to go to the next song.Triple click to increase the sound volume.

previous song next song

In the music play state,double click the left earbud to switch to the previous song.and double click the right earbud to switch to the next song.

Triple click the left earbud to decrease the sound volume. Triple click the right earbud to increase the sound volume.

Sound volume increase and sound volume decrease

In the using state,triple click the left earbud to decrease the sound volume.Triple click the right earbud to increase the sound volume.

Wake up smart voice assistant (such as Siri)

when the earpphones are under the using state or standby state, light touch the the main earbud (left earbud) for 1.5 second to wake up Siri.

Turn off smart voice assistant (such as Siri)

When using siri, light touch the main earbud(the left earbud) for 1.5 second to turn off Siri.

Note: In the dual earbuds mode, when in the situation of answering the phone call / talking / voice mode , only the microphone of the Left earbud can work normally, the microphone of the right earbud will not work at the moment. When phone call is finished, the earbuds will enter into the the dual earbuds mode automatically.

Singel earbud mode:

1.Use the main earphone (Left earbud) separately. Take the Left earbud out of the charging case, it will enter into the pairing state automatically , you can search for XG-5.0 directly on the list of function for mobile phone ,and click to connect the deviee, then come into use. At the same time, the sub-earbud (right earbud) should be placed into the charging case to get charged and it should be turned off.

2.Use the right earphone separateiy. Take the right earbud out of the charging case,light touch the earphone for 5 seconds,it will enter into the pairing state automatically , you can search for XG-5.0 directly on the list of function of mobile phone ,and click to connect the device, then come into use.

How to charge the earphones?

After the earphones on both side are placed into the charging case, the light of LED display screen which shows the battery amount will flash in green, the quantities of green lights on LED display screen will increase from one to four gradually, then decreases from four to one. If the quantities of green lights is always changing ,it means the earphones are charging. When the four green lights are shown on LED display screen, it means the earphone are fully charged , the green lights on the LED display screen and the lights on earphones will turn off automatically.

How to charge the charging case?

Use the 5V power adapt to charge it.
When charging completed, the blue light is constant on.

About Signal

1.Please notice the wearing method, do not cover the earphone by ear to prevent interruption of signal.
2.Do not cover any one earbuds on the dual earbuds mode by hand, or it will result the interruption of signal.

3.Please use this earphone under its working range (10 meters) and for best results avoid obstacles in between the connected devices.
4.On the dual earbuds model, sometimes the connected of "R" may be interrupted, please check the using condition or the working range.

How to wear headphones



How to charge the charging case?

- Please use the power cord supplied to charge the charging case.
- The charging process of the charging compartment is divided into 4 according to the amount of electricity Level to show the capacity of electricity, for example, display 25 means25% of the remaining power in the charging bin, 50 means the remaining power in the charging bin 50% power, 75 means 75% power remaining in the charging compartment,100 means the charging compartment is fully charged.



Parameters of earphones:

Specification:
The specification of earbuds:
Model name: XG-31
Version: 5.0+BLE
Charging Voltage: DC 5V
Battery Voltage:3.7V
Charging time: 0.8h
Talk time: 4H
Music time:4H
Work range:10m
Battery capacity: 40mAh
Standby time: 120h
The specification of charging case:
Input Current: 5V/1000mA
Input earbuds Current: 5V/100mA
Battery capacity:400mAh
Charging times for earbuds: 2.5times

Warning

1. Please do not take the earbuds apart and remodel, otherwise, it may cause electrical breakdown by the fire or even completely damage the product.
2.Please do not put the product to too high or too low temperature(Below 0°C or above 45°C).
3.Please avoid using the device indicator light near the eyes of children or animals.
4.Please do not use the device under thunderstorms. It may cause the device to malfunction and increase the risk of electric shock.
5.Please do not wipe the product with oil or other volatile liquids.
6.Please do not let the device get wet with liquids.

Note

It may cause hearing damage under longtime using, please arrange the use time reasonably.

FCC Instructions:

This product has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This product generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If the product does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the product and receiver.
- Connect the product into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

Warning: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the product.