安科智能

Smart Socket
AK-WS1102

Thank you for purchasing the AK-WS1102 Smart Plug. Please read fhis user manual.Carefully and keep if for future reference.If you need any assistance,please contact our.support team with your product model number and Amazon order number.

Package Contents

Smart plug
User Manual
Warranty Card

Product Diagram



Specific ations

Model	AK-WS1102
Input/Output	110-125V AC 50/60Hz 10A
Max Load	10A
Max Power Output	1250W
Apps Supported	Amazon Alexa. Google Home IFTTT
System Requirements	iOS 8/ Android 4.4 or higher
Wi-Fi Network Support	2.4GHz

Getting started

Compatibility Requirements

- A smartphone or tablet running ios 8/ Android 4.4or higher
- A 2.4GHz Wi-Fi connection

Inst alling the Smart Life App

Search for ‘Smart Life’ on the Apple App StorGoogle Play or scan fhe QR code below and download the app

Setting up the Smqrt Plug

1.Plug fhe AK-WS1102 into a wall socket
2.Plug your AC-powered device into AK-WS1102's socket

Note:Don' f exceed fhe maximum power output of 1250W

3. Connectyour phone or tablet to your 2. 4GHz Wi-Fi network

Note:This smart plug only supports 2.4GHz (not 5GHz)networks

4. Launch the Smart Life app and log in.For first-time users follow fhe in app instrucfions to register



5. Once logged in, tap **Add Device** or tap the+button in the top-right and select the device type that you've plugged into the smart plug from the list



6.On the smart plug, press and hold the power button for 5 seconds (until blue LED indicator flashes rapidly) to enter connection mode



7.On the app,tap **Confirm indicator flash rapidly**, enter your Wi-Fi password and fhen confirm



8.Once connected,setup is complete and you can start using the smart plug to control power to the device that' s plugged into it



AP Mode

If quick setup isn't successful for any reason, you can use the AP mode to manually configure your smart plug (see in-app instructions on how to set up)

LED Indicator

Indicator	Status
Off	Power off
Blue flashing rapidly	In connecfion mode
Blue flashing slowly	Connecfing
Solid blue	Connecfed

Using fhe Smart Plug

Countdown

Set this to automatically turn on or off device plugged into the smart plug after time haselapsed

Timer

Set up a schedule of specific times and days to automatically turn on or off appliance plugged into the smart plug.Great for organizing and simplifying your daily life



Create Your Own Scene

Set multiple devices to automatically turn on or off together in specific situations,like switching things on when you get home



Using AMazon Echo Quick Guide

Preparation

Amazon Alexa APP Account
Smart Life APP Account
(Users need to register their own account, select region as "The United States)"
Echo, Echo Dot, Tap and other Amazon voice-operated devices
Tip: Rename the device after configuring successfully. The name of the device is recommended to use easy pronunciation of the English words

Set your Echo speaker by Alexa APP

1. Sign in with Alexa account password(Ifnot registered, sign up first) After log in, click the menu at the top left. then click the Settings , "and choose set up a new device"
2. Choose a device (for example,Echo). when the right page appears,press the small button continuously on your Echo device until the lights turn yellow. Then click continue on APP. (Note: at this time the mobile phone can not open a variety of VPN software)

3. Choose user s WiFi and wait for a few minutes
4. After an introduction video, click next step. It will go to "Home page automatically. Now the echo is connected to Alexa APP through WIFI successfully

Enable our skill in Alexa App

1. Choose skills in the options bar, and then search smart life in the search bar, Select Smart life in the search results, and fhen click Enable

2. Input the user name and password that you had previously register ed When you see the right page, it means that the Alexa account is linked with Smart Life account



Control Smart Socket by Voice

After previous operation succeeded, youcan control socket via Echo.

1. Discover devices: Firstly,users need to say to Echo: "Echo(or Alexa),discover my device"
   Echo will start to finding the devices which is added in Smart Life APP, it will take about 20 seconds to show the result. Or you may click "Discover devices" in Alexa APP, it will show the devices that found successfully.
   Note:"Echo" is one of the wake-up names, which can be any of these three names (Settings):Alexa/Echo/Amazon.
2. **Support Skill List**
   Users can control devices by instructions like below:
   Alexa, turn on [fridge socket]
   Alexa, turn off [fridge socket]
   Attention:The name of the device must be consistent with the addition of Smart Life APP.

Q&A

What can be connected to the smart plug?
Lights,fans,portable heaters,and other small appliances.
Why won't my device connect to the smart plug?
Ensure that the smart plug is in connection mode with blue indicator flashing rapidly.Your device and the smart plug must be connected to the same wi-fi network.

Product Care & Use

- keep away from liquids and extreme heat
- Don't exceed the maximum power output of 1250W
- To reset to factory default settings,press and hold the power button for 8 seconds

FCC Statement

1.This device complies with Part 15 of the FCC Rules.
Operation issubject to the following two conditions:
(1) This device may not cause harmful interference.
(2) This device must accept any interference received, including interference that may cause undesired operation.
2.Changes or modifications not expressly approved by the partyresponsible for compliance could void the user's authority to operate the equipment.
Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
(1) Reorient or relocate the receiving antenna.
(2) Increase the separation between the equipment and receiver.
(3) Connect the equipment into an outlet on a circuit differ ent from that to which the receiver is connected.
(4) Consult the dealer or an experienced radio / TV technician for help.

FCC RF exposure statement:
The equipment complies with FCC Radiation exposure limit set forth for uncontrolled environment. This equipment should be installed and operated with minimum distance 20cm between the radiator and your body.

Warning: Changes or modifications to this unit not expressly approved by the part responsible for compliance could void the user's authority to operate the equipment.