本機２台までペアリング可能２台ペアリング時には
L/R ステレオサウンドがお楽しみいただけます
Bluetooth®
灯り 音楽をもっと身近に
Light and Music even closer

※Bluetooth®はBluetooth SIG,Inc.の登録商標です。

製品仕様

主材料　：ポリカーボネイト / シリコンゴム / フロストガラス
本革 / 木 / 鋼 / 塗装
本体サイズ　：H287mm(レザーベルト含まず) φ168mm
本体重量　：1.7 Kg
防水　：非防水 (防水性をもたない性能)
連続再生時間：最大 9 時間 (中音量 / 中光量時)
連続点灯時間：最大 17 時間 (光量 100% 時)
動作常温環境：5 ～ 35°C
LED 光源種類：3 段階調光式 LED 0.4w　寿命：40,000 時間
光源色温度 (k) 2,000k　光源照度 (lm) 35ml
内蔵電池　：リチウムイオン充電式電池 3.7 V, 2600mAh
充電方式　：USB Type-C
充電時間　：約 4.5 時間フル充電 (5V-1A)　※充電時の使用可
リチウム電池充電寿命：500 回 (0~100%)
通信方式　：Bluetooth 5.1
注：本機は全ての無線接続 (Bluetooth) 機器とペアリング可能ではありません。
最大通信距離：8m 注：通信距離は目安です。本機を使用される環境により異なります。
スピーカー　：5W
梱包内容　：本体 / USB Type-C / 取説保証書
メーカー保証：お買い上げ日より１年間
製産国　：中国

・本製品の仕様は告知なく変更する場合があります。【2022 年 10 月】

同梱品 / 各部名称 / 主素材



・USB ケーブル Type-C / USB charging cable,Type-C

ペアリング

Bluetooth ペアリング　本機 1：スマホ1

1. ペアリングするスマホの Bluetooth を設定から OFF。
2. 本機 Bluetooth ON/OFF ボタンを長押し、発信音とともにペアリング先検索状態。(Bluetooth ボタン点滅状態)
3. ペアリングするスマホの Bluetooth を設定から ON。Bluetooth リスト中 **LED LanternSpeaker ROOMS** を選択、発信音とともにペアリング完了。

Bluetooth ダブルペアリング 本機2：スマホ1

1. ペアリングするスマホの Bluetooth リスト中 **LED Lantern - Speaker ROOMS** の履歴を全て削除。BluetoothをOFF。
2. 本機 2 台共に Bluetoothスイッチを押し、電源 ON 状態。発信音とともに 2 台ともペアリング先検索状態。(2 台とも Bluetooth ボタン点滅状態 ◀)
片方 1 台 (任意) の Bluetooth ボタンを押す、発信音とともに本機 2 台がペアリングされます。(1 台 ◀ 1 台 ◀ 状態)
3. 上記 3. 操作同様、Bluetooth リスト中 **LED LanternSpeaker ROOMS** を選択、本機 2 台とスマホ 1 台のペアリング完了。

※記載の QR コードにてペアリング方法を動画にてご確認いただけます。

LED ライト ON-OFF / Bluetooth ON-OFF

○　LEDライト LED ライトスイッチ ON-OFF
OFF → 30% → 60% → 100% → OFF

＜Bluetooth 電源スイッチ表示状態＞

- ◀ – ブルー,レッド点滅 / Bluetooth ON / 検索状態
  Flashing in RED-BLUE / Bluetooth ON, Searching
- ◀ – ブルー点灯 / Bluetooth ON / ペアリング完了状態
  for Bluetooth device to connect. Connect successed, BLUE.
- ◀ – ブルー点滅 / Bluetooth ON / 音源再生状態
  Flashing in BLUE, playing music
- ◀ – レッド点灯 / 充電中USB接続中
  Charging, RED
- ◀ – レッド点滅 / 充電中USB接続中/ Bluetooth ON
  Charging, RED / Bluetooth ON
- ◀ – グリーン点灯 / 充電完了 (USB 接続時)
  Charged, GREEN (USB connecting)
- ◀ – グリーン点灯/BluetoothON (USB 接続時)
  GREEN / Bluetooth ON (USB connecting)
- ◀ – グリーン点灯/Bluetooth ON/ 音源再生状態(USB 接続時)
  GREEN/BluetoothON playing music (USB connecting)

使用上の注意

使用上の注意を無視して、誤った取り扱いをすると本製品保証を受けられなくなるばかりではなく、火災や感電などにより人身事故になることがあります。
事故を防ぐために次のことを必ずお守りください。

- 本製品は**非防水** (防水性をもたない性能) 製品です。
  屋外での降雨下などでの使用、放置はしない。
- 火気近くではの使用はしない。
  暖房器具の近くや、長時間直射日光が当たる温度が非常に高い (45°C以上)、または高くなる場所での本製品の使用、放置はしない。(ファンヒーターやガスコンロなどの近く、キャンプファイヤーなど近く、窓際への放置)
- 本製品を高温(45°C以上)になる車中に放置しない。
- 本製品は寒冷地仕様ではありません。
  氷点下以下(0°C)での本製品使用はしないでください。
  機能低下だけのみならず、重大な事故になることがあります。
- 本製品を覆うような使用、覆われてしまう場所では使用しない。
  (布や洋服、カーテンなど)
- 充電状態のまま、放置しない。

免責事項

- 持運び時など、過度な衝撃を与えない。
- 異臭や本体の異常を感じた時は、使用を直ちに止めてください。
  (使用を中止し、株式会社 フォレストにご相談ください)
- **本体の分解、改造、修理はしない。**
  (危険ですので、絶対おやめください)

落下の危険性がない、安定した場所に置いてお楽しみください。

＊本製品はリチウムイオン充電式電池を内蔵しています。

電池の液漏れが生じた場合、素手で触るのは危険です。
電池の液が目に入ったときは、目をこすらず、すぐに水道水などのきれいな水でよく洗浄し、医師の診断を受けてください。
電池の液が衣服についた場合も、すぐにきれいな水でよく洗浄してください。やけどなどの原因になるおそれがあります。
炎症やけがの症状がある場合は、医師の診断を受けてください。

Li-ion

一般ゴミとは別に、リサイクルへ。

補償範囲

当社製品を使用したお客様の製品に故障が生じ、その原因が当社製品の瑕疵による場合、 **お買い上げ１年以内に限り、** 当社製品の代替品の提供または、修理品の提供を無償で行わせていただきます。
ただし、お客様の製品の故障により生じた損害のうち、当社が負担する割合は、お買い上げ頂いた当社製品の価格を上限とさせていただきます。
また、お客様の製品の故障が下記事由に基づく場合は、当社はあらゆる損害賠償責任から免責されるものといたします。

1) お客様による当社製品の不適当な取扱いならびにご使用の場合。
(カタログ、仕様書、取扱説明書などに記載されている条件、環境、注意事項などの不遵守)
2) 故障の原因が、当社製品以外の事由の場合。
3) 当社もしくは当社が委託した者以外の改造または修理による場合。
4)「使用上の注意」に反し当社製品が使用された場合。
5) 当社出荷当時の科学・技術水準では予見不可能であった場合。
6) その他、天災、災害、第三者による行為などで当社側の責にあらざる場合。

なお、インターネットオークションなどで当社製品を購入された場合、上記の保証は一切受けられませんのでご注意ください。

保証書 / Warranty Card

＊本取扱説明書は修理時、代替品のご提供時に必要になります。
大切に保管頂けますようお願いします。
※This instruction manual is required when you need to register for repair or when offering substitute products.

充電式 LED ランタンスピーカー ROOMS
レシート / スタンプ類
Receipt / Stamp

Date of purchase and the Store :　Year　Month　Day
お買上げ店舗名　年　月　日

forest
株式会社 **フォレスト**　：販売元
〒150-0012 東京都渋谷区広尾 3-8-19
0120-608020【2022 年 10 月】
https://forestjapan.co.jp/

Made in China / Printed in China

Warranty Card

If the product does not conform to our specifications and is defective, we will offer substitute products or offer the repair of products free of charge **within one year of purchase.**
However, the maximum warranty amount from our company for the damage incurred by the non-conformity will be the price of the products purchased.
Additionally, we are free from any warranty for any damage or loss due to the following reasons:

1) Inappropriate handling and usege by user.
(Failure to comply with the conditions, environment, and precautions stated in the catalogue, spscification and instruction manual.)
2) If the cause of the failure is for reasons other than our products.
3) In case the product is modified or repaired by other than our company or those entrusted by our company.
4) When the product has been used contrary to "PRECAUTIONS"
5) When it was impossible to foresee at the science and technology level at the time of our shipment.
6) In addition, the company is not responsible for fire, disaster, acts by a third party, etc.

Please note that we can not accept any of the above warranty if you have purchased our products at internet auction etc.

Usage notes / Li-ion battery

- When moving the product, there should not be any excessive impact.
- Stop using immediately when you get an abnormal odor or product abnormality. (Please immediately discontinue use.)
- Do not disassemble, remodel, or repair the product.
  It is very dangerous, so doing it is absolutely prohibited.

Place the product on a stable area that has no risk of falling over, and enjoy it.

***This product has a built-in Li-ion rechargeable battery.**

If battery leakage occurs, touching with bare hands is dangerous.
If the battery liquid gets into your eye, don't rub it, wash it with clean water immediately, and go to see a doctor.
If you have symptoms of inflammation or injury, consult the doctor.

Li-ion

*Apart from general garbage, to recycle

How to use, Pairing Bluetooth

● **LEDlight** 3-level dimming LED OFF →30% →60% →100% →OFF

● **Bluetooth Pairing 1:1**

***Connection Method Please turn OFF Bluetooth of the device which you wish to connect with.**

1. Press turn the Bluetooth ON. (dial tone will sound)
2. Connect the speaker and the such as smart phone.
   Turn the Bluetooth ON.
   Select “ Lantern Speaker ROOMS ”
   Connecting the speaker and the smart phone has been success. (dial tone will sound)

● **Bluetooth double pairing 1:2(Speakers)**

***Please delete all the history of LanternSpeaker ROOMS on Bluetooth list.**

1. First, pair the 2 speaker to each other.
   Press the Both Bluetooth turn ON. (dial tone will sound)
   Press the Bluetooth button of one of the speaker.
   2 speaker have been paired. (dial tone will sound)
2. Connect the paired two speakers and the such as smart phone. Turn the Bluetooth ON.
   Select “ LED LanternSpeaker ROOMS”
   Connecting the paired speaker and the smart phone has been success. (dial tone will sound)

Note：This unit can also be used as a single speaker. But after using as a single speaker, it is necessary to reset for use two Speaker.
Please delete all the history of LanternSpeaker ROOMS on bluetooth list.

Technical Specification

Light source　: 3 level dimmable LED (0.4W / 2000k)
Luminance　: 35lm Hight (100%)
LED durability　: 40,000 hours
Transmission type　: Bluetooth 5.1　*2 units can be paired
*This product is not connectable to all wireless connection (Bluetooth) devices.
Transmission distance：8 m
(Transmission distance depend on the environmental factors with your phone or Bluetooth device differs.)
Speaker　: 5W
Dimensions　: φ168mm x H287mm(without leather belt)
Weight　: 1.7 kg
Battery　: Li-ion Rechargeable battery DC 3.7V, 2600mAh
Battery charge time : 4.5 hours, DC 5V-1A / USB Type-C
Battery durability　: 500 times
Playing time　: max 8 hours (Medium volume/ lighting 30%)
Water resistance　: Non-waterproof
Frequency response : 200 Hz～20 kHz
RF Power control range : 5dBm
Production country : Made in China

- **This product does not have completely waterproof specifications. Do not leave it in a bathroom of high humidity or outdoors in the rain.**

90 mm

FCC STATEMENT

Caution: The user is cautioned that changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/ TV technician for help.

FCC Radiation Exposure Statement

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment.
This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

90 mm