成品尺寸：120*65mm/展开尺寸：720*65mm/材质：80g书纸/风琴折

120mm

65mm

正面

Fanvil | LINKVIL




Quick Start

DH301D

DECT Wireless Headset

English

DH301D DECT Wireless Headset



1. In the Box



DH30 Headset



DT10 Dongle



DB10 Charging Stand




USB Cable



Quick Start*1
Safety Information & Declaration*1

2. Power ON/OFF

Push the power button down to power ON the headset, and push the power button up to power OFF the headset.




3. Pairing and Device Connection

3.1 DECT Mode

3.1.1 Connection

Keep the headset power ON and insert the DT10 Dongle into your device.

You can connect the DT10 Dongle to the PC or IP Phone.



Notes:
1. Your DT10 Dongle is pre-paired with your headset.
2. One DT10 Dongle can only pair with one device at a time.
3. If the DT10 Dongle is not paired or purchased separately, follow the pairing instructions.

3.1.2 Pairing

Simultaneously press and hold the call button and mute button for 5s.



Insert DT10 into the device and hold the pair button for 3s.



Pair Button

3.1.3 LED Indicator

Event	Dongle LED		Headset Busylight	
Insert dongle into device	Flashing Green 5 times	◌	/	
Dongle in standby(Connected)	Solid Green	○	/	
Out of range or Disconnected (Reconnecting)	Flashing Orange	◌	Flashing Orange	◌
Pairing	Flashing Red & Green	◌	Flashing Red & Green	◌
Connected	Flashing Blue 5 times	◌	Solid Green 3s	○

3.2 Bluetooth Mode

3.2.1 Pairing

Push the power button down fully and release to turn on Bluetooth and enter auto-reconnect mode. Push the power button down fully for 1.5s to enter pairing mode.



背面

3.2.2 LED Indicator


Event	Headset Busylight	
Reconnected	Solid Blue 3s	○
Pairing	Flashing Red & Blue	◌
Connected	Solid Blue 3s	○
Disconnected	Flashing Blue 5 times	◌

3.3 USB Mode

Connect the headset to your device via USB cable to enable simultaneous charging and audio calls.



4. Mute Control





5. Call Button



Play / Pause	Answer / Hang up	Reject call	Hold/unhold call	Redial
Press	Press	Double-press	Press for 1.5s	Double-press

6. Busylight Control



Simultaneously press and hold the Volume +/- buttons for 2s to turn on/off the Busylight.

7. LED Indicator

Event	Headset Busylight		Dongle LED	
Headset power on	Solid Green 3s	○	/	
Headset power off	Solid Red 3s	○	/	
Incoming call	Flashing Red	◌	Flashing Green	◌
In call	Solid Red	○	Solid Red	○
Hold current call	Solid Red	○	Flashing Green 3 times	◌
Battery below 20%	Flashing Red 5 times	◌	/	

8. Charge





Charging Started	Headset Busylight	
Battery below 20%	Flashing Red	◌
Battery below 80%	Flashing Green	◌
Battery above 80%	Solid Green	○

Note:
When the power of DH30 headset drops below 20%, there will be sound notifications. Please charge DH30 as soon as possible.

Please scan the QR code to see the User Manual.

© 2025 FANVIL Link Technology Co., Ltd.
All rights reserved. No parts of this publication may be reproduced or transmitted in any form or by any means, electronic or mechanical, photocopying, recording, or otherwise, for any purpose, without the express written permission of FANVIL Link Technology Co., Ltd.

Tel: +86-755-2640-2199 EMail: sales@fanvil.com Web: www.fanvil.com
Fanvil Link Technology Co., Ltd.