

Label Location



Confirm the use of real appearance photos as references

Portable Power Station

- Model: Ark2000
- Battery Information: 38.4Vdc, 40Ah, 1536Wh
- AC Input: 1500W Max, 100-120Vac, 50/60Hz
- PV(XT60) Input: 12-90Vdc, 1200W Max
- USB-A(x2) Output: 5V $\rightarrow$ 3A, 9V $\rightarrow$ 2A, 12V $\rightarrow$ 1.5A, 36W Total
- Type-C PD 20W Output: 5V $\rightarrow$ 3A, 9V $\rightarrow$ 2.22A, 12V $\rightarrow$ 1.67A, 20W Max
- Type-C PD 100W Output: (5V/9V/12V/15V) $\rightarrow$ 3A, 20V $\rightarrow$ 5A, 100W Max
- Car Charger Port Output: 12V $\rightarrow$ 10A
- LED: 3W
- Operating Temperature: -10-40°C
- Charging Temperature: 0-40°C
- AC Output Voltage: 100-120Vac, 50/60Hz
Off-grid Mode Output Power: Rated 2000W
Bypass Mode Output Power: 1575W Max
- Total DC Output Power: 276W
- Total AC and DC Output Power: 2276W
- FCC ID: 2BFF7ARK2000

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

This device may not cause harmful interference, and This device must accept any interference received, including interference that may cause undesired operation.

⚠ CAUTION

This device is not intended for use in a commercial repair facility. Risk of Electric Shock. Refer replacement to qualified service personnel. Do not remove cover. Risk of Injury To Persons. Do not use this product if the power cord or the battery cables are damaged in any way.

⚠ WARNING

Risk of Electric Shock and Risk of Fire. This device is not to be stored in a vehicle. Do not overcharge the internal battery. See Instruction Manual. Do not smoke, strike a match, or cause a spark in the vicinity of the power pack. Only charge the internal battery in a well ventilated area.

⚠ DANGER

This device is intended to be used indoors only. Do not use outdoors.



Made in China

81mm

86mm