

come from
D9 | Bluetooth V 5.3
Breaking the traditional
limits of Bluetooth devices



Important tips:

- 3 please review manual carefully.
- 2 please follow the instructions of this specification.
- 3 do not use more than the rated current and voltage of the headset (SVIA) charger to the headset/charge, otherwise it will be easy to cause damage to the headset/battery.
- 4 please use and store this product in the common environment.
- 5 do not use this product near water, this product is not in any liquid or any spills, onto the product.
- 6 do not use this product in any near heat source, such as the radiator, the air conditioner, the stove/ or other heat generating apparatus.
- 7 do not block the opening of the headset, such as the microphone and the earpiece.
- 8 please avoid too much volume or too long time to use the headset, to avoid causing damage to the hearing.
- 9 read the manual carefully, in case, if necessary, to timely contact with my brand after-sales personnel, unauthorized demolition and change will make the warranty failure.
- Product structure description:

Product matching

The headset is not connected to any device:

- the headset will re-connect to any device:
1. Press and hold the **power** button for 4 seconds, first **LED** lamp 1 second, orange **LED** lamp flashes quickly for two, and orange and white flash alternately, the voice prompt "boot - pairing state" (If the user in the headset voice prompt "boot" after "pairing" before loosening multiple function keys, the headset is in boot state, has not yet entered the pairing state. At this time, the power button of the headset, re grow press the function key to pairing state);
 2. start the phone Bluetooth function, search for Bluetooth devices, and then select the Bluetooth headset model D9, click on the pairing.
- Tip:** when the Headset into the matching mode, if you fail to complete the pairing, please wait 3 minutes, the headset will automatically shut down. Such as the continued pairing, restart the Bluetooth headset to the pairing state.

Function description

Boot: In the shutdown state, press and hold the "multi-function" 3 seconds. The headset is switched on and a prompt tone, the headset will automatically connect to the last device;

Shutdown: In the standby mode or the work of holding down the "multi-function" 3 seconds, the headset is off and a prompt tone, the orange LED light flash 3;

Play/pause: when playing the song, press the "multi function key" to achieve a pause; again press this key will continue to play;

Volume plus: click "+" button to increase the volume;

Volume reduction: click "-" button to reduce the volume;

On: a long press "+" button, play on a track;

Next song: long press "+" key, play the next track;

Answer the phone: when there is an incoming call, click "multi function key";

End of the call: in the call, press the "multi function key";

Related to call: when there are calls, long press the "Multi function key";

Paired with two functions (simultaneous pairing of two mobile phones)

- 1, and connecting two Bluetooth devices: in accordance with the matching method, the first pairing a cell phone, and then close the Bluetooth headset, and then again in accordance with the paired with a second mobile phone, and then connect the Bluetooth headset headset, to maintain the matching connection Bluetooth head set and the second mobile phone, open the first mobile phone Bluetooth list, click in the list of Bluetooth "D9", at this time, Bluetooth headset will automatically with the first cell phone paired connection.
 - 2, When two mobile phones at the same time, can be achieved 4, 3 point operation:
 - 3, a cell phone call, another phone call Double click on the multifunction button to keep the current phone call, and answer the call-Short press the multifunction key, hang up the current call and answer the call.
 - 4, a cell phone call, another phone call Double click on the multifunction key to keep the current phone call and connect the phone to be maintained-Short press the multifunction key, hang up the current call and connect the mobile phone, mobile phone is maintained.
- Switching mode in Chinese and English**
- Long press the power button to enter the matching state, the white LED light will flash, and then double-click the volume button to

Charging - Bluetooth headset

- ### Charging Bluetooth headset
- 1 connect the charging wire to the charging socket on the earphone;
 - 2 during the charging period, the indicator light turns orange;
 - 3 full power, the orange indicator light will turn white, at this time, unplug the charging line;
 - 4 must choose the regular factory production through the national CCC certification of the charger;
 - 5 repeat the charge and discharge of the headset, which will lead to battery efficiency over time. Can drop, which is normal for all rechargeable batteries.

Description

- Description**
1. Bluetooth version: v5.3
 2. support: HFP, HSP, AVRCP, A2DP protocol
 3. the battery capacity: 230mAh
 4. one with two support function
 5. product size: 64.2*18.2*28mm
 - 6 Bluetooth normal off range: 10M
 7. frequency: 2.40 GHz
 8. support voice prompt / voice broadcast function

Common problem

- [illegible]

- [illegible]