

5折页 成品130x115mm 展开尺寸 130x575mm 双面印 英文面是封面 100g双胶纸 特注意英文面是封面


正面

SOVENMUND®

VENOM BALL

FERROFLUID SPEAKER

USER MANUAL



Model: SP-B01

www.sovenomund.com

Look! music is alive.

Product Overview

VENOM BALL ferrofluid speaker is a fusion of art and technology, visualizing sound through a mesmerizing ferrofluid display. The magnetic liquid dances gracefully in sync with the music, offering dual enjoyment for both your eyes and ears.

Features

- Certified by sovenomund.com
- Wireless connection with BT
- Built-in rechargeable battery
- Pairing two speakers using TWS True Wireless Stereo technology to create a stereo sound experience.
- Great sound quality
- AUX input connection
- DSP for improving sound quality
- Built-in LED lights that change colors
- Compact and sturdy
- USB Port connection
- Stylish design
- Tripod or pole support (fixed placement)

Quick Start Guide

➔ - || + 🔊

● **Power on:**
Press the **⏻** on the back for 3 seconds.


● **Connect the speaker:**
By default, the speaker is in wireless BT pairing mode.
Use a phone or computer to connect VENOM BALL on BT list.

● **Play music, and the ferrofluid will dance to the beat.**
Adjust the volume to control the intensity of the ferrofluid's movements.

Operating Instruction

Button **⏻** (Mode)
When powered on, the default mode is wireless BT. If no USB drive or AUX input is connected, the **⏻** button has no effect. If an AUX signal or USB drive is connected, touch the **⏻** button to switch modes.
If there are two VENOM BALL speakers, before connecting to Bluetooth, a USB drive or an AUX signal, long press the **⏻** button on either speaker for 2 seconds to activate the TWS pairing mode and connect the two VENOM BALL speakers to form a stereo system.

Technical Specification



Audio Specifications:
Output power: 30W
15W x4 range speaker x2
Frequency response: 65Hz-13.5kHz
S/N ratio: >85dB

BT Wireless: 5.3 version
Pairing name: VENOM BALL
Input-Output: USB to Type-C/IV 2.5A
Connectivity: BT, AUX, USB drive
Battery capacity: 7.4V 4500mAh
Operating temperature: -15°C
Size: Diameter 150mm, Height 150mm
Net weight: 1.8kg

Safety Instruction

- The speaker contains a built-in glass container that is fragile. Please ensure it is placed upright and stable before playing the speaker. Avoid dropping it.
- Do not disassemble or modify the speaker, as this could result in electric shock or damage.
- Keep the speaker away from water to prevent electric shock or damage.
- Do not place the speaker near heat sources such as radiators, stoves, or other appliances that produce heat. Use only the recommended power supply and charger for the speaker.
- Keep small parts and packaging materials out of reach of children to prevent choking hazards.
- Please do not use the speaker in cold and icy environments, and avoid using it in hot environments for long periods.
- Do not use it in a car, especially under direct and intense sunlight.
- Please do not add water to the bottle. The liquid is custom-formulated by experts, and adding water will affect the ferrofluid's movement.

Troubleshooting

Q: If I have two VENOM BALL speakers, how can I pair them to create TWS stereo sound?
A: 1. Turn on both VENOM BALL speakers simultaneously, but do not connect to BT immediately.
2. On either speaker, long press the **⏻** button to initiate TWS pairing. Once paired, both speakers will make a sound to indicate a successful connection.
3. Search the BT list, connect VENOM BALL, and then you can start playing.

Q: If I have a bubble inside the bottle, how can I make it disappear?
A: 1. Turn off the speaker. Try recharging the speaker fully before using it again.
2. Overheating: The ferrofluid might have overheated. It will automatically resume dancing once it cools down.
3. Power saving mode: If no music is played for more than 20 minutes, it enters standby mode. Press the button on the back to turn it on again.

Q: If there is a bubble inside the bottle, how can I make it disappear?
A: Hold the speaker at a 45-degree angle and play 3-5 songs. The bubble will rise to the top and disappear.

Here is some FAQs. If you haven't solved your problem, please contact us via email at: sales@sovenomund.com Or at our Facebook service page to contact us.




Packaging Includes

- VENOM BALL Speaker x1
- Foot x3
- AUX line x1
- User Manual x1
- USB to Type-C charging cable x1
- Magnet x1 (interact with ferrofluid)

Tripod installation illustration

Align the notches of the three support foot with the corresponding slots on the bottom of the speaker and insert them.



FCC Warning:
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation. Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

NOTE: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

NOTE: This device and its antenna(s) must not be co-located or operated in conjunction with any other antenna or transmitter.

RF exposure:
This device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Brand: SOVENMUND
Product Name: VenomBall Ferrofluid Speaker
Model: SP-B01
Design Unit: Dongguan Yexunmould Technology Co., LTD
Manufacturer: Dongguan Xunyu Mould Technology Co., LTD
Address: Room 101, Building 2, No.4 Guangkou Street, Hengli Town, Dongguan City, Guangdong Province, China
Service Call: +86-137 2629 5871

© R&Hs CE FC UK

To learn more about our other products, please visit our website: www.sovenomund.com
Copyright ©2025 All Rights Reserved Manual Edition 2.0, Mar 2025
Made in China


背面

SOVENMUND®

VENOM BALL

磁流体蓝牙音响

使用说明书



型号: SP-B01

www.sovenomund.com

Look! music is alive.

产品概述

VENOM BALL磁流体蓝牙音响是艺术和技术的融合，让音乐可视化，磁性液体与音乐同步优雅地舞动，给您眼睛和耳朵带来双重享受。

特点:

- SOVENMUND出品
- 音质绝佳
- 结构坚固
- 蓝牙连接播放
- AUX输入播放
- U盘输入播放
- 内置电池
- DSP音效
- 时尚的设计
- TWS配对两台音响，创造立体声场
- LED灯彩背光
- 三脚架支撑杆支撑固定

快速入门指南

➔ - || + 🔊

● **接通电源:**
按下背面的开/关 **⏻** 按钮3秒。


● **连接蓝牙:**
开机情况下，音响处于蓝牙配对模式，打开手机或电脑的蓝牙链接名称“VENOM BALL”。

● **播放音乐:**
蓝牙播放会随着音乐节奏起降，调节音量以控制磁流体的舞动幅度。

操作指令

按钮 **⏻** (模式)
开机时，默认模式为蓝牙连接模式。
如果没有插入U盘或AUX输入，则 **⏻** 键不起作用。
如果插入了U盘或连接了AUX输入，则 **⏻** 键可切换输入信号。
如果有两个VENOM BALL音响，在未连接蓝牙、U盘或AUX信号前，长按其中任一“台音响”的 **⏻** 键2秒，可启动TWS配对模式，连接两台VENOM BALL音响由立体声。

产品规格



规格:
输出功率: 30W
15W x4全频喇叭 x2
频率响应: 65Hz-13.5kHz
信噪比: >80dB

蓝牙版本: 5.3
蓝牙名称: VENOM BALL
输入电压: Type-C 5V2A
电源输入: 蓝牙、AUX、U盘
连接容量: 7.4V 4500mAh
工作温度: -15-35°C
尺寸: 直径150mm、高250mm
净重: 1.8kg

使用注意事项

- 音箱内置了一个玻璃容器，使用的时候请保持位置直立且稳定，避免掉到地上。
- 请勿拆卸或改装音箱，以免导致电路损坏。
- 请勿将音箱浸入水，以免导致电路损坏。
- 请勿将音箱放置在热源附近，如散热器、炉具或其他产生热量的电器。
- 使用推荐的电源和充电器。
- 将配件和包装材料放在儿童够不到的地方，以防止窒息危险。
- 请勿在寒冷、冰冻的环境中使用，同时避免在高温的环境中长时间使用。
- 不要在车内使用，尤其在阳光直射的情况下。
- 请不要往容器里加水，磁流体是专业配制的，加水会影响磁流体的舞动状态。

故障排除

Q: 如果我有两个VENOM BALL音响，我想将它们TWS配对成立体声？
A: 1. 两个VENOM BALL音响同时开机，但不要立即连接蓝牙。2. 长按任意其中一个音响的 **⏻** “回”键2秒，配对两个音响都会发出声音，表示TWS连接成功。3. 打开手机或电脑的蓝牙，连接VenomBall，即可立体声播放。

Q: 播放了一会儿后，音响停止了，原因是什么？如何解决？
A: 1. 电池电量不足：请尝试为音响充满电。2. 过热：玻璃瓶中的磁流体可能过热了。将机冷却后会重新启动。3. 省电模式：如果超过20分钟没有音乐播放，则进入待机模式，按一下背面的开/关重新开机即可。

Q: 如果玻璃容器里有气泡，该怎么办才能让它消失？
A: 将音响保持45度角，播放3-5首音乐，气泡会上升到容器顶部并消失。

以上是一些常见问题的解答，如果还没有解决您的问题，请通过电子邮件联系我们: sales@sovenomund.com 或访问我们的售后服务:




包装清单

- 音箱x1
- 三脚架x3
- AUX线x1
- 使用说明书x1
- Type-C充电线x1
- 小磁铁x1 (与磁流体互动用)

三脚架安装示意图

• 分别将三个支撑脚的卡口对准音箱底座的孔位，插入即可。



品牌: SOVENMUND
产品名称: 磁流体蓝牙音响
型号: SP-B01
设计单位: 东莞市伟能模具科技有限公司
生产厂: 东莞市伟能模具科技有限公司
生产地址: 广东省东莞市塘厦镇广田路4号2号楼101室
服务电话: +86-137 2629 5871

© R&Hs CE FC UK

了解更多产品，请浏览我们的官方网站: www.sovenomund.com
版权所有©2025 版本2.0, 2025年3月
中国制造

