

I. Package Contents Viefong Help Mobile Power bank x 1 Charging Cable x 1 User Manual (With warranty card) x 1 Certificate x 1 II. Product Overview Viefong Help Mobile Power bank User Manual	III. Function Operation 1. [Power Button] ① Press the power button, the Bluetooth indicator light flashes, and the power indicator light turns on, indicating that the device is powered on. ② When the device is not connected to Bluetooth, the power indicator light will turn off after 1 second of no operation. In an idle state, the power bank will enter sleep mode after a period of time. If the phone and power bank exceed the effective communication distance and disconnect, the power bank will automatically shut down if there is no connection within 30 minutes. 2. [Charging External Device] Connect the power output line of the mobile power supply to the external device that needs charging, and charging can be performed.	3. [Charging with Mobile Power Supply] Connect the Type-C charging cable to the power source and insert it into the Type-C power input port of the device. Charging process: The power indicator light flashes intermittently. Fully charged: The power indicator light stays on.	4. [Download Viefong APP] Android users may search for [Viefong] in the mobile application null, while iOS users can search for [Viefong] in the App Store or scan a QR code for download. Note: To maintain the stability of the [Viefong] background operation and ensure timely reception of Viefong voice intercom, SOS distress signals, and other information, Android users are advised to manually set relevant permissions according to their phone model after installing the software. Specific setting steps can be found in the App [Settings]->[Help]->[Viefong APP Software Manual], or follow the prompts from the contact's Viefong Assistant. iOS users do not require this step.	5. [App Registration] Click the desktop Viefong App icon --> Select Region --> register --> Enter the mailbox, verification code, password, and confirm the password (Read and check the [Software License and Service Agreement] and [Privacy Policy]) --> Click the OK button to complete the "sign up" and successfully log in to the account.	6. [Add friends] Entering the Viefong APP homepage and click [+] in the upper right corner to add friends or group chat (according to different conditions. Note: The counterpart must also download and register the Viefong APP so that each other can be added as friends yet) 7. [Viefong APP voice intercom] Click on any friend in the Viefong APP to conduct voicecommunication. 8. [Viefong APP voice intercom] ① Press the [Power ON/OFF] button. The blinking Bluetooth indicator light indicates power-on. Then enable Bluetooth in your mobile settings. ② Open the Viefong APP, then go to Devices (bottom-right corner) --> Search (Add Device) [+] top-right --> Select [NM_VF_VF162]. The device status will change to "Connected" within 2-3 seconds with the Bluetooth indicator blinking intermittently. The Bluetooth indicator ceases blinking when the power bank enters sleep mode. (Should multiple identical device names appear during pairing, select the one with the strongest signal value. Featuring persistent pairing memory, this device requires no repetitive reconnection). 9. [Shortcut contacts settings] ① You can set up shortcut contacts on the Viefong APP on your phone, steps: Open the Viefong APP --> click "My" --> click "Shortcut/contact key settings" to set up shortcut contacts. ② Click the [PTT] button to cycle through quick contacts. After finding the corresponding contact, long press the [PTT] button to send a real-time voice message to your friend.
10. [Setting for Viefong APP SOS] ① Enter the homepage of Viefong APP and click "my" in the upper left corner --> "SOS Settings" --> "Turn on SOS" --> Set SOS Contacts and select friends and click OK (10 emergency contacts Max. can be set) ② Users can set SOS alarm or SOS alert function per need: Click SOS for alarm. The alarm information (name, addresstime and longitude time remarks) and 60 seconds of environmental recording can be sent to the pre-set SOS contact and the recipient will receive an alarm prompt tone.	Click SOS for alarm: The alarm information (name, addresstime and longitude time remarks) and 60 seconds of environmental recording can be sent to the pre-set SOS Contacts and select friends and click OK (10 emergency contacts Max. can be set) ③ Set SOS alarm notes: Click Edit to enter the editing page, edit the text content and send a photo together. ④ Set SOS alarm notes: Click Edit to enter the editing page, edit the text content and click Finish. The alarm notes will be displayed on the recipient's phone and the notes will be read out in voice, when SOS alarm was sent.	④ The gray [SOS Alarm] button will be turned as a red [Stop Alarm] button once clicked or SOS alarm. The user can click the icon in the upper right corner to preset the update and sending of alarm information every 25/50 minutes; click [Stop Alarm] to stop sending alarm information. ⑤ In the alarm pop-up window received by the SOS contact, the alarm information updated every 25/50 minutes will no longer be received. Press checked "No longer receive alarms" and confirmed "OK" will receive it continuously if you do not check. ⑥ The SOS alarm information will be sent to the SOS contact in the form of a pop-up window, and the SOS alarm notes will be broadcasted on the contact's phone (It will not be broadcasted if the sender does not set a note). ⑦ In answering of a SOS calls automatically: All incoming calls within 5 minutes will be automatically answered by the phone after the person sent the SOS alarm voice, under the circumstance that turned on SOS and answering for SOS Calling (Without incoming call prompt tone). 11. [Power Bank SOS Button and Power Button] SOS Button Function Description: ① When the mobile power bank is connected to the Viefong APP, the SOS button function is enabled. During the setup of the security mode, the buzzer alarm will not be triggered. When the mobile power device is not connected to the Viefong APP, click the [SOS] key, and the device will trigger the buzzer alarm. Click the [SOS] key again, and the device will stop the buzzer alarm. ② Double-click the [SOS] key to enable the radar security mode. The red indicator light stays on the night light flashes, indicating that the radar security mode is enabled. During the setup of the security mode, the buzzer alarm will not be triggered. When the mobile power device is not connected to the Viefong APP, click the [SOS] key, and the device will trigger the buzzer alarm. Click the [SOS] key again, and the device will stop the buzzer alarm. ③ When the mobile power device is not connected to the Viefong APP, click the [SOS] key, and the device will trigger the buzzer alarm. Click the [SOS] key again, and the device will stop the buzzer alarm. ④ When the mobile power device is not connected to the Viefong APP, click the [SOS] key, and the device will trigger the buzzer alarm. Click the [SOS] key again, and the device will stop the buzzer alarm. Power button function: ① Press the power button once to wake up, and the battery level display will be turned on at the same time. Bluetooth will also be turned on. The white light will stay on for 5 seconds before automatically turning off (the battery level after turning on can be checked in the APP).	⑧ Long press the power bank's [Power] button for 2 seconds to turn the flashlight mode ON/OFF; the LED night light will turn ON/OFF accordingly. ⑨ Double-click the power button to turn ON the radar LED sensor night light mode. The night light will flash to indicate sensing is activated only the LED night light radar sensor is activated, the buzzer will not sound; Double-click again to turn OFF the night light radar sensor function.	12. [Power Bank Radar Night Light Setting] Mobile power is connected to the Viefong APP. After enabling the radar night light mode, when the user enters the radar area of the mobile power, the LED light of the mobile power will light up. The specific operation steps are as follows: ① Connect the mobile power and the Viefong APP. Double-click the [Power] key of the mobile power to turn on and off the radar night light mode, and the LED night light mode will be activated. ② Connect the mobile power and the Viefong APP. In the Viefong APP, go to [Device] --> long-press or single-click the connected device [NM_VF_VF162] --> click [Radar Settings] --> Select [Night Light Mode]. ③ After activating Radar Night Light Mode, when the LED light is off, it will illuminate upon detecting a user in the radar sensing area. ④ With Radar Night Light Mode enabled, toggle radar sensing and night light by double-tapping the power key repeatedly. Alternatively, navigate to [Radar Settings]. In the Viefong APP device info page, then double-click Radar Night Light Mode to turn off the LED Light. Additional Settings: using Viefong App Radar Distance Adjustable from 5 to 5 meters. Larger distances expand the sensing range. Light Brightness: Configurable across 1 ~ 100 levels. Higher levels increase brightness. Delayed Turn-Off Time: Set between 10 seconds to 10 minutes. Longer durations extend the lights-out delay.	This will trigger an alarm notification to be sent to the emergency contacts. A maximum of 10 emergency contacts can be set to receive notifications. The specific operation for connecting the power bank to the Viefong APP on your phone and turning the radar alarm arming mode on/off in the app are as follows: ① Viefong APP --> [Device] --> Tap the "+" icon at the top-right corner --> Select device [NM_VF_VF162] --> Long-press or tap the connected device [NM_VF_VF162] --> Choose [Device Info] --> Select [Radar Mode] --> Choose [Alarm Arming] to enable the radar alert protection mode for the power bank. ② After activating the radar alert arming mode, go to the Device Information page in the Viefong APP, tap [Radar Mode], and select Double Radar Alert Arming Mode to silence the buzzer alarm and turn off the LED night light. ③ Double-click the power bank's [SOS] button to toggle the radar alert arming mode. The LED night light will flash to confirm successful operation. ④ After activating the radar alert arming mode, if a user enters the radar detection area, single-press the power bank --> [SOS] button to temporarily suspend the buzzer alarm. The LED night light will continue flashing. ⑤ After activating the radar alert arming mode, double-click the power bank --> [SOS] button to deactivate the radar alert arming mode. This will Silence the buzzer alarm. Stop all alert notifications and pop-up messages. Turn off the LED night light. Other related Settings: Radar range: A range of 0.5 to 5 meters can be set in the Viefong APP. The greater the radar distance, the wider the radar sensing range. The delay time for the alarm status to take effect: The frequency of sending alarm information for defense can be set. Users can go to the Viefong APP --> Radar Mode --> Set the delay period for the alarm status of the security contact person to take effect. The interval for sending alarm information for defense can be set to four levels: 30 seconds, 10 minutes, 30 minutes, and 60 minutes.

10. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).	11. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).	12. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).	13. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).	14. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).	15. [Radar Identification Range for Defense Purposes] Alarm notification contact persons: You can set the alarm notification person into Viefong APP. Up to 10 alarm defense contact persons can be set. When the radar alarm defense is triggered, the alarm information will be sent to the defense contact person in the form of a pop-up window, and the remarks of the defense alarm will be broadcast by voice on the defense contact person's mobile phone if the sender of the alarm has not set remarks. It will not be broadcast. The contact person for the alarm notification received the alarm information (Name, Address, Longitude and latitude, time, remarks).
16. [Delete device] Viefong APP --> [Device] --> Long press the connected device [NM_VF_VF162] --> Select [Delete device], the device is disconnected, and the connected device is deleted. 18. [Device Shutdown] Viefong APP --> Long press the connected device [NM_VF_VF162] (Double-click shutdown) to shut down the device.	20. [Turn on hardware device messages] Press and hold the connected [NM_VF_VF162] device, and the following functions will be available after enabling [Hardware Device Message Association]: 1. Hidden Chat History Function: After connecting the device via the Viefong APP, press and hold the connected device, click "Enable Hardware Device Message Association", and then in the chat interface with your friend, select "Hide Chat History". Once enabled, if you disconnect the Bluetooth device connected to the Viefong APP, the chat history with that friend will be hidden. Additionally, when the Viefong App is online, there will be no message push and voice message will play automatically. The chat history will be visible again upon reconnecting the device. 2. Whisper Function: In the chat interface with your friend, click the menu in the top right corner. When the whisper function is enabled, the whisper status display will be hidden.	21. [Device Info] Viefong APP --> [Device] --> Long press the connected device [NM_VF_VF162] --> Select [Device Information] to view the device name and device version number. The device name can be modified.	22. [Device Info] Viefong APP --> [Device] --> Long press the connected device [NM_VF_VF162] --> Select [Device Information] to view the device name and device version number. The device name can be modified.	23. [Device Info] Viefong APP --> [Device] --> Long press the connected device [NM_VF_VF162] --> Select [Device Information] to view the device name and device version number. The device name can be modified.	24. [Device Info] Viefong APP --> [Device] --> Long press the connected device [NM_VF_VF162] --> Select [Device Information] to view the device name and device version number. The device name can be modified.

展开尺寸为:120mm×880mm

黑白印刷,80g双胶纸。成品尺寸60x80mm, 折叠方式向外对折后风琴折