



1. Touchscreen display shows temperature, humidity, and max/min values at the base and remote units.
2. Temperature can be displayed in Fahrenheit or Celsius.
3. Maximum and minimum value can be easily reset.
4. Maximum and minimum value can be set to automatically reset every 24 hours.
5. Includes magnets, quick-connect bracket and screws for installing on wall.
6. Eliminates odors for 60 Days. For optimal freshness, replace every 30 days. Natural & effective odor elimination, Clean burst maintains freshness for long hours. Deodorizing balls filled with odor eliminating baking soda and Clean Burst fresh scent. Perfect for every room in the house, closets, hampers, travel bags, shoes, athletic gear & much more!

1. Keep product clean. A buildup of dust could affect the accuracy of the thermometer and hygrometer.
2. Do not drop as it may damage the sensitive electronics
3. For indoor use only. Do not immerse in any liquid.
4. Replace batteries when the display begins to dim.
5. The touchscreen is designed to read a soft fingertip.
6. Use only with Listed/Certified Power Supply.

DO NOT use a fingernail or other hard object as it may damage the screen.

Begin by removing the battery cover from the base and remote unit and installing new AAA batteries into both the base and remote units. It may take up to one minute for the base and remote to connect after installing batteries.

A. REMOTE / BASE BUTTON

- Press and release to toggle between displaying the remote readings and base readings.
- Press and hold to manually initiate pairing between the base and remote.

A diagram of a green remote control. On the right side, there are two buttons: the top one is labeled 'REMOTE' and the bottom one is labeled 'BASE'. A red arrow points to the 'REMOTE' button, and a red letter 'D' is placed next to the arrow.

NOTE: Whenever batteries are placed in the base unit, the base unit automatically initiates the connection process with the remote, but it must wait until the remote broadcasts a signal to establish a connection. If replacing the batteries in just the remote, a manual connection will be needed. It is best to replace the batteries in the base and remote at the same time.

- Press to toggle between displaying temperature in Fahrenheit or Celsius.

C. ALL TIME/24 HRS:

- Press and release to toggle between ALL TIME and 24 Hrs min/max interval.
 - **ALL TIME:** Displays the min/max readings until manually reset.



1. The LED light turns on automatically when dark and motion is detected within a 10 foot range.

- ### NON-METAL SURFACE



A Type-C cable is included to connect the dehumidifier to a power outlet for heating and drying out the desiccant crystals. (Typical dry time is about 8-12 hours.)

1. Temperature range: -20 ~ 60°C (-4 ~ 140°F)
2. Humidity range: 10% ~ 99% RH
3. Maximum read distance: 65 feet unobstructed
4. Measurement period: 50 second intervals for Remote Sensor and 10 second intervals for Base Display
5. Power supply: Six AAA batteries total (not included).
6. Base Display requires two batteries and Remote Sensor requires four batteries.

- Base Display: 140 x 92 x 22mm (5.5" x 3.6" x 0.9")
Net weight: 3.9 oz (111g)
- Remote Sensor : 232 x 110 x 45mm (9.1" x 4.3" x 1.8")
Net weight: 21.2 oz (600g)

- Base Display Unit
- Remote Unit
- Metal Bracket
- User manual
- Wood Screws
- USB Cable

Mode	Mode Description
Sensor Mode	When powered on normally, the light stays on for 3 seconds during initialization. After a 2-second lockout period, the unit enters Sensor Mode.
Quick Test Mode	Toggle the power switch 5 times; the light will flash 3 times to enter Quick Test Mode. This mode ignores the photosensor, with a 5-second delay timer. The unit automatically exits this mode after 4 minutes and reverts to standard Sensor Mode.

©2026 Remington Ammunition. REMINGTON, and GREEN COLOR are trademarks of Remington Ammunition and its affiliates. Made in China.

尺寸：70x100mm（展开尺寸:350

双面印刷，157g铜版纸