




BGVP Q5

用户操作手册


BGVP Q5 User Manual



Product Description



1. Microphone
- 2.Touching
- 3.Indicator Light



Indicator Light

Parameter Configuration

Model: BGVP Q5
Bluetooth version: V5.4
Impedance: 20Ω @1kHz
Frequency response range: 20Hz - 20kHz
Sensitivity: 104 dB SPL @ 1kHz
Harmonic distortion: ≤ 1% (at 1kHz)
Channel difference: ≤ 2dB
Driver: Moving iron type flat + Composite moving iron + 7.8mm voice coil + Piezoelectric 8mm
Cavity material: Resin
Cable: High-purity oxygen-free copper cable
Headphone jack: 0.78mm 2pin
Transmission distance: Approximately 10 m(without obstacles)
Item battery capacity: 60mAh
Battery capacity of the charging compartment: 400mAh
Rated input: 5V

Operation Instructions

Function	Operation	Instructional Note
power on	Press and hold for 5s	Stays on for 2s, then emits a beep (Power on).
power off	Press and hold for 5s	Stays on for 2s, then emits a beep (Power off)
Enter Pairing Mode	Double Click	Ringtone (Pairing)
Mode Switching	Any earphone, press the touch button 4 times consecutively.	None
Play/Pause	Click	None
Previous song	Double-click left earphone	None
Next	Double-click right earphone	None
Volume up	None	None
Volume down	None	None
Voice Assistant	Press and hold the right earphone for 2s until you hear a "beep" sound, then release.	None
Turn transparency mode on or off.	Left earphone, press and hold for 2s until you hear a "beep" sound, then release. A voice prompt will play after the operation is successful.	None
Answer the phone	Click	None
Call Rejection	Any earphone, double-tap to touch	None
End Call	Any earphone, tap the touch button	None
Game Mode	Any earphone, press the touch button 4 times consecutively.	Prompt sound (du du du)
Factory Reset	No charging case operation steps: Step 1: With the earbuds powered off, press and hold for 10s until the white light stays on, starting a 20s countdown. Step 2: Within 20s, double-click the earbuds to exit charging; the earbud lights will flash rapidly, indicating they are ready to be paired.	Within 20 s, if the headphones are not double-clicked, after the countdown ends, the light will go out for 0.5s and then return to the breathing light.
DUT Mode	Operation without charging compartment: When the headset is turned off, press and hold for 10s + double-click to exit charging; immediately after the light is on. When the light flashes quickly, click 6 times quickly. When the white light is on, it means entering the DUT mode. Note: Let the headset charge to exit the DUT mode and enter the headset pairing state.	The white light remains on.
Low battery warning	If the battery level is 10% or less, a voice prompt will be played every 10 minutes.	"Low battery, please charge"
Power off due to low battery	The battery level is 0%, and the headphones will shut down after playing a voice prompt.	"Power Off" "Du du du (fading tone)" means "Power Off"

FCC Statement:

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Caution: Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment complies with FCC radiation exposure limits set forth for an uncontrolled environment. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter.

Facebook: BGVP
Instagram: bgvp_official
Twitter: @BGVP_HiFi
售后服务交流QQ群: 378080445

