

Panasonic®

Basic Owner's Manual
Manuel d'utilisation Fonctions de base
Instrucciones básicas de funcionamiento

Digital Wireless Stereo Headphones
Casque d'écoute stéréo sans fil
numérique
Cascos auriculares estéreo
inalámbricos digitales

Model No. **RP-HTX80B**
N° de modèle

Thank you for purchasing this product.
Please read these instructions carefully before using this product, and save this manual for future use.
Nous vous remercions d'avoir arrêté votre choix sur cet appareil.
Il est recommandé de lire attentivement ce manuel avant d'utiliser l'appareil et de le conserver pour consultation ultérieure.
Le agradecemos haber adquirido este producto.
Le cuidadosamente estas instrucciones antes de usar este producto, y guarde este manual para usarlo en el futuro.



Panasonic Corporation of North America
Two Riverfront Plaza, Newark, NJ 07102-5490
<http://shop.panasonic.com>
Panasonic Canada Inc.
5770 Ambler Drive, Mississauga, Ontario L4W 2T3
www.panasonic.com
© Panasonic Corporation 2017

Register online at <http://shop.panasonic.com/support> (U.S. customers only)

If you have any questions, visit:
In the U.S.A.:
<http://shop.panasonic.com/support>
In Canada:
www.panasonic.ca/enfr/index
Pour toute question, visitez:
www.panasonic.ca/enfr/index

English
More detailed operating instructions are available in "Operating Instructions (PDF format)".
To read it, download it from the website.
Click the desired language.
Français
More detailed operating instructions are available in "Operating Instructions (PDF format)".
To read it, download it from the website.
http://panasonic.jp/support/global/cs/accessories/oi/rp_hx80b
Click the desired language.

Spanish
More detailed operating instructions are available in "Operating Instructions (PDF format)".
To read it, download it from the website.
http://panasonic.jp/support/global/cs/accessories/oi/rp_hx80b
Click the desired language.

Accessories
Please check and identify the supplied accessories.
Only for U.S.A.:
To order accessories, refer to "Limited Warranty" on the rear page.
Only for Canada:
To order accessories, contact the dealer from whom you have made your purchase.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
Pour commander des accessoires, contacter le revendeur chez qui vous avez réalisé votre achat.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

Accessories
Please check and identify the supplied accessories.
□ 1 x USB charging cord

English
Safety precautions

For California Residents
California Proposition 65 Warning
WARNING
This product contains a chemical known to the State of California to cause cancer and birth defects or other reproductive harm.

For the U.S.A. and Canada only
A lithium ion battery that is recyclable powers the product you have purchased. Please call 1-800-8-BATTERY for information on how to recycle this battery.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA.
This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. FCC Note:
This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.
However, there is no guarantee that interference will not occur in a particular installation. If the equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
• Reorient or relocate the receiving antenna.
• Increase the separation between the equipment and receiver.
• Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
• Consult the dealer or an experienced radio/TV technician for help.
Any unauthorized changes or modifications to this equipment would void the user's authority to operate this device.
This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.
Responsible Party: Panasonic Corporation of North America
Two Riverfront Plaza, Newark, NJ 07102-5490
Support Contact: <http://shop.panasonic.com/support>

FCC CAUTION
Any changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.
The serial number of this product can be found on the speaker. Remove the right earpad to see it.
Please note them in the space provided below and keep for future reference.
MODEL NUMBER RP-HTX80B
SERIAL NUMBER
User memo:
DATE OF PURCHASE
DEALER NAME
DEALER ADDRESS
TELEPHONE NUMBER

THE FOLLOWING APPLIES ONLY IN CANADA. CAN ICES-3(B)/NMB-3(J)USBS
■ Unit
WARNING:
To reduce the risk of fire, electric shock or product damage,
• Do not expose this unit to rain, moisture, dripping or splashing.
• Do not place objects filled with liquids, such as vases, on this unit.
• Use only the recommended accessories.
• Do not remove covers.
• Do not repair this unit by yourself. Refer servicing to qualified service personnel.
• Avoid using or placing this unit near sources of heat.
• Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
• Do not listen with this unit at high volume in places where you need to hear sounds from the surrounding environment for safety, such as at railroad crossings, and construction sites.
■ Allergies
• Discontinue use if you experience discomfort with the speakers or any other parts that directly contact your skin.
• Continued use may cause rashes or other allergic reactions.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

Troubleshooting
Before requesting service, make the following checks. If you are in doubt about some of the check points, or if the remedies indicated do not solve the problem, refer to "Customer Services Directory" on the rear page if you reside in the U.S.A., or refer to "WARRANTY SERVICE" on the rear page if you reside in Canada.

The unit does not respond.
• This unit can be reset when all operations are rejected. To reset the unit, press and hold (ON/OFF) for 10 seconds or more. (The pairing device information will not be deleted.)
Cannot charge the unit.
• Make sure the computer is turned on and is not on standby or sleep mode.
• Is the USB port you are currently using working properly? If your computer has other USB ports, unplug the connector from its current port and plug it into one of the other ports.
• If the measures mentioned above are not applicable, unplug the USB charging cord and plug it in again.
• If the change time and operating time become shortened, the battery may have run down. (Number of charging times of the installed battery: Approximately 500.)
LED does not light when charging / Charging takes longer.
• Is the USB charging cord (supplied) connected firmly to the USB terminal of the computer? (→ Rear page, [3])
• Make sure the charge is at room temperature between 10 °C and 35 °C.
The power does not turn on.
• Is the unit being charged? The power cannot be turned ON during charging. (→ Rear page, [3])
The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
No sound.
• The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
Low volume.
• Increase the volume of the unit. (→ Rear page, [3])
• Increase the volume on the Bluetooth® device.
Sound from the device is cut off / Sound quality is bad.
• Sound may be disrupted if signals are blocked. Do not fully cover this unit with the palm of your hand, etc.
• The device may be out of the 10 m communication range. Move the device closer to this unit.
• Remove any obstacle between this unit and the device.
• Switch off any wireless LAN device when not in use.
• A communication problem may arise if the battery is not fully charged. Charge the unit. (→ Rear page, [3])
You cannot hear the other person.
• Make sure that the unit and the Bluetooth® enabled phone are turned on.
• Check if the unit and the Bluetooth® enabled phone are connected. (→ Rear page, [3])
• Check the audio settings of the Bluetooth® enabled phone. Switch the calling device to the unit if it is set to the Bluetooth® enabled phone. (→ Rear page, [3])
• If the volume of the other person's voice is too low, increase the volume of both the unit and the Bluetooth® enabled phone.
Cannot make a phone call.
• Check if the Bluetooth® compatible device supports "HSP" or "HFP" profile. For details on profiles, see "Listening to music" and "Making a phone call" in "Operating Instructions (PDF format)". Also refer to the operating manual for the Bluetooth® enabled phone.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. The present apparatus is conforming to the article 15 des règles de la FCC et aux normes CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.
Modèle: RP-HTX80B
IC: 216A-RP17X80B
Cet équipement est conforme aux limites d'exposition aux rayonnements électromagnétiques pour un environnement non contrôlé et les exigences des règles d'exposition radioélectriques (RE) de la FCC et les lignes directrices d'exposition aux fréquences radioélectriques (RF) CNR-102 de l'IC. Cet équipement émet une énergie RF très faible qui ne considère conforme sans évaluation du débit d'absorption spécifique (DAS).

CE QUI SUIT NE S'APPLIQUE QU'AU CANADA. CAN ICES-3(B)/NMB-3(J) ■ Unit
WARNING:
To reduce the risk of fire, electric shock or product damage,
• Do not expose this unit to rain, moisture, dripping or splashing.
• Do not place objects filled with liquids, such as vases, on this unit.
• Use only the recommended accessories.
• Do not remove covers.
• Do not repair this unit by yourself. Refer servicing to qualified service personnel.
• Avoid using or placing this unit near sources of heat.
• Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
• Do not listen with this unit at high volume in places where you need to hear sounds from the surrounding environment for safety, such as at railroad crossings, and construction sites.
■ Allergies
• Discontinue use if you experience discomfort with the speakers or any other parts that directly contact your skin.
• Continued use may cause rashes or other allergic reactions.
■ Precautions for listening with the Headphones
• Do not use your headphones at a high volume. Hearing experts advise against continuous extended play.
• If you experience a ringing in your ears, reduce volume or discontinue use.
• Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
• You should use extreme caution or temporarily discontinue use in potentially hazardous situations.

The unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
This unit is intended for use in moderate and tropical climates.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

Français
Safety precautions

Pour les résidents de la Californie
Avertissement - Proposition 65
AVERTISSEMENT
Ce produit contient un produit chimique qui, selon l'état de la Californie, peut causer un cancer, des anomalies congénitales ou d'autres problèmes liés à la reproduction. (Pour les États-Unis seulement)

Uniquement pour les États-Unis et le Canada
L'appareil que vous vous êtes procuré est alimenté par une batterie au lithium-ion. Pour des renseignements sur le recyclage de la batterie, veuillez composer le 1-800-8-BATTERY.

CE QUI SUIT NE S'APPLIQUE QU'AUX ÉTATS-UNIS ET AU CANADA. Le présent appareil est conforme à la partie 15 des règles de la FCC et aux normes CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.
Modèle: RP-HTX80B
IC: 216A-RP17X80B
Cet équipement est conforme aux limites d'exposition aux rayonnements électromagnétiques pour un environnement non contrôlé et les exigences des règles d'exposition radioélectriques (RE) de la FCC et les lignes directrices d'exposition aux fréquences radioélectriques (RF) CNR-102 de l'IC. Cet équipement émet une énergie RF très faible qui ne considère conforme sans évaluation du débit d'absorption spécifique (DAS).

CE QUI SUIT NE S'APPLIQUE QU'AU CANADA. CAN ICES-3(B)/NMB-3(J) ■ Unit
WARNING:
To reduce the risk of fire, electric shock or product damage,
• Do not expose this unit to rain, moisture, dripping or splashing.
• Do not place objects filled with liquids, such as vases, on this unit.
• Use only the recommended accessories.
• Do not remove covers.
• Do not repair this unit by yourself. Refer servicing to qualified service personnel.
• Avoid using or placing this unit near sources of heat.
• Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
• Do not listen with this unit at high volume in places where you need to hear sounds from the surrounding environment for safety, such as at railroad crossings, and construction sites.
■ Allergies
• Discontinue use if you experience discomfort with the speakers or any other parts that directly contact your skin.
• Continued use may cause rashes or other allergic reactions.
■ Precautions for listening with the Headphones
• Do not use your headphones at a high volume. Hearing experts advise against continuous extended play.
• If you experience a ringing in your ears, reduce volume or discontinue use.
• Do not use while operating a motorized vehicle. It may create a traffic hazard and is illegal in many areas.
• You should use extreme caution or temporarily discontinue use in potentially hazardous situations.

The unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
This unit is intended for use in moderate and tropical climates.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

Troubleshooting
Before requesting service, make the following checks. If you are in doubt about some of the check points, or if the remedies indicated do not solve the problem, consult your dealer for instructions.

The unit does not respond.
• This unit can be reset when all operations are rejected. To reset the unit, press and hold (ON/OFF) for 10 seconds or more. (The pairing device information will not be deleted.)
Cannot charge the unit.
• Make sure the computer is turned on and is not on standby or sleep mode.
• Is the USB port you are currently using working properly? If your computer has other USB ports, unplug the connector from its current port and plug it into one of the other ports.
• If the measures mentioned above are not applicable, unplug the USB charging cord and plug it in again.
• If the change time and operating time become shortened, the battery may have run down. (Number of charging times of the installed battery: Approximately 500.)
LED does not light during charging / Charging takes longer.
• Is the USB charging cord (supplied) connected firmly to the USB terminal of the computer? (→ Rear page, [3])
• Make sure to charge in a room temperature between 10 °C and 35 °C.
The power does not turn on.
• Is the unit being charged? The power cannot be turned ON during charging. (→ Rear page, [3])
The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
No sound.
• The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
Low volume.
• Increase the volume of the unit. (→ Rear page, [3])
• Increase the volume on the Bluetooth® device.
Sound from the device is cut off / Sound quality is bad.
• Sound may be disrupted if signals are blocked. Do not fully cover this unit with the palm of your hand, etc.
• The device may be out of the 10 m communication range. Move the device closer to this unit.
• Remove any obstacle between this unit and the device.
• Switch off any wireless LAN device when not in use.
• A communication problem may arise if the battery is not fully charged. Charge the unit. (→ Rear page, [3])
You cannot hear the other person.
• Make sure that the unit and the Bluetooth® enabled phone are turned on.
• Check if the unit and the Bluetooth® enabled phone are connected. (→ Rear page, [3])
• Check the audio settings of the Bluetooth® enabled phone. Switch the calling device to the unit if it is set to the Bluetooth® enabled phone. (→ Rear page, [3])
• If the volume of the other person's voice is too low, increase the volume of both the unit and the Bluetooth® enabled phone.
Cannot make a phone call.
• Check if the Bluetooth® compatible device supports "HSP" or "HFP" profile. For details on profiles, see "Listening to music" and "Making a phone call" in "Operating Instructions (PDF format)". Also refer to the operating manual for the Bluetooth® enabled phone.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. The present apparatus is conforming to the article 15 des règles de la FCC et aux normes CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.
Modèle: RP-HTX80B
IC: 216A-RP17X80B
Cet équipement est conforme aux limites d'exposition aux rayonnements électromagnétiques pour un environnement non contrôlé et les exigences des règles d'exposition radioélectriques (RE) de la FCC et les lignes directrices d'exposition aux fréquences radioélectriques (RF) CNR-102 de l'IC. Cet équipement émet une énergie RF très faible qui ne considère conforme sans évaluation du débit d'absorption spécifique (DAS).

CE QUI SUIT NE S'APPLIQUE QU'AU CANADA. Le présent appareil est conforme à la partie 15 des règles de la FCC et aux normes CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes:
(1) l'appareil ne doit pas produire de brouillage, et
(2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.
Modèle: RP-HTX80B
IC: 216A-RP17X80B
Cet équipement est conforme aux limites d'exposition aux rayonnements électromagnétiques pour un environnement non contrôlé et les exigences des règles d'exposition radioélectriques (RE) de la FCC et les lignes directrices d'exposition aux fréquences radioélectriques (RF) CNR-102 de l'IC. Cet équipement émet une énergie RF très faible qui ne considère conforme sans évaluation du débit d'absorption spécifique (DAS).

The unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
This unit is intended for use in moderate and tropical climates.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

Español
Safety precautions

LO QUE SIGUE SE APLICA SOLAMENTE EN LOS ESTADOS UNIDOS Y EL CANADÁ. Este dispositivo cumple con (a) las normas para dispositivos exentos de licencia RSS de Industry Canada. El funcionamiento está sujeto a las dos siguientes condiciones:
(1) este dispositivo no puede producir interferencias y
(2) este dispositivo debe aceptar cualquier interferencia, incluyendo aquellas que puedan ocasionar un funcionamiento no deseado del mismo.
ID FCC: ACJ-FRP-HTX80B
Modelo: RP-HTX80B
IC: 216A-RP17X80B
Este transmisor no debe colocarse o hacerse funcionar junto con otra antena o transmisor.

Este dispositivo cumple los límites de exposición a la radiación de la FCC/IC establecidos para un entorno no controlado, así como las directrices de exposición a radio frecuencia (RF) de la FCC y la RSS-102 de las reglas de exposición a radio frecuencia (RF) de la IC.
Este equipo presenta niveles muy bajos de energía RF que se estima cumplen sin necesidad de comprobar la relación específica de absorción (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

The unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
This unit is intended for use in moderate and tropical climates.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

Troubleshooting
Before requesting service, make the following checks. If you are in doubt about some of the check points, or if the remedies indicated do not solve the problem, consult your dealer for instructions.

The unit does not respond.
• This unit can be reset when all operations are rejected. To reset the unit, press and hold (ON/OFF) for 10 seconds or more. (The pairing device information will not be deleted.)
Cannot charge the unit.
• Make sure the computer is turned on and is not on standby or sleep mode.
• Is the USB port you are currently using working properly? If your computer has other USB ports, unplug the connector from its current port and plug it into one of the other ports.
• If the measures mentioned above are not applicable, unplug the USB charging cord and plug it in again.
• If the change time and operating time become shortened, the battery may have run down. (Number of charging times of the installed battery: Approximately 500.)
LED does not light during charging / Charging takes longer.
• Is the USB charging cord (supplied) connected firmly to the USB terminal of the computer? (→ Rear page, [3])
• Make sure to charge in a room temperature between 10 °C and 35 °C.
The power does not turn on.
• Is the unit being charged? The power cannot be turned ON during charging. (→ Rear page, [3])
The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
No sound.
• The device cannot be connected.
• Delete the pairing information for this unit from the Bluetooth® device, then pair them again. (→ Rear page, [3])
Low volume.
• Increase the volume of the unit. (→ Rear page, [3])
• Increase the volume on the Bluetooth® device.
Sound from the device is cut off / Sound quality is bad.
• Sound may be disrupted if signals are blocked. Do not fully cover this unit with the palm of your hand, etc.
• The device may be out of the 10 m communication range. Move the device closer to this unit.
• Remove any obstacle between this unit and the device.
• Switch off any wireless LAN device when not in use.
• A communication problem may arise if the battery is not fully charged. Charge the unit. (→ Rear page, [3])
You cannot hear the other person.
• Make sure that the unit and the Bluetooth® enabled phone are turned on.
• Check if the unit and the Bluetooth® enabled phone are connected. (→ Rear page, [3])
• Check the audio settings of the Bluetooth® enabled phone. Switch the calling device to the unit if it is set to the Bluetooth® enabled phone. (→ Rear page, [3])
• If the volume of the other person's voice is too low, increase the volume of both the unit and the Bluetooth® enabled phone.
Cannot make a phone call.
• Check if the Bluetooth® compatible device supports "HSP" or "HFP" profile. For details on profiles, see "Listening to music" and "Making a phone call" in "Operating Instructions (PDF format)". Also refer to the operating manual for the Bluetooth® enabled phone.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

The unit may receive radio interference caused by mobile telephones during use. If such interference occurs, please increase separation between this unit and the mobile telephone.
This unit is intended for use in moderate and tropical climates.

Maintenance
Clean this unit with a dry and soft cloth.
• Do not use solvents including benzene, thinner, alcohol, kitchen detergent, a chemical wipe, etc. This might cause the exterior case to be deformed or the coating to come off.
Specifications
■ General
Power supply DC 5 V, 500 mA
Internal battery 3.7 V (Li-polymer 430 mAh)
Operating time * Approx. 20 hours
Charging time * (25 °C (77 °F)) Approx. 2.5 hours
Charging temperature range 10 °C to 35 °C (50 °F to 95 °F)
Operating temperature range 0 °C to 40 °C (32 °F to 104 °F)
Operating humidity range 35%RH to 80%RH (no condensation)
Mass (Weight) Approx. 190 g (X.X oz.)
■ Bluetooth® section
Frequency band 2402 MHz to 2480 MHz
Supported profiles A2DP, AVRCP, HSP, HFP
Supported codec SBC
*1 It may be shorter depending on the operating conditions.
*2 Time taken to recharge from empty to full.

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

THE FOLLOWING APPLIES ONLY IN THE U.S.A. AND CANADA. This device complies with Part 15 of FCC Rules and Industry Canada's license-exempt RSSAs. Operation is subject to the following two conditions:
(1) This device may not cause interference, and
(2) This device must accept any interference, including interference that may cause undesired operation of this device.
FCC ID: ACJ-FRP-HTX80B
Model: RP-HTX80B
IC: 216A-RP17X80B
This transmitter must not be co-located or operated in conjunction with any other intentional RF device.
This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment and meets the FCC radio frequency (RF) Exposure Guidelines and RSS-102 of the IC radio frequency (RF) Exposure Rules. This equipment has very low levels of RF energy that is deemed to comply without testing of specific absorption rate (SAR).

