

iBTW215VM - QSG (English)
Size: 700 x 160 mm (unfold), 140 x 160 mm (folded)
Color: 1C + 1C
material: 154gsm, art card, 1C + 1C, ☐☐
July. 14, 2026



Front Cover

iHome

Model: iBTW215VM

Bluetooth Sunrise Alarm Clock

with Wireless Charging and Mood Lighting

Quick Start Guide

1 YEAR WARRANTY

For warranty visit:
<https://support.ihome.com/>

What's Included:

iBTW215VM unit

USB-C charging cable (included)

Overview of Controls

Top

Bluetooth/Nature Sound/Play/Pause button

Long press to activate Bluetooth pairing mode. Short press to play or pause audio playback

Wireless Charging Pad

Mood Light Button

Turns the ambient mood light on or off, and cycles through available lighting modes.

Volume Down/Previous Song

Short press to decrease the volume level. Long press to return to the previous audio track.

Volume Up/Next Song

Short press to increase the volume level. Long press to skip to the next audio track

Front

Snooze / Display Light Button

Short press to cycle through 5 brightness levels for the display or turn it off. During an alarm, pressing this button activates the snooze function.

Back

USB-A port

Insert USB flash drive with mp3 audio files automatically switch to USB mode. (USB Drive does not support charging and output power supply.)

Charging Indicator

Charging Devices

Connect the charging cable to the USB-C port on the back of the unit, and the standard end to USB-PD adapter.

Operations

Power On and Off

Slide the Power Switch to ON. The display will illuminate, and the unit will enter standby mode, ready for use. Slide the switch to OFF to completely shut down the device.

Using Wireless Charging

- Power Supply Required: The device must be connected to **USB adapter** to enable wireless charging.
- Battery Mode Restriction: Wireless charging will not operate when the device runs on its built-in battery.

CAUTION: Remove metal protective or magnetic case from phone before charging. When charging phone, do not place magnetic-stripped or other metal objects on the charger. Doing so could damage the object or this unit.

Red light Slow blinking : Device is charging properly.

Red light off: Device is charged.

Rapid blinking: Device is not charging properly.

Note: The lightning icon may continue to blink slowly when iOS devices are fully charged.

Display Brightness Adjustment

In clock display mode, short press the Snooze / Display Light Button repeatedly to cycle through five brightness settings: Brightest, Medium, Slightly Bright, Dim, Off .

Battery and Memory Function

The unit has a built-in rechargeable battery. When external power is lost, the battery maintains the current time and all alarm settings. If the battery level is low, the battery indicator icon will flash. If the battery is fully charged, the indicator icon off. If not charged, the unit will automatically shut down while preserving all settings.

Note: Battery charging only operates when the unit is connected to external power.

Voice-Activated Display

When operating on battery power (without external power), the display will automatically turn off to save energy. A sound louder than approximately 90 decibels **from 5 inch** (such as clapping or speaking loudly) will wake the display for 6 seconds , after which it will turn off again.

Factory Reset

If the unit malfunctions or you wish to clear all personalized settings, use the extended tip of a paper clip or other thin tool to press in the Reset Button. This action restores the device to its original factory state.

Bluetooth Connection and Automatic Time Sync

- Ensure the unit is powered ON .
- Long press the Bluetooth/Nature Sound/Play/Pause button until you hear a confirmation tone. The Bluetooth function will activate, and the device name iHome iBTW215 will be discoverable.
- On your smartphone, enable Bluetooth and search for available devices. Select iHome iBTW215 from the list.
- Once connected, the unit will automatically synchronize the time with your phone.
- After the initial pairing, the device will automatically reconnect to the last paired phone when powered on.

Note: First-time pairing may require permission to access device information.

Bluetooth Speaker

After successfully connecting your phone via Bluetooth, you can play music, podcasts, or other audio directly through the unit.

Play / Pause: Short press the Bluetooth/Nature Sound/Play/Pause button .

Adjust Volume: Short press the Volume Up / Down Buttons .

Switch Tracks: Long press the Volume Up / Down Buttons to skip forward or backward.

White Noise and Nature Sounds

The unit features 12 built-in relaxation sounds to aid sleep, meditation, and relaxation.

Note: Ensure Bluetooth and USB playback are disconnected before using this function.

- Short press the Bluetooth/Nature Sound/Play/Pause button to start playback.
- Short press the Volume Up /Down button to adjust the volume. Long press it to skip to the next track.
- Press the Bluetooth/Nature Sound /Play/Pause button again to stop.

Sound List:

1. Rain 2. Thunderstorm 3. Bird Song 4. Cricket 5. Bonfire 6. Wind 7. Stream 8. Waterfall 9. Ocean Wave 10. Lullaby 11. Yoga Music 12. Meditation Music

Mood Lighting

The built-in mood light creates a soft ambient glow for your bedside. Press the Mood Light Button to turn the light on and cycle through different lighting modes. Press and hold the button to turn it off.

Back

The Display

AM Indicator

Alarm 1

Battery Indicator

Alarm 2

PM Indicator

Setting the Clock

Bluetooth Time Sync is enabled by default. Once the iBTW215 is paired to your device the time will set automatically.

To manually set the clock:

- Short press Time Set button to switch between 12 or 24 hour format.
- Press and hold the Time Set Button for 2 seconds to enter Time set process.
- The hour on the display flashes. Press + or - Button to adjust the hour. Press Time Set Button to confirm
- The Minute on the display flashes. Press + or - Button to adjust the minute. Press Time Set Button to confirm and exit the process.

Alarm Clock Functions

- Power Switch Sliding to ON powers the unit on and enters standby mode. Sliding to OFF shuts the unit down completely.
- Alarm 1 Switch Toggles ON to activate Alarm 1 (indicator icon on), OFF to deactivate it (indicator **icon** off).
- Alarm 2 Switch Toggles ON to activate Alarm 2 (indicator **icon** on), OFF to deactivate it (indicator **icon** off).
- Alarm Set Button Long press for 1.5 seconds to enter Alarm setting mode. Short press to confirm settings or briefly display the set alarm time for 3 seconds.

Bottom

Activating and Deactivating Alarms

Alarm 1: Slide the Alarm 1 Switch to ON to enable, or OFF to disable.

Alarm 2: Slide the Alarm 2 Switch to ON to enable, or OFF to disable.

The corresponding indicator icon will light up when an alarm is active.

Setting Alarm

- Long Press TUNES SET button to set the desired wake-to alarm source, Press the + or - Buttons to adjust the desired alarm volume, short press TUNES SET button to confirm the alarm Volume setting, then press + or - Buttons to select a tone sounds, total 8 tone sounds.
- Long press the Alarm 2 Set button for 1.5 seconds until the hour digits begin to flash.
- Use the Volume + or - Buttons to adjust the desired hour.
- Short press the Alarm 2 Set button to confirm the hour; the minute digits will now flash.
- Use the Volume + or - Buttons to adjust the desired minute.
- Short press the Alarm 2 Set Button to save the setting and return to the clock display.

Note: The process for setting Alarm 1 follows the same steps.

Viewing the Alarm Time

To quickly check the set time for Alarm 1/2, short press the Alarm 1/2 Set Button. The alarm time will appear on the display for 3 seconds before returning to the current time.

Sunrise Simulation Wake-Up Light

The unit features a gentle sunrise simulation to help you wake up naturally. Five minutes before the alarm is scheduled to ring, the built-in light will gradually brighten from dim to full brightness.

At the set alarm time, the light will reach maximum brightness, accompanied by the alarm sound.

Snooze Function

When the alarm rings, a short press of the snooze/indicator light button will pause the alarm for ten minutes. During the snooze period, the alarm indicator light will flash. You can use the snooze function up to 5 times per alarm. Pressing any button other than the snooze button while the alarm is ringing will turn off the alarm for the day. The alarm will not stop automatically if no action is taken.

Maintenance

Remove plastic protective film from the clock display.

Place the unit on a level surface away from sources of direct sunlight or excessive heat.

Protect your furniture when placing your unit on a natural wood and lacquered finish. A cloth or other protective material should be placed between it and the furniture.

Clean your unit with a soft cloth moistened only with mild soap and water. Stronger cleaning agents such as thinner or similar materials can damage the surface of the unit.

FCC Information

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

-- Reorient or relocate the receiving antenna.

-- Increase the separation between the equipment and receiver.

-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

-- Consult the dealer or an experienced radio/TV technician for help.

ISED Information

This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions:

(1) This device may not cause interference.

(2) This device must accept any interference, including interference that may cause undesired operation of the device.

L'émetteur/récepteur exempt de licence contenu dans le présent appareil est conforme aux CNR d'Innovation, Sciences et Développement économique Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes :

(1) L'appareil ne doit pas produire de brouillage;

(2) L'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

CAN ICES-3 (B) / NMB-3(B)

RF Exposure Compliance

Bluetooth:

The equipment complies with FCC/IC Radiation exposure limit set forth for uncontrolled environment. The device shall be operated and installed without restriction.

Cet équipement est conforme aux limites d'exposition aux rayonnements établies par la FCC/IC pour un environnement non contrôlé. Son utilisation et son installation ne sont assujetties à aucune restriction.

Wireless charger:

This equipment complies with FCC/IC radiation exposure limits set forth for an uncontrolled environment. This equipment is installed and operated with minimum distance 20cm/8in between the radiator and human body.

Cet équipement est conforme aux limites d'exposition aux rayonnements FCC/IC établies pour un environnement non contrôlé. Cet équipement est installé et utilise à avec une distance minimale de 20cm/8in entre le radiateur et le corps humain.

©2026 SDI Technologies, Inc. All rights reserved.
Questions? Visit <https://support.ihome.com/>

iBTW215VM-061526-A

Printed in China