

Parent Unit Icons (continued)

Alert Icons

• Displays when the parent unit's battery is low and needs charging.

• Displays when motion is detected by a baby unit.

• Displays when sound is detected by a baby unit.

• Displays when the temperature detected by the baby unit exceeds the set maximum.

• Displays when the temperature detected by the baby unit is lower than the set minimum.

Night Vision (B&W and Color)

Night Vision Mode	Description
	B&W night vision - Suitable for extremely dark or low light environments.
	Color night vision - Suitable for low-light room conditions with night light as an assisting light source.

Change your night vision viewing mode

1. Press the **Night mode quick set key** to view the Night mode menu.

2. Press to choose for black and white night vision viewing or for color night vision viewing.

The baby unit has infrared LEDs that allow you to see your baby clearly at night or in a dark room. When the baby unit being viewed detects low light levels, the infrared LEDs are switched on automatically. When the images from the baby unit are in black and white, and appears on the screen. When the images from the baby unit are in color, appears on the screen.

- Notes
- It is normal to see a short white glare on your parent unit screen as the baby unit is adapting to the dark environment.
 - When the infrared LEDs are on, it is normal for the images to be in black and white.
 - If night vision is not activated, newly saved settings will apply the next time night vision is activated.
- Tip
- The video quality may vary depending on the surrounding environment and interfering factors like lightings, objects, colors and backgrounds. Adjust the baby unit's angle or place the baby unit at a higher elevation to prevent glare and blurry displays.

Sound Detection and Auto Wake Up

Adjust Sound Detection Sensitivity
You can turn on **Sound Detection Alert** and adjust the **Sound Sensitivity** to only detect your desired level of sounds. When detected, the parent unit screen turns on if it has been switched off or dimmed.

When the baby unit detects sounds that exceed the chosen level, the parent unit screen turns on and the baby unit transmits the detected sounds to the parent unit. You will be able to see and hear your baby.

If you have turned on **Sound Detection Alert**, the parent unit beeps when the baby unit detect sounds.

Sound Sensitivity Level	Level 3 (Highest)	Level 2 (Medium)	Level 1 (Lowest)
Description	The parent unit screen and speaker turn on for very small sounds, including background noises from your baby's room.	The parent unit screen and speaker turn on for babbling and louder sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.	The parent unit screen and speaker turn on only for loud crying or screaming sounds from your baby. The parent unit remains quiet when your baby makes soft sounds.

Sound Activated Screen and Audio - Auto Wake-Up

When **Auto Wake-Up** is turned on, the parent unit screen stays off to save power when the baby unit detects no sound. Once the baby unit detects sounds that are louder than the chosen sound sensitivity level, the parent unit screen and speaker turn on automatically. The parent unit will then turn off again after no sound has been detected for a while.

- Notes:
- If you have muted the parent unit speaker, only the parent unit screen will turn on when a sound is detected.
 - If you have turned on **Auto Wake Up** but turned off **Sound Detection Alert**, the parent unit will wake up when the baby unit detects sounds that are louder than the chosen sound sensitivity level.

Motion Detection

Adjust Motion Detection Sensitivity
You can turn on **Motion Alert** and adjust the **Motion Sensitivity** to only detect your desired level of motion. When detected, the parent unit screen turns on if it has been switched off or dimmed.

When the baby unit detects motions that exceed the chosen level, the parent unit screen turns on and displays lives images from the baby unit. You will be able to see and hear your baby.

If you have turned on **Motion Alert**, the parent unit beeps when the baby unit detect movements.

Motion Sensitivity Level	Level 3 (Highest)	Level 2 (Medium)	Level 1 (Lowest)
Description	The parent unit screen and speaker turn on for small motions, such as yawning or stretching.	The parent unit screen and speaker turn on for normal daily motions, such as people walking around the house.	The parent unit screen and speaker only turn on for large motions, such as children running or jumping around.

Night Light

Want a softer hue from the baby unit's night light to relax your little one? You can control the brightness of its glow remotely from your parent unit, or directly on the baby unit.

Adjust the night light on the parent unit

1. Press the **Night mode quick set key** to view the Night mode menu.

2. Press to brighten the night light (or turn on the night light when it is switched off). Press to dim the night light (or turn off the night light when it is at the lowest brightness level).

- OR -

1. Press **MENU** to enter the main menu.

2. Press and to select , press **SELECT**.

3. Press and to select , press **SELECT**.

4. Press and to choose the desired brightness level, then press **SELECT** to confirm your selection.

Adjust the night light on the baby unit

- Tap the **Night light control key** located on the top of the baby unit to turn on/off the night light.
- Tap and hold** the **Night light control key** to adjust the night light's brightness.

Troubleshooting	
Symptom	Try this
Why does the baby monitor not respond normally?	Try the following (in the order listed) for a common cure: 1. Disconnect the power to the baby unit(s) and the parent unit. 2. Wait a few seconds before connecting power back to the baby unit(s) and the parent unit. 3. Turn on the baby unit(s) and the parent unit. 4. Wait for the parent unit to synchronize with the baby unit(s). Allow up to one minute for this to take place.
Why doesn't the baby unit's and parent unit's power LED turn on when I switch on the units?	The parent unit may not be connected to power. Insert the appliance plug into the power jack of the parent unit and put the adapter in a wall socket. Then, press the Power button on the parent unit to establish connection with the baby unit. The baby unit may not be connected to power. Insert the appliance plug into the power jack of the baby unit and put the adapter in a wall socket. Then, slide the On/Off switch on the baby unit to establish connection with the parent unit.
Why doesn't my parent unit charge when connected to AC power?	Make sure your power source is not controlled by a wall switch.
Why are my images in black and white?	The images are in black white during night-time or in a dark room when night vision is automatically activated. You can also choose to view your baby at night in color, see Night Vision (B&W and Color) to learn how.
Why is the baby unit producing a high-pitched noise?	The parent unit and baby unit(s) may be too close to each other. - Move the parent unit away from the baby unit(s) until the noise stops; OR - Turn down the volume of your parent unit.
Why does the parent unit beep?	The baby unit(s) may be out of range. Move the parent unit closer to the baby unit(s) (but not less than 3 feet). The parent unit may not have enough battery for the parent unit to perform normally. Charge the parent unit until the battery icon becomes solid .
Why can't I hear any sounds from the parent unit? Why can't I hear my baby cry?	The parent unit speaker volume may be too low or muted. Press VOL to open the volume adjustment menu, then press to increase the speaker volume. Or you can use the parent unit menu to change the parent unit's sound sensitivity to the highest level (level 5), see Sound Detection and Auto Wake Up .
Why can't I establish a connection? Why does my connection cut off every now and then? Why are there sound interruptions?	The baby unit(s) may be out of range. Move the parent unit closer to the baby unit(s) (but not less than 3 feet). Other electronic and wireless products may cause interference with your baby monitor. Try installing your baby monitor as far away from these devices as possible. If you powered on only one baby unit but have two paired to the parent unit, your parent unit may display and the LINK LED light flashes. Switch to the baby unit you have turned on via the menu.

The RBRC seal

The RBRC seal on the Li-ion battery indicates that LeapFrog Enterprises, Inc. is voluntarily participating in an industry program to collect and recycle these batteries at the end of their useful lives, when taken out of service within the United States and Canada. The program provides a convenient alternative to placing used Li-ion batteries into the trash or municipal waste, which may be illegal in your area. LeapFrog's participation makes it easy for you to drop off the spent battery at local retailers participating in the program or at authorized LeapFrog product service centers. Please call 1 (800) 8 BATTERY for information on Li-ion battery recycling and disposal bans/restrictions in your area. LeapFrog's involvement in this program is part of its commitment to protecting our environment and conserving natural resources. The RBRC Seal and 1 (800) 8 BATTERY® are registered trademarks of Call2recycle, Inc.

FCC and IC regulations

FCC Part 15
This equipment has been tested and found to comply with the requirements for a Class B digital device under Part 15 of the Federal Communications Commission (FCC) rules. These requirements are intended to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

WARNING: Changes or modifications to this equipment not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with Part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that can cause undesired operation.

To ensure safety of users, the FCC has established criteria for the amount of radio frequency energy that can be safely absorbed by a user or bystander according to the intended usage of the product. This product has been tested and found to comply with the FCC criteria. The baby unit shall be installed and used such that parts of all persons' body are maintained at a distance of approximately 8 in (20 cm) or more. The transmitter and antenna of the parent unit shall be held at least 1 in (2.5 cm) from your face.

This Class B digital apparatus complies with Canadian requirement: CAN ICES-3 (B)/NMB-3(B)

Industry Canada
This device contains licence-exempt transmitter(s)/receiver(s) that comply with Innovation, Science and Economic Development Canada's licence-exempt RSS(s). Operation is subject to the following two conditions: (1) This device may not cause interference. (2) This device must accept any interference, including interference that may cause undesired operation of the device.

The term "IC" before the certification/registration number only signifies that the Industry Canada technical specifications were met. This product meets the applicable Innovation, Science and Economic Development Canada technical specifications.

RF radiation exposure statement
The baby unit complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. The baby unit should be installed and operated with a minimum distance of 8 in (20 cm) between the baby unit and all persons' body. Use of other accessories may not ensure compliance with FCC RF exposure guidelines. This transmitter must not be co-located or operating in conjunction with any other antenna or transmitter. This equipment complies also with Industry Canada RSS-102 with respect to Canada's Health Code 6 for Exposure of Humans to RF Fields.

California Energy Commission battery charging testing mode

This baby monitor meets the California Energy Commission (CEC) regulations for energy consumption. Your baby monitor is set up to comply with the energy-conserving standards right out of the box. Follow the instructions to install and charge the battery. The CEC battery charging testing mode is activated while charging. Even if the parent unit is paired to baby units, the CEC battery charging testing mode is activated while it is powered off and charging.

For cETL compliance only

Measures de sécurité importantes
La plaque signalétique appliquée est située au bas du socle de l'unité du bébé.
Les risques que vous utilisez votre appareil, vous devriez toujours suivre certaines mesures de précaution de base afin de réduire les risques d'incendie, d'électrocution et de blessures corporelles, dont ceux qui suivent:

1. Observez toutes les instructions et mises en garde inscrites sur l'appareil.
2. L'installation par un adulte est requise.
3. MISE EN GARDE: N'installez pas l'unité du bébé à une hauteur supérieure à 2 mètres.
4. Ce produit ne remplace pas la surveillance adulte du nourrisson. La supervision du nourrisson est la responsabilité du parent ou de la personne qui s'occupe de l'enfant. Ce produit pourrait cesser de fonctionner et, par conséquent, vous ne devriez pas présumer qu'il continuera de fonctionner correctement pendant une période de temps donnée. De plus, il ne s'agit pas d'un instrument médical et ne devrait pas être utilisé comme tel. Ce produit est destiné à vous aider à superviser votre bébé.
5. N'utilisez pas cet appareil près de l'eau ni de toute autre source d'humidité, par exemple, près d'une baignoire, cuve à lessive, évier de cuisine, dans un sous-sol humide ni près d'une piscine, dans un soussol humide ou une douche.
6. MISE EN GARDE: Utilisez uniquement la pile fournie. Un risque d'explosion pourrait survenir si un mauvais type de pile est utilisé pour l'unité du parent. La pile ne peut pas être soumise à des températures extrêmes élevées ou basses et à une faible pression d'air à haute altitude pendant l'utilisation, l'entreposage ou le transport. L'élimination de la pile dans le feu ou dans un four chaud, ou l'écrasement ou le découpage mécanique de la pile peuvent entraîner une explosion. Laisser la pile dans un environnement à température extrêmement élevée peut entraîner une explosion ou la fuite d'un liquide ou d'un gaz inflammable. Une pile soumise à une pression d'air extrêmement basse peut provoquer une explosion ou une fuite de liquide ou de gaz inflammable. Éliminer la pile usagée conformément aux informations du Scellé RBRC.
7. N'utilisez que les adaptateurs inclus avec ce produit. L'utilisation d'un adaptateur dont la polarité ou la tension serait inadéquates risque d'endommager sérieusement le produit et mettre votre sécurité en péril.

Informations sur les adaptateurs électriques : Adaptateur de l'unité du parent : Sortie : 5V DC 2A V Tech Telecommunications Ltd. Modèle: VT07EU050150 Adaptateur de l'unité du bébé : Sortie : 5V DC 1.5A V Tech Telecommunications Ltd. Modèle: VT07EU050200

Informations sur les piles rechargeables : Zhuhai Great Power Energy Co., Ltd. Lithium battery, 3.7V 5000mAh, Modèle: GSPB06090

Lorsqu'ils sont branchés dans une prise de courant, les adaptateurs secteur ont été conçus pour être orientés correctement, soit à la verticale ou au plancher. Les broches d'installation ne doivent pas être pliées, tordues ou endommagées. Les adaptateurs secteur ont été conçus pour être utilisés avec des alimentations et le maintenir en place si celui-ci est branché dans une prise au plafond, sous une table ou dans un meuble.

Pour les PRODUITS À BRANCHER À UNE PRISE DE COURANT, la prise de courant doit être installée près du produit, afin d'assurer une accessibilité sécuritaire à la prise de courant.

10. Débrancher ce produit de la prise de courant avant de procéder au nettoyage. N'utilisez pas de nettoyants en aérosols. Utilisez un chiffon humide pour le nettoyer.
11. Ne coupez pas les cordons d'alimentation pour remplacer les fiches, car ceci peut présenter un danger potentiel.
12. Ne laissez aucun objet reposer ni appuyer sur le cordon d'alimentation. N'installez pas cet appareil dans un endroit où l'on risque d'écarter le cordon d'alimentation ou de le piétrer.
13. Ne laissez fonctionner cet appareil qu'avec le type d'alimentation indiqué sur l'étiquette. Si vous ne connaissez pas le type d'alimentation que vous possédez à votre domicile, consultez votre marchand ou votre compagnie locale d'électricité.
14. Ne surchargez pas les prises de courant murales ni les rallonges électriques.
15. Ne placez pas cet appareil sur un chariot, meuble, trépied, support de montage ni table chancelants.
16. Les trous et ouvertures du boîtier, situés à l'arrière de l'appareil ou sous celui-ci, servent à aérer l'appareil. Pour empêcher de surchauffer, ne bloquez sous aucun prétexte ces ouvertures et n'empêchez pas l'aération adéquate de

Dim Mode

The parent unit display will dim to conserve energy after 5 minutes of inactivity, in which there were neither any key pressed nor alert received from the baby unit.

For LF920-2HD Only

Monitoring mode

1

2

Change different views - Single CAM

Select baby unit 1 or baby unit 2 to view the image from the selected baby unit.

1

Change different views - Patrol

Select Patrol mode as your monitoring mode to alternately view the image from baby units and every 10 seconds.

1 2

Change different views - Split

Select Split mode as your monitoring mode to view the images from both baby units at once.

Note

- While in Split mode, you can press to highlight the view of the baby unit or baby unit 2 , and hear the sounds transmitted from the highlighted baby unit.

Mount the baby unit on a dry wall (optional)

Notes

- Check for reception strength and the baby unit's viewing angle before drilling the holes.
- The types of screws and anchors you need depend on the composition of the wall. You may need to purchase the screws and anchors separately to mount your baby units.

1. Place the wall mount bracket on a wall and then use a pencil to mark the top and the bottom holes as shown. Remove the wall mount bracket and drill two holes in the wall (7/32 inch drill bit).

2. If you drill the holes into a stud, go to step 3.

- If you drill the holes into an object other than a stud, insert the wall anchors into the holes. Tap gently on the ends with a hammer until the wall anchors are flush with the wall.

3. Align the wall mount bracket and screws with the holes in the wall as shown. Tighten the screw in the middle hole first, so that the wall mount bracket position is fixed. You can tighten the other screw in the top hole.

OR

4. Place the baby unit on the wall mount bracket. Tighten the screw into the threaded socket at the bottom to secure the baby unit.

3. Insert the screws into the holes and tighten the screws until only 1/4 inch of the screws are exposed.

4. Place the baby unit on the wall mount bracket. Tighten the screw into the threaded socket at the bottom to secure the baby unit. Align the holes on the wall mount bracket with the screws on the wall, and slide the wall mount bracket down until it locks into place.

5. You can maximize your baby unit's viewing angles by tilting the wall mount bracket. Hold the baby unit, and then rotate the knob in an anti-clockwise direction. This will loosen the joint of the wall mount bracket. Tilt your baby unit up or down to adjust to your preferred angle. Then, rotate the knob in a clockwise direction to tighten the joint and secure the angle.

Disclaimer and Limitation of Liability

LeapFrog and its suppliers assume no responsibility for any damage or loss resulting from the use of this handbook. LeapFrog and its suppliers assume no responsibility for any loss or claims by third parties that may arise through the use of this software. LeapFrog and its suppliers assume no responsibility for any damage or loss caused by deletion of data as a result of malfunction, dead battery, or repairs. Be sure to make backup copies of important data on other media to protect against data loss.

THIS DEVICE COMPLIES WITH PART 15 OF THE FCC RULES. OPERATION IS SUBJECT TO THE FOLLOWING TWO CONDITIONS: (1) THIS DEVICE MAY NOT CAUSE HARMFUL INTERFERENCE, AND (2) THIS DEVICE MUST ACCEPT ANY INTERFERENCE RECEIVED, INCLUDING INTERFERENCE THAT MAY CAUSE UNDESIRABLE OPERATION.
CAN ICES-3 (B)/NMB-3(B)

Caution: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Warranty: Please visit our website at leapfrog.com/legal for full details of the warranty provided in your country.

Customer Support

Visit our Consumer Support website 24 hours a day at:
U.S.: leapfrog.com/support
C.A.: leapfrog.ca/support
Or call our **Customer Service number:** 1 (800) 701-5327 in the U.S. and Canada during Customer Service hours Monday to Friday, 7am - 2pm PST

Instructions for Care

FOR INDOOR, DRY-LOCATION USE ONLY.
To keep this product in good condition, follow these guidelines:

- Avoid putting it near heating appliances and devices that generate electrical noise (for example, motors or fluorescent lamps). - Clean with a slightly damp cloth in cold water (do not use soap, detergent, or other chemicals). - Make sure the product is dry before you connect it to the power source again. - Avoid prolonged exposure to extreme temperatures and direct sunlight or moisture.	- Do not spill liquid of any kind on this product or immerse the product in water as it may render it inoperative. - Keep food and beverages away from this product. - Never try to dismantle the unit. - Avoid dropping the product or treating it roughly.
--	--