



Figure 1 - LABEL LOCATION

FINAL
PROOF
APR 09 1998

WanderGuard E Remote Reset and Bypass

See Instruction manual for complete instructions & warnings.

To reset: Hold within 4' of WG-E door module. Press button **once**. LED turns green and alarm stops.

To bypass: Hold within 4' of WG-E door module. Press button **twice**. LED turns red. Door can be opened without sounding alarm.

0507-104

#18035 WG-E Remote Reset & Bypass FCC ID: LA5 WERB001 Canada 2459102936

model

200% size

WG-E remote bypass label 3/98 fh7 Bill Shaffer (402) 475-4002 ext. 3413

