

Safety 1st®

900 MHz Premium Privacy Link Monitor
Owner's Guide

No. 49242

Introduction

Thank you for purchasing the Safety 1st 900 MHz Premium Privacy Link Monitor. This dependable monitor allows you to hear your baby's sounds and activities, while the patented Voice Encryption Technology helps to keep outsiders from tuning into your communications for maximum privacy.

The baby's unit sends a continuous transmission of your baby's sounds to the parent's unit. The parent's unit is pager sized for easy mobility, and features both sound and lights to monitor your baby's activities. By using 900MHz technology, these units provide superior clarity with an extended range of up to 1000 feet. Both units feature unique "rubberized" bases that allow them to be placed on dresser tops and counters more securely. The parent's unit may be clipped to a belt for additional mobility, and utilizes an audio and visual alarm to indicate signal loss. The units have 4 channels to minimize outside interference and the Premium Privacy Link Monitor sends and receives encrypted audio signals that only it can decode. All other monitors or scanners will hear nothing but silence.

The parents' unit may be used with AC power or with a rechargeable battery pack (included) for portability. The baby's transmitter is AC powered, or can also be used with one 9 volt battery (not included) for maximum portability.

We are sure that you will find the 900 MHz Premium Privacy Link Monitor convenient and easy to use. To insure that you benefit from all of the great features that your monitor offers, and to make sure that you use it properly, we urge you to:

Please read all instructions carefully before using this product and keep these instructions for future reference. If you have any questions, please call our consumer relations number at (800)723-3065. In Canada please call (800)721-3389.

CAUTION:

- THE 900 MHz Premium Privacy Link Monitor IS NOT INTENDED TO REPLACE RESPONSIBLE AND PROPER PARENTAL SUPERVISION.
- YOU SHOULD CHECK YOUR CHILD'S ACTIVITY AT REGULAR INTERVALS AS THIS MONITOR WILL NOT ALERT PARENTS TO THE SILENT ACTIVITIES OF A CHILD.

WARNING: Changes or modifications to this unit not expressly approved by Safety 1st, Inc. could void user's authority to use equipment.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Safety Instructions

(caution flags/graphics)

WARNING: TO REDUCE THE RISK OF ELECTRICAL SHOCK, DO NOT REMOVE COVERS.

NO SERVICEABLE PARTS INSIDE.

REFER TO SAFETY 1ST CONSUMER RELATIONS: (800) 723-3065.

WARNING: TO REDUCE THE RISK OF FIRE OR ELECTRICAL SHOCK, DO NOT EXPOSE THIS PRODUCT TO WATER OR MOISTURE.

NEVER TOUCH THE END OF THE ADAPTER CORD WHEN THE ADAPTER IS PLUGGED INTO AN ELECTRICAL OUTLET.

READ INSTRUCTIONS: All the safety instructions should be read before the 900 MHz Premium Privacy Link Monitor is operated.

RETAIN INSTRUCTIONS: The safety instructions should be retained for future reference.

HEED WARNINGS: All warnings on the 900 MHz Premium Privacy Link Monitor and operating instructions should be adhered to.

FOLLOW INSTRUCTIONS: All operating instructions should be followed.

WATER AND MOISTURE: The 900 MHz Premium Privacy Link Monitor should not be used near water, for example, near a bath tub, wash bowl, kitchen sink, laundry tub, in a wet basement, near a swimming pool, etc.

VENTILATION: The 900 MHz Premium Privacy Link Monitor should be placed so that its location does not interfere with proper ventilation of the unit. For example, it should never be situated on a bed, sofa, rug or similar surface that may block ventilation.

HEAT: The 900 MHz Premium Privacy Link Monitor should be kept away from heat sources such as radiators, heat registers, stoves or other appliances that produce heat.

AC POWER SOURCE: The 900 MHz Premium Privacy Link Monitor should be connected only to the AC adapters supplied with the unit.

POWER CORD PROTECTION: The power supply cord should be routed so that it is not likely to be walked on or pinched by items placed upon or against it. Pay particular attention to the cord at the plug, convenience receptacle, and at the point it exits from the AC adapters.

CLEANING: Use a dry cotton cloth to keep the 900 MHz Premium Privacy Link Monitor free from dust. Do not use water!

NON-USE PERIODS: The power cords of the 900 MHz Premium Privacy Link Monitor should be unplugged from the outlet when unused for long periods of time. The batteries should also be removed during these periods.

OBJECT AND LIQUID ENTRY: Care should be taken so that objects do not fall onto the product, and liquids are not spilled into the enclosure through the openings.

DAMAGE REQUIRING SERVICE: The 900 MHz Premium Privacy Link Monitor should be serviced by qualified personnel when:

A: The power supply cord or plug has been damaged.

B: Objects have fallen or liquid has been spilled onto the product.

C: The Monitor has been exposed to rain.

D: The Monitor does not appear to operate normally or exhibits a marked change in its performance.

E: The Monitor has been dropped or the enclosure damaged.

THE USER... CHILD.

Contents

Parent's Unit (Receiver)

Baby's Unit (Transmitter)

Rechargeable battery pack (pre-installed in parent's unit)

(2) AC Adapters

(LD 0f: baby unit; parent unit; two AC adapters; rechargeable battery pack)

Battery Required (Optional)

One 9 volt alkaline battery (not included) for Baby's Unit

Features and Components - Parent's unit

1 Power/Volume Dial

2 LED Power Indicator (red)

3 LED Low Battery Indicator (amber)

4 LED Sound/Loss of Signal Lights

5 Antenna

6 Speaker

7 AC Adapter Jack

8 Belt Clip

9 Battery Compartment (rechargeable battery pack)

10 4 Channel Selector (located inside battery door)

11 Keyhole for optional wall mounting

(LD of parent's unit: front, left side, right side, back & back w/battery compartment open)

Parent's Unit (Receiver)

1 2 3 4 5 6 7 8 9 10 11

Features and Components - Baby's Unit

- 1 Antenna
- 2 LED Power/Low Battery Indicator
- 3 Microphone
- 4 ON/OFF Dial
- 5 Channel Selector
- 6 AC Adapter Jack
- 7 Battery Carrier

(LD of Child's unit front & back)

Baby's Unit (Transmitter)

1 2 3 4 5 6 7

AC Adapters

The AC Adapters are a low voltage power source that allows you to use your household electricity to run the Parent's and Baby's Units. They connect to the AC Adapter Jacks in the Parent's Unit and the Baby's Unit, and plug into any standard electrical outlet in your home.

CAUTION: These adapters were made with a specific design for Safety 1st 900 MHz Premium Privacy Link Monitor. They cannot be used with any other appliance. Never use a different type of adapter with this monitor.

WARNING: Never touch the end of the adapter cord when the adapter is plugged into an electrical outlet.

(LD of AC Adapter)

AC Adapter

Operating Your 900 MHz Premium Privacy Link Monitor

Follow these instructions to operate your 900 MHz Premium Privacy Link Monitor. Reference the illustrations on pages 2 & 3 for the location of all features described in these instructions.

Baby's Unit:

For best results, place the Baby's Unit on a table near the crib or bed. It should be facing the baby's head as close to the crib as possible, but out of baby's reach.

To Install Battery (One 9 volt battery not included)

Locate battery carrier on bottom of the Baby's unit and using Phillips head screwdriver remove the screw and take off the battery carrier as shown.

Snap 9 volt battery (not included) onto the battery pad and return to battery carrier as shown.

Replace battery carrier and secure with Phillips screwdriver as shown taking care not to over tighten.

(LD of baby's unit showing battery carrier screw being removed w/Phillips screwdriver)

(LD of 9 volt battery correctly snapped onto battery and pad being returned to proper position in carrier)

(LD of battery carrier replaced on the unit w/indication of screw being replaced w/Phillips screwdriver)

To Activate Baby's Unit

STEP 1 To use household power, plug the round end of adapter cord into the jack on the Baby's unit, then plug the the adapter into an electrical outlet.

NOTE: Battery power is available when one 9 Volt battery (not included) is installed in the Baby's Unit, however it is not recommended to use the battery power for extended periods when household power is available.

STEP 2 Locate the channel selector on the back of the Baby's unit. Select one of the four channel options, and note your selection on a separate piece of paper.

STEP 3 Turn power switch to "ON" position. The LED Light on the Baby's unit should be illuminated.

To Activate Parent's Unit:

For best results, the Parent's Unit should be placed at least 10 feet away from the Baby's unit. The Parent's Unit can be mounted to the wall by using a screw (not included) to hang the unit using the keyhole on the belt clip on the back of the unit.

STEP 1 Remove battery cover and select channel to correspond to the same channel used on Baby's Unit as shown.

(LD of parent's unit w/battery cover removed indicating channel selector)

STEP 2 Place the Parent's Unit at least 10 feet from the Baby's Unit.

STEP 3 To use household power, plug the round end of adapter cord into the jack on the Parent's unit, then plug the the adapter into an electrical outlet. Turn the power switch to "ON" and set at an appropriate volume level to hear baby at all times. The power-on LED Light on the Unit should be illuminated and solid red.

NOTE: The pre-installed rechargeable battery pack in the Parent's Unit will automatically charge when the A/C adapter is in use.

STEP 4 For optional battery power, do not attach AC Adapter. Simply turn the power switch to "ON" and the Parent's Unit will run on battery power.

Note: If you experience a power failure, the Parent's Unit and the Baby's Unit will not automatically switch to battery power. You must disconnect the AC Adapters from the Parent's and the Baby's Unit. You must have have installed (1) 9-Volt battery in the Baby's Unit, and the rechargeable battery pack in the Parent's Unit must have been charged prior to use.

LED SOUND LEVEL LIGHT INDICATORS/LOSS OF SIGNAL INDICATORS

The four (4) RED LEDs at the top of the Parent's Unit light up to display sound levels. These sound level indicators are factory pre-set and are not affected by the volume setting. This feature allows you to view the relative volume level of your baby's sounds. It is most effective when you are in a noisy environment and may not be able to hear your baby's sounds clearly. The louder the sound, the more RED LEDs will light up. These RED LEDs, along with the Speaker, also serve as a loss of signal alarm. When the Parent's unit is too far from the Baby's Unit for monitoring, the LEDs will flash and the Speaker will give off an audible alarm.

Operating Tips

- Make sure that both units are on the same channel. Even though you may hear your baby's sounds, proper use of this system requires that both units must be on the same channel. If the units are on different channels, the signals from the Baby's Unit may be strong enough to be picked up by the Parent's Unit, but these signals are unreliable and may contain substantial static.
- When using the AC Adapters with household electricity, make sure the out-let has power. Some electrical outlets are powered through a wall switch in

the room. If both Units are plugged in and "ON", the Power indicator LEDs should be lit. If this does not take place, try placing the wall switch in the room in another position.

Troubleshooting Your Grow-With-Me Intercom Monitor

Problem	Possible cause	Solution
---------	----------------	----------

Warranty

ONE (1) YEAR LIMITED WARRANTY
Safety 1st... WARRANTY.

If you... © 1999 Safety 1st, inc.

10/99