

1 Copyright	1
2 Getting Started	3
Your Phone at a Glance	3
Keys and Functions	4
Inserting the USIM Card and the Battery	6
Inserting the MicroSD Card	7
Charging the Battery	7
Status Icons	8
3 Text Entry	11
Entering Spanish	11
Entering English	11
Smart English Input Method	11
Traditional English Input Method	11
Entering a Digit	12
4 Contacts	13
Adding a Contact	13
Searching for a Contact	13
5 Voice Services	14
Making a Call	14
Dialing via Keypad	14
Dialing via Contacts	14
Dialing via Call Log	14
Answering a Call	14
6 Direct Connect (DC) and DC Group	16
Making a DC Call	16

Dialing a DC Number	16
Last call notification	17
Making a DC call from Contacts	17
Making a DC call from the Call Log	17
Alert	17
Sending a Alert	18
DC Group	18
Creating a DC Group	18
Making a DC Group Call	18
Adding Members to a DC Call	19
Joining a DC Call After it has Started	19
Sending an Interrupt Request	20
Converting a DC Call to a Voice Call	20
Concurrency	20
Other Operations	22

7 Messaging.....24

SMS & MMS	24
Writing and Sending a Text Message	24
Reading a Message.....	24
Email.....	24
Creating an Email Account.....	24
Creating and Sending an Email.....	25
Receiving an Email	25

8 Media Applications27

Camera	27
Taking a Photo.....	27
Recording a Video	27
Music Player.....	27

Starting the Music Player.....	27
Adding a Playlist	28
Playing music.....	28
Playing a Video	28
Picture Viewer.....	29
FM Radio	29
Switching on the FM Radio	29
Switching off the FM Radio	30
Recorder	30
9 Browser.....	31
Surfing the Internet.....	31
Other Browser Options	31
10 Connectivity	32
Connecting via USB.....	32
Installing PC Suite	32
USB-based Internet Access	33
Bluetooth.....	34
Bluetooth-based Data Transfer	34
Using a Bluetooth Headset.....	34
11 Security.....	36
Enabling/Disabling the Phone Lock	36
PIN and PUK	36
Locking the Keypad.....	36
Unlocking the Keypad	37
12 Warnings and Precautions.....	38

1 Copyright

Copyright © Huawei Technologies Co., Ltd. 2011. All rights reserved.

No part of this document may be reproduced or transmitted in any form or by any means without prior written consent of Huawei Technologies Co., Ltd.

The product described in this manual may include copyrighted software of Huawei Technologies Co., Ltd and possible licensors. Customers shall not in any manner reproduce, distribute, modify, decompile, disassemble, decrypt, extract, reverse engineer, lease, assign, or sublicense the said software, unless such restrictions are prohibited by applicable laws or such actions are approved by respective copyright holders under licenses.

Trademarks and Permissions



HUAWEI, and  are trademarks or registered trademarks of Huawei Technologies Co., Ltd.

Other trademarks, product, service and company names mentioned are the property of their respective owners.

Notice

Some features of the product and its accessories described herein rely on the software installed, capacities and settings of local network, and may not be activated or may be limited by local network operators or network service providers, thus the descriptions herein may not exactly match the product or its accessories you purchase.

Huawei Technologies Co., Ltd reserves the right to change or modify any information or specifications contained in this manual without prior notice or obligation.


Import and Export Regulations

Customers shall comply with all applicable export or import laws and regulations and will obtain all necessary governmental permits and licenses in order to export, re-export or import the product mentioned in this manual including the software and technical data therein.

2 Getting Started

Your Phone at a Glance

For optimal voice or Direct Connect calls and FM radio performance, please use the headset that was included with your phone.



- | | | | |
|---|---------------|---|----------------|
| 1 | Earpiece | 2 | Screen |
| 3 | Confirm key | 4 | Right soft key |
| 5 | End/Power key | 6 | Clear/back key |

7	Camera button	8	Microphone
9	Number key	10	Network
11	Talk/Send key	12	Left soft key
13	Navigation keys	14	Torch
15	Headset jack	16	Volume Control button
17	DC button	18	Charger Interface/Data Cable Connector
19	Speaker	20	Camera

Keys and Functions

Send key	• Make or answer a call. • Access call logs in standby mode.
End key	• Power on or power off the phone. • End or reject a call. • Return to the standby mode. • Turn on or off the phone backlight when user has activated the setting.
Left soft key	Select the option displayed in the lower left corner of the screen.
Right soft key	Select the option displayed in the lower right corner of the screen.


Clear/back key	• Delete a character in editing mode or delete a selected item in an application. • Return to the upper-level menu.
* key	Switch between the general volume mode and the Vibration mode by pressing and holding the key.
# key	Switch between text input methods when editing text.
0 key ... 9 key	• Enter numbers, letters, and symbols. • Call voicemail in standby mode by pressing and holding the 1 key. • Speed-dial phone numbers in standby mode by pressing and holding the desired key 2–9 after a phone number is assigned to the number key.
Confirm key	Confirm a selection.
Navigation key	• Switch between shortcuts when the standby screen is set to widgets mode. • Access the corresponding widgets in standby mode when the standby screen is set to Concise mode.
DC button	Make or answer a DC call.
Camera button	• Launch the camera. • Take a photo after the camera is launched. • Turn on/off the Torch by pressing and holding the button for 4 seconds.

Inserting the USIM Card and the Battery

1




2




4



3



Inserting the MicroSD Card



Charging the Battery

Before charging the battery with the charger, ensure that the battery is installed in your phone. Do not use a damaged battery or charger.

1. Connect the charger to a power outlet.
2. Connect the charger to the charger connector of the phone. The phone begins charging. When the battery icon changes to fully charged, it indicates that your phone is fully charged.
3. When the phone is fully charged, disconnect the charger from the phone and then from the power outlet.

Status Icons

	Signal strength		Roaming
	2G network available		3G network available
	Receiving and sending data on a 2G network		Receiving and sending data on a 3G network
	Call in progress		Missed call
	Call forward		Video call
	Music player playing in the background		No memory for messages
	New text message received		New multimedia message received
	Alarm clock enabled		New voicemail message received
	Bluetooth headset connected		Bluetooth on
	Bluetooth searching		Data receiving via Bluetooth
	Low battery		Data sending via Bluetooth
	Charging		Battery level

	Ring and vibration mode activated		Ring mode activated
	MicroSD card inserted		Silence mode activated
	Speaker on		Speaker off
	GPS turned on		Headset connected
	DC Group call in progress		DC service not available
	DC call roaming		DC call in progress
	Number type (PTT 1)		Number type (PTT 2)
	Missed DC call		Incoming DC call
	Outgoing DC call		Incoming Alert
	Outgoing Alert		Missed Alert
	Missed Invitation		Outgoing Invitation
	Incoming Invitation (in the call log list)		Incoming Invitation (on the PTT call screen)
	Missed DC Group call		Incoming DC Group call
	Outgoing DC Group call		Alert received



Originator in a DC
Group call



To add a member to
an ongoing call

3 Text Entry

Entering Spanish

You can enter Spanish words using Spanish text input methods. The traditional Spanish input method and the smart Spanish input method are similar to the traditional English input method and the smart English input method. For details, see "Entering English".

Entering English

Smart English Input Method

1. Based on the sequence of the word, press the key labeled with the desired letter once. Then the phone predicts the commonly used words according to the numeric sequence of key presses.
2. Select the desired word, and press **Confirm key** or **0 key** to enter the word.
3. Press **1 key** to enter a full stop or another commonly used punctuation. Press *** key** to display the symbol list. Then you can select and enter a symbol.



NOTE

The indicator of the current input method is displayed in the upper right corner of the screen. You can press **# key** to change the input method.

Traditional English Input Method

The traditional text input method allows you to enter uppercase or lowercase English letters. You can press the key labeled with

the desired letter once to enter the first letter on the key, twice to enter the second letter on the key, and so on.

- Press **1 key** to enter a full stop or another commonly used punctuation.
- Press **0 key** once to enter a space, twice to enter a carriage return, and three times to enter 0.

Entering a Digit

- In "123" input mode, press the key labeled with your desired digit.
- In "Abc" input mode, press a number key consecutively until the digit appears.
- In "En" input mode, press a number key and then press **Navigation keys** to scroll to the digit and press **Confirm key** to enter it.
- In any text input mode, except the "123" input mode, press and hold a number key to enter the digit.

4 Contacts

Adding a Contact

1. Select **Menu > Contacts > Create new**, you can choose **Create contact** or **Create DC Group**.
2. On the Edit screen, enter the information about the contact.
For each contact, at least one number needs to be entered.
3. Select **Save** to save the contact.

Searching for a Contact

1. Select **Menu > Contacts**.
2. Enter the name of the contact in the text box. The contacts that comply with the search information you entered will be displayed.

5 Voice Services

Making a Call

Dialing via Keypad

1. In standby mode, enter the phone number.
 - To make an international call, press *** key** twice consecutively to enter the international long-distance code (+), and then enter the country code or region code, area code, and phone number in sequence.
 - To dial an extension number, enter the phone number, press *** key** three times consecutively to insert P or press *** key** four times consecutively to insert W, and then enter the extension number.
2. Press **Send key** to dial the number.
3. Press **End key** or select **End** to end the call.

Dialing via Contacts

Select **Menu > Contacts**, select a contact, and press **Send key** to make a call.

Dialing via Call Log

Select **Menu > Call log** or press **Send key** to select the desired number from the call log. Then press **Send key** to dial the number.

Answering a Call

When there is an incoming call, you can press **Send key** to answer it, press **End key** to reject it.

- If the Any Key answer function is enabled, you can press any key except **End key**, **Clear/back key** and **Right soft key** to answer an incoming call.
- If the Headset auto-answer function is enabled, when the headset is connected to the phone, the incoming call is answered automatically.

6 Direct Connect (DC) and DC Group

With DC, you can instantly talk to another DC user or group of users with the push of a button.



NOTE

You can select **Menu > Settings > Call > DC settings** set the DC button and DC-related functions.

Making a DC Call

You can make a DC call using one of the following methods:

Dialing a DC Number

A DC number has three parts. When you enter a DC number, you must separate all the three parts with an asterisk. A DC number contains a maximum of 15 characters (including asterisks), and the number of digits in each part of a DC number may vary; for example, 000*00000*00000 and 99*99999*999999. You must have all 3 parts when calling iDEN or 3G users.

1. In standby mode, enter a DC number directly by using the number pad.
2. Push and hold the **DC button** on the left side of your phone. Then speak after you hear the Chrip sound.
3. When you finish speaking, release the DC button to listen. The call will end automatically if no party speaks for several seconds.



NOTE

When no party is speaking during an active call, the phone displays Open and any party can push and hold the DC button to talk when the phone displays Speak, when you are speaking do not release the DC button until you finish speaking. When another party is speaking, the phone displays Listen. You can hear the other party talking at this moment.

Last call notification

Upon completion of a DC call or a DC Group call, the Last Call Notification screen will appear. It shows the contact name or number on the last call, and the date and time of the call. The screen can be cleared by pressing the indicated soft key, or it will disappear after a period of time. Pushing the **DC button** from the last call screen will attempt a restart of the last call indicated.

Making a DC call from Contacts

Select **Menu > Contacts**. Select a contact with a DC number, and push the **DC button** to start a DC call.

Making a DC call from the Call Log

Select **Menu > Call log** or press the **Send key** to select the desired number from the **DC calls** log. Then push the **DC button** to start the DC call.

Alternatively, if you have selected **Menu > Settings > Call > DC settings > DC button function > Call log**, push the **DC button** to select the required number from **Call log** and then push and hold the **DC button** to start the DC call.

Alert

Alerts enable you to notify someone that you want to communicate with them using DC. When the other party

receives an Alert, the phone of the other party receives an Alert tone and displays your name or DC number on their screen.

Sending a Alert

1. In standby mode, select **Contacts** or **Call log > DC calls**. Then select a contact or a **DC** number.
2. Press the right soft key select **Alert**. Push the **DC button** as prompted to send an Alert.

DC Group

Creating a DC Group

You can create a DC Group using one of the following methods:

- When you have selected **Menu > Settings > Call > DC settings > One touch DC > Call log** or **Contacts**, push the **DC** button and then select contacts from **Contacts** or **Call log**, or enter several DC numbers on the **Enter number** screen to create a DC Group.
- Select **Menu > Contacts**. Select **Create New > Create DC Group** or press the left soft key to select **Options > Create DC Group** to create a DC Group.
- In standby mode, press **Send key** or select **Menu > Call log** to access the call log. Press the left soft key to select **Options > Create DC Group** to create a DC Group.

If you want to delete a member from a DC Group, select **Contacts > Open DC Group**. Then highlight a member and press the left soft key to select **Options > Remove contact**. Select **Yes** to confirm your operation.

Making a DC Group Call

A DC Group call includes multiple DC users at the same time. Operations during a DC Group call are similar to those during a DC call.



NOTE

DC Group calls with iDEN users are not possible.

1. Select a group from **Contacts** or **Call log**, or select multiple contacts from the contact list to create a temporary DC Group. You can also enter the DC numbers to create a DC Group.
2. Push the **DC button** to start the DC Group call directly, or press the left soft key to select **Invite** and push the DC button to send an invitation to all group members. When the group members receive the invitation, they can select **Join** to join the call or select **Reject** to reject the invitation.



NOTE

- A DC Group can contain a maximum of 25 members.
- During a DC Group call, you can view the participant status of group members, access **Contacts** and **Messages**, add a member to the call, or write a memo.

Adding Members to a DC Call

During a DC call do the following to add members to the call: Select **Option > Add Member** to select members from **Contacts** or **Call log**, or directly enter DC numbers on the **Enter number** screen. Then press the left soft key to select **Done**. An invitation will be sent to the desired members.

Joining a DC Call After it has Started

If a DC Group call has ended when you receive the invitation, after you select **Join** by pressing the left soft key, the phone displays "The call is not running. Restart the call?".

- If you select **Yes**, the phone displays "Push DC button to start call". Then you can push and hold the DC button to make a DC group call to the Group.
- If you select **No**, no operation will be performed.

Sending an Interrupt Request

During a DC call or a DC Group call, when another party is speaking, you can do the following to make a speak request: Press the left soft key to select **Options > Request to speak**. Then the speaker's phone displays **xxxx Request to speak**. After the speaker releases the DC button, you can push and hold the DC button to talk.

Converting a DC Call to a Voice Call

The phone supports the switch between a DC call and a voice call.

During a DC call, if you have saved the voice call number of the other party on the phone, to convert the DC call to a voice call, press **Send key** and then select **Yes** when the phone displays "Convert to voice call?"

Concurrency

Receiving a Voice Call During a DC Call

When you receive a voice call during a DC call, the phone displays the incoming DC call icon. At this moment, press the right soft key to select **Reject**; press the confirm key to select **Accept**; press the left soft key to select **Option** and then **Accept** or **Reject**.

Receiving a DC Call During a Voice Call

When you receive a DC call during a voice call, the phone displays "Missed DC call From: xxxxxxxx." At this moment, press the right soft key to select **Ignore** and continue with the voice call; press the left soft key to select **Hold** and the phone will

display "Push DC button to call xxxxxxxx." Then you can do the following:

- Press the right soft key to select **Cancel**. Then press the Send key to return to the voice call screen.
- Press the left soft key to select **Alert**. An alert will be sent to the other party.
- Push and hold the DC button to make a DC call.

Receiving a DC Group Call During a Voice Call

When you receive a DC Group call during a voice call, the phone displays "Missed DC Group call From: xxxxxxxx." At this moment, press the right soft key to select **Ignore** and continue with the voice call; press the left soft key to select **Hold** and the phone will display "Push DC button to call xxxxxxxx." Then you can do the following:

- Press the right soft key to select **Cancel**. Then press the Send key to return to the voice call screen.
- Press the left soft key to select **Invite**. An invitation will be sent to the group members.
- Push and hold the DC button to make a DC call to the group call initiator.

Receiving an Alert During a Voice Call

When you receive an Alert during a voice call, the phone displays "Incoming Alert From: xxxxxxxx." At this moment, press the right soft key to select **Ignore** and continue with the voice call; press the left soft key to select **Hold** and the phone will display "Push DC button to call xxxxxxxx." Then you can do the following:

- Press the right soft key to select **Cancel**. Then press the Send key to return to the voice call screen.
- Press the left soft key to select **Alert**. An alert will be sent.

- Push and hold the DC button to make a DC call to the group call initiator.

Receiving an Invitation During a Voice Call

When you receive a DC Group invitation during a voice call, the phone displays "Incoming invitation." At this moment, press the right soft key to select **Ignore** and continue with the voice call; press the left soft key to select **Hold** and the phone will ask "Join the DC Group call?". Then you can do the following:

- Press the right soft key to select **No**. Then press the Send key to return to the voice call screen.
- Press the left soft key to select **Yes**. Then you can join the DC Group call.

Other Operations

DC Button function

- Contacts: Allows you to quickly access Direct Connect contacts when the Direct Connect button is pushed from idle.
- Off: Turn off DC button operation from idle.
- Call log: Access the call log to start a Direct Connect call.
- Last call: Start a Direct Connect call with the most recent DC caller in the call log.
- Contacts list: Access the list of DC Contacts stored on your phone.

Exiting a DC Group Call I initiated

Select one of the following settings to allow the call to continue when you exit a DC Group call you initiated.

- Allow call to continue.
- End call for everyone.

Add Member to ongoing call

Select one of the following to allow a member to add a contact to a Direct Connect or DC Group Call you initiated.

- Allow call to continue.
- End call for everyone.

Save unknown number

Select whether you want your phone to prompt you to save Direct Connect callers to your Contact list if you do not have them previously stored.

My DC Number

Displays your Direct Connect number.

Blocked user

View and modify the list of users you have blocked from making a Direct Connect call to you.

Alert Timeout

Set the length of time you want the Alert ringtone to repeat.

Invitation Timeout

Set the length of time you want the Invitation ringtone to repeat.

DC Button backlight

Select whether you want to turn on the Direct Connect button light on incoming DC events.

7 Messaging

SMS & MMS

Writing and Sending a Text Message

1. Select **Menu > Messages > Create message**.
2. Enter one or more recipient's numbers directly, or press **Confirm key** to access the contact list and then select one or multiple recipients.
3. Enter text contents in the text box. You can press **Confirm key** to add a picture, video, audio or slide to the message, and the message will be converted to MMS mode automatically.
4. Select **Options > Send** to send the message.



NOTE

Your phone supports a multimedia message of a maximum size of 600 KB.

Reading a Message

To read a text message stored in the inbox, do the following:

1. Select **Menu > Messages > Inbox**.
2. Press **Navigation keys** to scroll to a message. Press **Confirm key** to read the message.

Email

Creating an Email Account

Before sending or receiving emails, you need to create an email account. When you open the Email application for the first time, create an email account according the on-screen instructions:

1. Select **Menu > Email**, and then select **OK** to start creating an email account.
2. In the email server list, select the desired server.
3. On the Setup wizard screens, enter the information of your email account.
4. Select **Done**. The email account is created and the account name is displayed in the Email menu.
5. When you want to create another email account, select **Email > Settings > Account management > Create account**.
6. When you want to remove an email account, select **Email > Settings > Account management**, highlight the account you wish to remove, and select **Delete**.



NOTE

The preset server configures server parameters automatically. You need to enter the correct email address, user name, and password only.

Creating and Sending an Email

1. Select **Email**, and then select an account.
2. Select **Create** to create an email.
3. Enter the recipient's email address, subject, and contents in the corresponding text box.
4. In the email editing screen, select **Options > Send** to send the email.

Receiving an Email

1. Select **Menu > Email > Get new emails**.
2. In the email inbox select **Options**, and then select **Download**. Only the email heading (the sender, theme, and sending time) is received by default. You can select **Download** to download the email contents. You can also download the email

contents by pressing **Confirm key** to open the email and press **Confirm key** to download the contents.



NOTE

To change the download mode, select an email account, and then select **Account settings > Download settings**.

8 Media Applications

Camera

Taking a Photo

1. Select **Menu** > **Camera** or press the camera button to enter the camera interface.
2. In the viewfinder screen, select **Options** for the camera settings.
3. Focus the camera on the scene. Press **Confirm key** or Camera button to take a photo.
4. Your photo is automatically saved to the album of the default storage that you select.

Recording a Video

1. Select **Menu** > **Camera** > **Options** > **Shooting mode** to switch to the video camera.
2. In the viewfinder screen, select **Options** for the camera settings.
3. Press **Confirm key** or camera button to start recording. Select **Pause/Continue** to pause or continue. Select **Stop** to stop recording. The video is automatically saved to the Videos folder of the storage that you select.

Music Player

Starting the Music Player

To start the music player, you can select **Menu** > **Multimedia** > **Music player**.

Adding a Playlist

1. Select **Menu > Multimedia > Music player**.
2. Select **Options > Media library > Playlist**.
3. Select **Options > Create** to create a new playlist. Open the playlist and select **Add** to add songs to the playlist.



NOTE

You can also select **Menu > File Mgmt** to select music to play.

Playing music

When the music is playing, you can do the following:

- Press **Confirm key** to pause the song; press it again to continue playing.
- Press **Right navigation key** to play the next song. Press and hold **Right navigation key** to fast-forward the song.
- Press **Left navigation key** to play the previous song. Press and hold **Left navigation key** to rewind the song.
- Press **Up navigation key** to access the current playlist.
- Press **Down navigation key** to access the media library.
- Press **Volume key** to increase or decrease the volume.
- Select **Options > Exit** or the End key to exit the media player.



NOTE

When a song is played, you can select **Minimize** to minimize the media player screen. In this case, the media player is running in the background.

Playing a Video

1. In standby mode, select **Menu > Multimedia > Video player**.
2. Select **Options**, and then select **All videos** or **playlist** to access a video list.

3. Press **Navigation keys** to scroll to the video to be played. Then press **Confirm key** to play the video.



NOTE

After you select **All videos**, the phone automatically lists all videos stored on the phone.

Picture Viewer

1. Select **Menu > Pictures**.
2. Press **Navigation keys** to scroll to a picture and then press **Confirm key** to view the picture in Full-screen mode. Select **Options** for the following options:
 - **Send**: to send a picture via messaging, Bluetooth, or email.
 - **Set as**: to set a picture as the wallpaper or a contact image.
 - **Delete**: to delete a picture.
 - **Rotate**: to rotate the picture clockwise or counterclockwise.
 - **Zoom in**: to zoom in the picture.
 - **Play**: to play all pictures in full-screen mode.

FM Radio



NOTE

To use the FM radio, you need to insert the headset since it serves as the antenna for the radio.

When you use the FM radio for the first time, select **Options** and then select **Automatic tuning**, **Manual tuning**, **Precise tuning**, or **Set frequency** to search for channels.

Switching on the FM Radio

1. Select **Menu > Multimedia > FM radio** to access the FM radio.
2. On the FM screen, you can do the following:

- Press **Confirm key** to switch between the headset and the loudspeaker.
- Press **Navigation keys** to adjust the frequency or switch between the channels saved in the channel list.
- Press **Volume key** to adjust the volume.
- Select **Minimize** to minimize the radio screen, and listen to radio programs played in the background.

Switching off the FM Radio

To switch off the FM radio, select **Options > Exit**, or press the End key.

Recorder

1. In standby mode, select **Menu > Multimedia > Recorder**.
2. Press **Confirm key** to start recording. Select **Pause/Continue** to pause or continue.
3. Select **Stop** to stop recording. The sound clip is automatically saved to the Recordings folder of the default storage that you select.
4. Press **Confirm key** to play the sound clip.



NOTE

When recording a sound clip, keep the microphone of your phone near the sound source for a better recording effect.

9 Browser

Surfing the Internet

1. To open the **Opera Mobile** browser, select **Menu > Browser**, or in standby mode, press the left or right navigation key to select **Browser**.
2. Nextel's homepage will be displayed as the default webpage.
3. Press the navigation keys to move the pointer on the screen. When a link is highlighted, you can press the OK key to open the link.
4. If you want to browse other web pages, press the left soft key and select **Menu**. Press the up navigation key to highlight the address bar. Press the OK key and select **Edit** to enter a Web address in the address bar. Press the left soft key and select **GO** to browse the webpage.

Other Browser Options

After you open the browser, press the left soft key to select **Menu** and then press the down navigation key for the following options:

- **Bookmarks**: to add, delete or edit bookmarks.
- **History**: to access your website history.
- **Saved Pages**: to view the web pages you have saved.
- **Settings**: to set the browser properties.
- **Downloads**: to view the download progress.


10 Connectivity

Connecting via USB

Installing PC Suite

The PC Suite software supplied with your phone runs automatically after you connect your phone to the PC with the USB cable. To install the PC Suite software, perform the following operations:

1. Connect your phone and PC with the USB cable.
2. Double-click My Computer. Find the disk named HUAWEI ASSITANT and double-click it. Wait for the dialog box to appear on your PC.



3. If it does not automatically appear, open **My Computer** and find the drive for the phone (appears as a CD drive). Double-click on Setup.exe to run the install program. The drivers will be installed. If you do not automatically see the popup, double-click on Setup.exe again.
4. Select **Start PC Suite** to finish installing the PC Suite software
5. Follow the wizard to complete the installation.
6. When the installation is complete, PC Suite will start automatically. After your phone is detected, you can manage

your contacts, files, calendar, synchronize emails, and send SMS from PC Suite.



NOTE


- To download the general edition of the PC Suite, go to Huawei Device website: <http://www.huaweidevice.com> and choose **Service Center** > **Software** to find the software.
- For the method of transferring files using the PC Suite, refer to the help document contained in the software.

USB-based Internet Access

Connecting your phone to the PC with the USB cable enables the PC to use the phone as a modem and allows a connection to the Internet.

Only Windows 2000, 32-bit and 64-bit versions of Windows Vista, Windows XP and Windows 7 are supported.

1. Connect your phone and PC with the USB cable.
2. Double-click My Computer. Find the disk named HUAWEI ASSITANT and double-click it. Wait for the dialog box to appear on your PC.



3. Select **Start Mobile Modem**. Follow the wizard to complete installation.
4. After installation, click **Connect** on the displayed dialog box to set up a connection and access the Internet.



NOTE

For details, contact your service provider.

Bluetooth

Bluetooth-based Data Transfer

You can exchange data between your Bluetooth phone and other Bluetooth devices. If you want to exchange data between your phone and another device, that device must support Bluetooth and the Bluetooth function must be enabled.

1. Select **Menu > Settings > Connectivity Bluetooth** to enable the Bluetooth function.
2. Select **Search for devices** to search a Bluetooth device, select a Bluetooth device that you want to connect with from the device list. If the other Bluetooth device requires verification before connection, your phone displays "Enter password" on the screen. Then create a password that is to be used together with the other device. After the password has been entered in both devices, the Bluetooth connection can be set up.
3. After the connection is set up, you can exchange data between your phone and the other Bluetooth device.

Using a Bluetooth Headset

For more information, refer to the user manuals of the relevant devices.

1. Open/turn on the Bluetooth headset and keep it in the discoverable state.
2. Select **Menu > Settings > Connectivity > Bluetooth** to enable the Bluetooth function.
3. Select **Search for devices** to search for a Bluetooth device, select a Bluetooth device that you want to connect with from

the device list. If the other Bluetooth device requires verification before connection, your phone displays "Enter password" on the screen. Then create a password that is to be used together with the other device. After the password has been entered in both devices, the Bluetooth connection can be set up.

4. After the connection is set up, you can use the Bluetooth headset.

11 Security

Enabling/Disabling the Phone Lock

The phone lock protects your phone from unauthorized use. The phone lock function is not enabled when you purchase the phone. You can change the default phone lock code 000000 to any string of 1 to 8 digits.

1. Select **Menu > Settings > Security > Phone lock**.
2. Press **Navigation keys** to select one of the following options:
 - **On:** The phone lock will be enabled when the phone is powered on next time.
 - **Off:** The phone lock will be disabled.

PIN and PUK

The personal identification number (PIN) protects your USIM card from unauthorized use. The PIN unblocking key (PUK) can unlock the blocked PIN. For details, contact your service provider.

If you enter wrong PINs 3 times consecutively, the phone asks you to enter the PUK.

If you enter wrong PUKs 10 times consecutively, the USIM card is invalidated permanently. Contact your service provider for a new one.

Locking the Keypad

When the keypad is locked, you can still answer incoming calls and make emergency calls by pressing the **Send key**.

To lock the keypad, do the following:

- In standby mode, press **# key** to lock the keypad.
- After you select **Menu > Settings > Phone > Auto keypad lock > On**, the keypad is automatically locked after the phone is idle for 3 seconds.

Unlocking the Keypad

In standby mode , Press the **left soft key** and then **right soft key** to unlock the keypad.

12 Warnings and Precautions

This section contains important information pertaining to the operating instructions of your device. It also contains information about how to use the device safely. Read this information carefully before using your device.

Electronic Device

Power off your device if using the device is prohibited. Do not use the device when using the device causes danger or interference with electronic devices.

Medical Device

- Follow rules and regulations set forth by hospitals and health care facilities. Do not use your device when using the device is prohibited.
- Pacemaker manufacturers recommend that a minimum distance of 15 cm be maintained between a device and a pacemaker to prevent potential interference with the pacemaker. If you are using a pacemaker, use the device on the opposite side of the pacemaker and do not carry the device in your front pocket.

Potentially Explosive Atmosphere

Power off your device in any area with a potentially explosive atmosphere, and comply with all signs and instructions. Areas that may have potentially explosive atmospheres include the areas where you would normally be advised to turn off your vehicle engine. Triggering of sparks in such areas could cause an explosion or a fire, resulting in bodily injuries or even deaths. Do

not power on your device at refueling points such as service stations. Comply with restrictions on the use of radio equipment in fuel depots, storage, and distribution areas, and chemical plants. In addition, adhere to restrictions in areas where blasting operations are in progress. Before using the device, watch out for areas that have potentially explosive atmospheres that are often, but not always, clearly marked. Such locations include areas below the deck on boats, chemical transfer or storage facilities, and areas where the air contains chemicals or particles such as grain, dust, or metal powders. Ask the manufacturers of vehicles using liquefied petroleum gas (such as propane or butane) whether this device can be safely used in their vicinity.

Traffic Security

Observe local laws and regulations while using the device. In addition, if using the device while driving a vehicle, comply with the following guidelines:

- Concentrate on driving. Your first responsibility is to drive safely.
- Do not talk on the device while driving. Use hands-free accessories.
- When you have to make or answer a call, park the vehicle at the roadside before using your device.
- RF signals may affect electronic systems of motor vehicles. For more information, consult the vehicle manufacturer.
- In a motor vehicle, do not place the device over the air bag or in the air bag deployment area. Otherwise, the device may hurt you due to the strong force when the air bag inflates.
- Do not use your device while flying in an aircraft. Power off your device before boarding an aircraft. Using wireless devices in an aircraft may cause danger to the operation of the

aircraft and disrupt the wireless telephone network. It may also be considered illegal.

Operating Environment

- Do not use or charge the device in dusty, damp, and dirty places or places with magnetic fields. Otherwise, it may result in a malfunction of the circuit.
- The device complies with the RF specifications when the device is used near your ear or at a distance of 1.5 cm from your body. Ensure that the device accessories such as a device case and a device holster are not composed of metal components. Keep your device 1.5 cm away from your body to meet the requirement earlier mentioned.
- On a stormy day with thunder, do not use your device when it is being charged, to prevent any danger caused by lightning.
- While using the device, observe the local laws and regulations, and respect others' privacy and legal rights.
- Keep the ambient temperature between 0°C and 40°C while the device is being charged. Keep the ambient temperature between 0°C to 40°C for using the device powered by a battery.

Prevention of Hearing Damage

Using a headset at high volume can damage your hearing. To reduce the risk of damage to hearing, lower the headset volume to a safe and comfortable level.

Safety of Children

Comply with all precautions with regard to children's safety. Letting the child play with your device or its accessories, which may include parts that can be detached from the device, may be

dangerous, as it may present a choking hazard. Ensure that small children are kept away from the device and accessories.

Accessories

Use the accessories delivered only by the manufacturer. Using accessories of other manufacturers or vendors with this device model may invalidate any approval or warranty applicable to the device, result in the non-operation of the device, and cause danger.

Battery and Charger

- Unplug the charger from the electrical plug and the device when not in use.
- The battery can be charged and discharged hundreds of times before it eventually wears out. When the standby time and the talk time are shorter than the normal time, replace the battery.
- Use the AC power supply defined in the specifications of the charger. An improper power voltage may cause a fire or a malfunction of the charger.
- Do not connect two poles of the battery with conductors, such as metal materials, keys, or jewelry. Otherwise, the battery may be short-circuited and may cause injuries and burns on your body.
- Do not disassemble the battery or solder the battery poles. Otherwise, it may lead to electrolyte leakage, overheating, fire, or explosion.
- If battery electrolyte leaks out, ensure that the electrolyte does not touch your skin and eyes. If the electrolyte touches your skin or splashes into your eyes, wash your eyes with clean water immediately and consult a doctor.

- If there is a case of battery deformation, color change, or abnormal heating while you charge or store the battery, remove the battery immediately and stop using it. Otherwise, it may lead to battery leakage, overheating, explosion, or fire.
- If the power cable is damaged (for example, the cord is exposed or broken), or the plug loosens, stop using the cable at once. Otherwise, it may lead to an electric shock, a short circuit of the charger, or a fire.
- Do not dispose of batteries in fire as they may explode. Batteries may also explode if damaged.

Cleaning and Maintenance

- The device, battery, and charger are not water-resistant. Keep them dry. Protect the device, battery, and charger from water or vapor. Do not touch the device or the charger with a wet hand. Otherwise, it may lead to a short circuit, a malfunction of the device, and an electric shock to the user.
- Do not place your device, battery, and charger in places where they can get damaged because of collision. Otherwise, it may lead to battery leakage, device malfunction, overheating, fire, or explosion.
- Do not place magnetic storage media such as magnetic cards and floppy disks near the device. Radiation from the device may erase the information stored on them.
- Do not leave your device, battery, and charger in a place with an extreme high or low temperature. Otherwise, they may not function properly and may lead to a fire or an explosion. When the temperature is lower than 0°C, performance of the battery is affected.

- Do not place sharp metal objects such as pins near the earpiece. The earpiece may attract these objects and hurt you when you are using the device.
- Before you clean or maintain the device, power off the device and disconnect it from the charger.
- Do not use any chemical detergent, powder, or other chemical agents (such as alcohol and benzene) to clean the device and the charger. Otherwise, parts of the device may be damaged or a fire can be caused. You can clean the device and the charger with a piece of damp and soft antistatic cloth.
- Do not dismantle the device or accessories. Otherwise, the warranty on the device and accessories is invalid and the manufacturer is not liable to pay for the damage.

Emergency Call

You can use your device for emergency calls in the service area. The connection, however, cannot be guaranteed in all conditions. You should not rely solely on the device for essential communications.

Certification Information (SAR)

This mobile device meets guidelines for exposure to radio waves. Your device is a low-power radio transmitter and receiver. As recommended by international guidelines, the device is designed not to exceed the limits for exposure to radio waves. These guidelines were developed by the independent scientific organization International Commission on Non-Ionizing Radiation Protection (ICNIRP) and include safety measures designed to ensure safety for all users, regardless of age and health.

The Specific Absorption Rate (SAR) is the unit of measurement for the amount of radio frequency energy absorbed by the body

when using a device. The SAR value is determined at the highest certified power level in laboratory conditions, but the actual SAR level of the device when being operated can be well below the value. This is because the device is designed to use the minimum power required to reach the network.

The SAR limit adopted by USA and Canada is 1.6 watts/kilogram (W/kg) averaged over one gram of tissue. The highest SAR value reported to the FCC and IC for this device type when tested for use at the ear is 1.190 W/kg, and when properly worn on the body is 1.160 W/kg.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.



CAUTION

Changes or modifications made to this device not expressly approved by Huawei Technologies Co., Ltd. may void the FCC authorization to operate this device.
