

# Power 7 WIFISD With Power Bank (Pontoon) Datasheet



## Table of Content

|                                                   |    |
|---------------------------------------------------|----|
| Introduction .....                                | 2  |
| Target Users/Markets .....                        | 2  |
| Features .....                                    | 3  |
| Applications .....                                | 4  |
| Hardware Specifications .....                     | 5  |
| Interface Illustration .....                      | 7  |
| Software Specifications .....                     | 7  |
| File & System Manager App .....                   | 9  |
| System Requirements .....                         | 9  |
| Client Tools .....                                | 9  |
| Pontoon Unifies Your Family with Recreation ..... | 10 |

Version 0.1

Last Updated: August 20, 2013

Author: Power 7 PM Department

## Introduction

Power 7 WIFISD With Power Bank (Project Name: Pontoon) is a portable wireless storage device with one Micro SD slot and one USB 2.0 host. Pontoon allows you to convert any SD memory card and USB external storage devices into a WiFi accessible media. Simply insert your SD memory card into the SD slot or connect your USB external storage into the built-in USB port. Switch the unit on and you can now wirelessly access your videos, music, photos, data and stream it to your iPad®, iPhone®, tablets, smartphones, and notebooks. There is no need to worry about running out of space on your mobile devices. For maximum portability, Pontoon has a built-in rechargeable battery. Simply plug it into any available USB port on your computer to charge. As simple as 1-2-3, you are ready to enjoy your device and no waiting needed. With the SD or External USB connected, the portable WiFi SD/USB can be accessed while the battery is charging. Without the wired limitation, you can enjoy listening to music while travelling with Pontoon in your backpack, share photo with your family by placing it at any house corner or lay back watching movies in the beach – with a range of up to 150ft you'll never feel tethered to your Pontoon. Best of all, the Pontoon can bridge the Internet connection to your existing wireless router, so you may access the data in the storage while surfing the Internet simultaneously.



All product pictures are for reference only

## Target Users/Markets

- **Mobile Device User**

iPhone®, iPad®, smartphone, tablet or notebook user may unleash from very limited storage capacity by throwing large files such as movies, music or PowerPoint files to Pontoon.

---

- **Frequent Business Traveler**

Businessman may show customer the product datasheet, contract or quotation in Pontoon anytime in the coffee shop, meeting room or hotel.

- **Movies & Music Download Mania**

Have already downloaded hundreds or thousands of movies, music by BitTorrent at home but you can not enjoy watching or listening to them while you are outside? Pontoon is the solution for you.

- **Salesman**

Pontoon may save mobile sales person like insurance broker, realty broker from carrying bulky brochure or flyers.

- **Legacy USB External HDD Device Hater**

Just can not stand anymore to be tethered by USB cable whenever you need to transfer files between your notebook and external HDD? Pontoon is the answer for you!

- **Small Enterprise Mobile NAS**

The critical and confidential business data should not be bound to the file server or NAS in your company. Pontoon allows you to have a backup of your important data which is portable with you.

- **Home Mobile NAS**

With Pontoon at home, you do not need to always turn on your notebook or PC in order to share data with your family. Moreover, Pontoon can be your portable entertainment center while your family go out for vacation.

## Features

- **File and System Manager App**

Two way file transferring between Pontoon and your iPhone®, iPad®, smartphone, tablet or computer with Wi-Fi connectivity (802.11 b/g/n). Available iOS and Android mobile app with search utility function to find and locate specific data file.

- **Bridge to Internet Access**

Bypass your Internet access to your existing Wi-Fi router, so you may access any data in the SD or USB Storage while surfing the Internet simultaneously.

- **WiFi SD or USB external HDD Accessible while Charging**

Using notebooks with available USB port or optional AC adaptor, the WiFi SD or USB Storage can be accessed while charging the internal battery.

- **Share with Friends & Family**

Allow 5 maximum concurrent connections for sharing videos, audios, photos and data.

- **Extended Battery Life**

Up to 10 hours of continuous use battery life for maximum portability.

- **USB 2.0 Host for Data Sync and Battery Charging**

USB 2.0 port for faster transfer between Micro SD and PC.


- **Easy to Configure and Operate**

Friendly user interface design with wizard guide to assure even the novice can get Pontoon start to operate in minutes.

## Applications

- **Bridge to Internet Access**

**Scenario 1 - If you got an existing wired router for Internet access**



**Scenario 1 - If you got an existing WiFi router for Internet access**



- **Connect to the USB Port**

**Scenario 1 - Press power switch button off and then connect to the USB port of notebook, Pontoon works solely as an Micro SD reader with power charge to extend usage time**



**Scenario 2 - Press power switch button on and then connect to USB port of notebook, Pontoon works solely as a WiFi SD or USB external HDD/Flash with power charge to extend usage time**



## Hardware Specifications


|              |                      |                                                                                                   |
|--------------|----------------------|---------------------------------------------------------------------------------------------------|
| Project name | Pontoon              |                                                                                                   |
| Model name   | PON-WIFI-D11U-C26-WG |                                                                                                   |
| CPU          | Model Ralin          | k RT5350                                                                                          |
|              | Frequency MIPS24KEc  | 360MHZ                                                                                            |
| Flash        | Model EN25Q          | 64-104WIP                                                                                         |
|              | Capacity 8MByte      | SPI flash                                                                                         |
| SDRAM        | Model M12L2          | 561616A-6TG (SDRAM)                                                                               |
|              | Capacity 32MB        | (256Mbit)                                                                                         |
| WiFi         | standard 802.1       | 1 b/g/n                                                                                           |
|              | Frequency 2.4GHz     |                                                                                                   |
|              | Speed                | 72Mbps for 20MHz<br>150Mbps for 40MHz                                                             |
| Interface    | Battery              | LED light to show the battery status right after power on:<br>Green: $\geq 30\%$<br>Red: $< 30\%$ |
|              | LED (Green&Red)      | Red LED fast flash: $< 10\%$ depleting                                                            |



|                            |                                                                                                                                                                                                                                                     |                                                                                                                                                                             |
|----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                            |                                                                                                                                                                                                                                                     | Green LED slow flash:<br>Every 2 seconds for charging<br>Every 1.5 seconds for shutting down                                                                                |
|                            | WiFi LED (Blue)                                                                                                                                                                                                                                     | WiFi LED shows the system initiating state:<br>Start flashing: Kernel loading in process<br>Stop flashing: System initiation completes<br>Fast blinking: Reading or writing |
|                            | Internet LED (Green)                                                                                                                                                                                                                                | Internet LED state:<br>Extinguishing: No connection<br>Flashing: Connecting underway<br>Solid green: Connecting successfully                                                |
|                            | Micro SD card slot                                                                                                                                                                                                                                  | Support micro SD/SDHC,SDXC upto 2TB                                                                                                                                         |
|                            | Power button                                                                                                                                                                                                                                        | Power on/off switch button                                                                                                                                                  |
|                            | Reset button                                                                                                                                                                                                                                        | Factory default reset button                                                                                                                                                |
|                            | WAN port                                                                                                                                                                                                                                            | RJ45 100Mbit/s                                                                                                                                                              |
|                            | USB device interface                                                                                                                                                                                                                                | Micro USB 2.0                                                                                                                                                               |
|                            | USB host interface                                                                                                                                                                                                                                  | USB 2.0:<br>Support USB flash/HDD<br>Support 1.0A output current charging for iPhone®, smartphone.                                                                          |
| Antenna                    | Signal strength                                                                                                                                                                                                                                     | 2.5dBi (WiFi component)<br>17dBm (Main chip)                                                                                                                                |
| Battery                    | Capacity                                                                                                                                                                                                                                            | 2600mAh Li-ion Polymer battery                                                                                                                                              |
|                            | Charging current                                                                                                                                                                                                                                    | Max 1.6A                                                                                                                                                                    |
| Power dissipation          | Max power dissipation (tested with Micro SD read/write without USB storage activity)<br>* It will vary slightly with different type of Micro SD                                                                                                     | 2W                                                                                                                                                                          |
|                            | Standby power (tested with TOSHIBA 1TB HDD,H DD slept during the test)                                                                                                                                                                              | 1.5W                                                                                                                                                                        |
| Environmental requirements | <ul style="list-style-type: none"><li>Operating Temperature: 5°C to 35°C</li><li>Non-Operating Temperature: 0°C to 60°C</li><li>Operating Humidity: 5% to 90% (Non-condensing)</li><li>Non-operating Humidity: 5% ~ 90 % (Non-condensing)</li></ul> |                                                                                                                                                                             |
| Product dimension          | 73mm L x 53mm W x 23mm H                                                                                                                                                                                                                            |                                                                                                                                                                             |

|                                                     |                                                                               |
|-----------------------------------------------------|-------------------------------------------------------------------------------|
| Emission (EMI),<br>Safety & Other<br>Certifications | <ul style="list-style-type: none"> <li>• FCC Class B</li> <li>• CE</li> </ul> |
|-----------------------------------------------------|-------------------------------------------------------------------------------|

## Interface Illustration



Pontoon Interface Illustration

## Software Specifications

|                |                                 |                                                                                                                                   |
|----------------|---------------------------------|-----------------------------------------------------------------------------------------------------------------------------------|
| System setting | Language selection              | To select your native languages                                                                                                   |
|                | Firmware upgrade                | To upgrade firmware by web browser                                                                                                |
|                | Configuration setting           | To backup and retrieve system configuration setting                                                                               |
|                | Factory default setting restore | To restore default system setting originated in factory production                                                                |
| File system    | FAT16/FAT32                     | A) Support Microsoft Windows FAT16/FAT32/exFAT file system<br>B) Application tools:<br>FAT file system inspection and repair tool |
| File service   | CIFS protocol                   | Provide shared services to files and printers for clients on Microsoft Windows Network                                            |
|                | Samba service                   | Provide shared services to files and printers for clients on Microsoft Windows Network and Unix-Like Network                      |



|                      |                     |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|----------------------|---------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| HTTP(S) service      | OS                  | A build-in browser which support common operation system such as Windows, Linux, Mac® OS and smart terminal for easy management                                                                                                                                                                                                                                                                                                                                                                 |
|                      | WebDAV protocol     | Makes the Web a readable and writable medium which allow users to edit and manage documents and files stored on World Wide Web servers                                                                                                                                                                                                                                                                                                                                                          |
| Access control       | Password protection | <p>A) WiFi access control:</p> <ul style="list-style-type: none"> <li>• Non e</li> <li>• WP A</li> <li>• WP A2</li> <li>• WP A&amp;WPA2</li> </ul> <p>B) WEB access control</p> <ul style="list-style-type: none"> <li>• Pa ssword login</li> </ul> <p>C) Samba access control</p> <ul style="list-style-type: none"> <li>• Pa ssword login</li> </ul> <p>Default security:</p> <p>A) Authentication needed with password 11 111111</p> <p>B) No authentication</p> <p>C) No authentication</p> |
| Network Management   | WiFi setting        | <p>A) WiFi login history cache</p> <p>B) WiFi auto login</p> <p>A) Available wireless networks display</p>                                                                                                                                                                                                                                                                                                                                                                                      |
|                      | LAN side setting    | <p>A) Pontoon IP setting</p> <p>B) Subnet mask setting</p> <p>C) DHCP server setting</p> <p>D) Default gateway setting</p> <p>E) Default DNS setting</p>                                                                                                                                                                                                                                                                                                                                        |
| Application software | Client              | <p>A) Windows XP/2003/Vista/7/8, Linux, Unix, Mac®</p> <p>B) Android: tablet, smartphone</p> <p>C) iOS: iPad®, iPhone®</p>                                                                                                                                                                                                                                                                                                                                                                      |
| File Formats         | iOS Client          | <p>A) Audio: Support formats of <b>MP3</b>, <b>AAC</b>, <b>m4a</b>, <b>wav</b>, <b>aiff</b></p> <p>B) Video: Support formats of <b>MP4</b>, <b>MOV</b>, <b>m4v</b>, <b>avi</b></p> <p>C) Photo: Support formats of <b>jpg</b>, <b>tiff</b>, <b>bmp</b>, <b>gif(image)</b></p> <p>D) Document: Support formats of <b>keynote</b>, <b>numbers</b>, <b>page</b>, <b>excel</b>, <b>word</b>, <b>pdf</b>, <b>txt</b>, <b>ppt</b></p>                                                                 |

|  |                |                                                                                                                                                                                                                                                             |
|--|----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|  | Android Client | <p>A) Audio: Support formats of <b>MP3</b> only at present</p> <p>B) Video: <b>MP4</b></p> <p>C) Photo: Support formats of <b>.jpg</b>、<b>.png</b></p> <p>D) Document: Support formats of <b>txt</b>、<b>word</b>、<b>excel</b>、<b>ppt</b> and <b>pdf</b></p> |
|--|----------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|

## File & System Manager App

- Support the keyword search function from the current folder
- Support the file list/thumbnail view, support thumbnail images show and MP3 artwork shows; Support gravity sensor switch direction
- Support checkmark/delete function and support local/WiFi Storage data transmission in between
- Playing music/video/photos by iPhone®, iPad® and tablet and smartphone (JPG, mp3, mp4, decoding ability more dependent on the system, file format depend on the player software installed on you device, Power7 suggest to use RockPlayer/Mobo player on the Android and Oplayer/GoodPlayer on iOS)
- Support to play the photos by filmstrip mode and support background music playing
- Support video drag and play
- Support music artwork shows, circulation play set, drag operation
- Support email to send out pictures/documents
- Support network and Pontoon's parameters setting
- Transfer videos and photos from and to the iPhone®, iPad® to Pontoon

## System Requirements

- iPhone®, iPad®, smartphone, tablet or computer with Wi-Fi connectivity (802.11 b/g/n)
- Mac® or PC computer running Windows 8, Windows 7, Windows Vista, Windows XP or Mac OS X 10.6.0 or later operating system for loading media on to Pontoon via USB

## Client Tools

### ■ Computer Client Tool

- Auto search and access the Pontoon on WLAN
- Supports Windows XP/2003Vista/7/8 and Mac® iOS operation system

### ■ Mobile Application Tool

- Supports iOS (iPhone® and iPad®) and Android (smartphone and tablet)
- Stream audios and videos and view photos from the Pontoon

### **FCC Caution:**

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### **Radiation Exposure Statement:**

This device complies with FCC radiation exposure limits set forth for the uncontrolled environment. This device should be installed and operated with minimum distance of 20 cm from human body.

## Pontoon Unifies Your Family with Recreation



Share music, photo and video files as well as data files with family and friends anywhere.

### USA OFFICE

World Headquarters

4601 E. Airport, Drive, Ontario, CA 91761, USA

<http://www.power7tech.com>

[sales@power7tech.com](mailto:sales@power7tech.com)

Tel: 909.230.6788 Fax: 909.230.6889

### TAIWAN OFFICE

Power 7 Technology Corporation

5F-3, No. 258, Liancheng Road, Zhonghe

District, New Taipei City 235, Taiwan (R.O.C.)

<http://www.power7tech.com.tw>

[sales@power7tech.com.tw](mailto:sales@power7tech.com.tw)

Tel: 886.2.8227.1790 Fax: 886.2.8227.1026

### CHINA OFFICE

Power 7 (Shenzhen) Technology Company, Ltd.

Building A, Zhangkeng Industry Zone, Minfu Road Minzhi

Village, Longhua Town, Baoan District Shenzhen, Guangdong

Province PR, China

<http://www.power7tech.com.cn>

[pm@power7tech.com.cn](mailto:pm@power7tech.com.cn)

Tel: 86.755.8886.8949 Fax: 86.755.8179.8032