

PHILIPS

Voice Recorder VTR7900



User manual

EN

Welcome

Welcome to the world of Philips! We are Philips products. You can have access to full set of technical support on Philips official website, such as user manuals, software downloads, and warranty information, etc.
www.philips.com/support

Product Features

This product is a convenient clip-on voice recorder, easy to carry, with the following product features:

- Real-Time Transcription.
- Real-Time Translation.
- File transfer.
- Call recording.

Safety Information

- To avoid short circuits, do not place the product in areas exposed to water or moisture.
- Do not place the product near heating equipment.
- Please note that do not squeeze the cable, especially at the plug.

Attention

- Special Statement: Please read this manual carefully before using this product. The company shall not be liable for any data loss or damage caused by human operation or force majeure. Users are specially reminded to operate with caution and back up data separately.
- The displayed images are for reference only. Philips reserves the right to change the color/appearance/design/parameters/product functions. For any updates to hardware, software, or APP, no prior notice will be given.

Usage Notes

- It is recommended to charge the device with a compliant charger for about 2 hours before first use.

Usage Instructions

Getting Started

- Power on: While powered off, press the recording button for 2 - 3 seconds. The device will vibrate and power on, entering standby mode with a green light illuminated. Press the recording button again for 2 seconds to power off the device; the green light will extinguish.
- Recording: In standby mode, press the recording button. The device will vibrate once and commence recording; during recording, the red light remains steadily illuminated. Press the record button again briefly to save the recording and the device will vibrate twice. It will then return to standby mode with the green light illuminated.
- Recording mode: When the toggle switch is in the upper position, the device is in telephone recording mode. When the toggle switch is in the lower position, the device is in standard recording mode. Telephone recording files are named with the prefix 'PH' , while standard recording files are named with the year, month, and day prefix.

Indicator Light Status

- Recording status: Steady red light
- Standby status: Steady green light
- Low battery: Red light flashing
- Charging status: Green light flashing; Lights turn off when fully charged

APP Operation Guide

- Both Android and iOS phones can scan this QR code to install and download the APP. For all permissions popped up during the installation process, please select the "Always Allow" option; otherwise, the APP cannot be used. Please be informed.



Warm Reminder: The APP will be updated regularly without prior notice. The manual is for reference only, and the actual operation shall be based on the latest APP.

- On the main menu interface of the APP's real-time translation function, turn on the button. The APP will start recording, recognize text and translate it, and the voice recorder will also start recording at the same time.
- On the APP's main interface, select "Files" to switch to the file list interface.
- Sync Device: Selecting this option displays a folder named by time. After selecting the relevant folder, pull down the screen to refresh and sync the files from the voice recorder. Note that files recorded via the APP will not be synced to the phone repeatedly; only files recorded independently by the voice recorder can be synced.
- Operations such as editing, sharing, and speaker differentiation can be performed on the file playback interface.

Sync File Operations

- On the APP interface, select the "Sync Device" option to enter the list interface, click the corresponding folder, then select the required files to sync in the list interface. The default transfer method is Bluetooth. During transfer, click "Accelerate" switches to Wi-Fi Fast Transfer. A connection prompt will appear upon switching; click "Connect" to commence transfer. Upon completion, you will return to the list screen. Note: After Fast Transfer concludes, manual connection to the external network is required to access online services.
- After the file is successfully uploaded, click the file to enter and transcribe it.
- The transcribed file can be played, edited, shared, saved, etc.
- On the sync device list interface, select "Delete" and a prompt will pop up with "Delete Phone Files" or "Delete Voice Recorder Files". Selecting "Delete Phone Files" will delete the transcribed content on the phone; selecting "Delete Voice Recorder Files" will delete the files on the voice recorder. Please exercise caution when using the delete function: back up important files to avoid accidental deletion.
- Delete All: Selecting "Select All" and then deleting will remove all files. You can choose "Select All" or "Deselect All".

Technical Specifications

- Connection port: TYPE-C
- Built-in storage capacity: 64GB
- Recording format: MP3
- Bit rate: 32 kbps
- Sampling rate: 16 kHz
- Battery capacity: 700 mAh

Warranty Card

This product is made of high quality material and great care has been taken in its manufacture. It is designed to give good performance provided it is properly operated and maintained. The product is sold subject to the understanding that if any defect in manufacture or material shall appear within 12 months, the warranty period is subject to country Consumer Law, Jingwah Digital Service will arrange for such defect to be rectified without charge under the following warranty terms and conditions.

Warranty Terms and Conditions:

The defect is not due to use of the product for other than domestic purposes, or an incorrect voltage, or use of improper accessories, or contrary to operating instructions, or to accidental damage(whether in transit or otherwise), misuse, neglect or inexpert repair, or incorrect installation, or the product is excessively used for improper purposes other than daily consumption, or accessories belonging to the product, transportation. Present this warranty card and sales invoice when demanding service from Philips authorized service centres.

User's Name:	Model No:
.....	
Address:	Serial No:
.....	
Tel.No:	Product Place:
.....	
Post Code:	Shop name and address:
.....	
Company Seal:	Tel.No/Post Code:
.....	
Date of Purchase:	Invoice No:
.....	

Product Service Hotline:400 800 7890

Register your product and get support at:

www.philips.com/voicetracer

© 2025 Speech Processing Solutions GmbH. All rights reserved.
This product has been manufactured by and is sold under the responsibility of Speech Processing Solutions GmbH, and Speech Processing Solutions GmbH is the warrantor in relation to this product.

Specifications are subject to change without notice. Philips and the Philips shield emblem are registered trademarks of Koninklijke Philips N.V. and are used under license.
Document version 1.0, 16/12/25

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation

This device has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This device generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.
However, there is no guarantee that interference will not occur in a particular installation. If this device does cause harmful interference to radio or television reception, which can be determined by turning the device off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
--Reorient or relocate the receiving antenna.
--Increase the separation between the device and receiver.
--Connect the device into an outlet on a circuit different from that to which the receiver is connected.
--Consult the dealer or an experienced radio/TV technician for help

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment

RF warning for portable device:
The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

