REV: A

440mm

55mm

80mm



认识耳机



尝试佩戴耳机



将耳机麦克风大致对准嘴部

双耳机配对

打开充电盒，取出两个耳机，耳机自动开机，开机后双耳自动配对成功，右耳灯无五耳连入配对状态，手机搜索连接"QCY_T5"即可完成双耳与手机的连接。

（此模式用于双耳配对失败的情况）

关机状态下，分别将左右耳长按5s进入配对状态，然后双击触控面板，进入TWS重新搜索配对状态（已经打同时双灯）配对成功。左耳进入配对状态右耳关灯，点击连接手机搜索"QCY_T5"。

主从切换

首次连接手机，左边为主耳机，有过连接记录不区分主副，自由切换。

双耳机操作功能

开机

关机状态下，触摸触控板约2秒（绿灯亮约1秒）

充电状态下，打开充电盒，取出耳机（绿灯亮约1秒）

关机

任何状态下，触摸触控板约8秒（红灯亮约2秒）

长按触摸面板键8秒（未连接设备时可取动关机,已连接设备，单耳长按关机只会关闭一边）

任何状态下，耳机进入充电盒

切换上一曲/下一曲

听音乐时，触摸右耳机的触控板约2秒后释放，切换下一曲

听音乐时，触摸左耳机的触控板约2秒后释放，切换上一曲

唤醒语音助手

待机或音乐模式下，三击左耳机触控板唤醒语音助手

游戏模式:

音乐或游戏状态下,三击右耳触控面板即进入游戏模式（低延时模式）（听歌再开启,喔嘴嘟三声关闭）

清除配对记录

关机状态下，长按触控面板键10秒，清除与手机的连接记录

双耳共享媒体

播放/暂停

听音乐时，任意一台耳机双击触控板暂停音乐，再次双击触控取播放

单耳机使用模式

1. 耳机在关机状态下，任一耳机长按触控板约5秒，进入配对状态（红绿灯交替闪烁）
2. 打开手机蓝牙搜索配对名，选择QCY_T5点击连接。
3. 连接完成

单耳操作功能

开机

关机状态下，触摸触控板约1秒（绿灯亮约1秒）

充电状态下，打开充电盒，取出耳机（绿灯亮约1秒）

关机

任何状态下，耳机放入充电盒自动关机（红灯常亮）或长按触摸面板键8秒（未连接设备时可取动关机）

接听电话

来电时，双击触控板接听，再次双击挂断电话

拒接来电

来电时，触摸触控板约2秒后释放

给耳机充电

耳机放入充电盒中，即关机进入充电状态，充电时红灯长亮，充满电后绿灯常亮1分钟后熄灭

给充电盒充电

连接USB充电线充电，充电时指示灯绿灯长亮，充满电后绿灯熄灭。



产品特点

- 蓝牙5.0
- 信号稳定低延迟
- 双边通话
- 高清降噪
- 随心触控
- 简单方便

产品参数

型　　号：In1933　　蓝牙版本：V5.0

待机时间：约70小时　　充电时间：约2小时

音乐时间：约4-5小时　　通话时间：约4小时

通信距离：10米（无障碍环境下）

电池类型：聚合物锂离子电池

耳机电池容量：3.7V　40mAh

充电盒电池容量：3.7V　300mAh

充电盒输入参数：5V ⎓500mA

支持协议：HSP/HFP/A2DP/AVRCP

售后服务与支持

保修期：

自产品购买之日起12个月（请妥善保管购买凭证）

免费服务：

在产品保修期内，凡属产品本身质量引起的故障，请将产凭购买凭证与经销商取得联系以享受售后服务。

如有任何产品损害或瑕疵非可归责于产品质量本身，则不在保修范围内。有下列情形者不属于保修范围内：

1、因天灾、地震、雷击、异常电压、环境因素而发生之故障或损毁的。

2、自行或委托未经原厂授权维修之厂商拆卸、改装或更换非原厂零件。

3、未按使用手册操作或因人为使用不当而造成损坏者，如产品进水、腐蚀、摔落、挤压或露在异常温湿度环境下。

若售后服务需求，请联系客服

电话：4008-306-708

执行标准：Q/HL 1-2019；Q/HL 2-2017

网址：www.qcy.com

制造商：东莞市和乐电子有限公司

地址：广东省东莞市道滘镇大岭丁工业区（粤晖路大丁段5号）

QCY蓝牙耳机售后服务

QCY蓝牙耳机售后服务承诺严格按照《中华人民共和国消费者权益保护法》、《中华人民共和国产品质量法》实行售后三包服务，服务内容如下：

在三包有效期内，您可凭购物凭证依照本规定享受免费的修理、更换、退货的权利。

1、自您购买之日起7日内，本产品出现故障，经由QCY售后服务中心确定为产品质量问题，可享受修理、更换、退货的服务。

2、自您购买之日起12个月内，本产品出现故障，经由QCY售后服务中心确定为产品质量问题，可享受修理或更换的服务。

3、自您购买之日起12个月内，本产品出现故障，经由QCY售后服务中心确定为产品质量问题，可享受修理的服务。

三包凭证

产品型号			
用户信息	用户姓名		购买日期
	联系电话		邮政编码
	用户地址		
购买信息	销售单位		
	订单编号		

产品中有害物质的名称及含量

部件名称	有害物质									
	铅(Pb)	汞(Hg)	镉(Cd)	六价铬(Cr(VI))	多溴联苯(PBB)	多溴二苯醚(PBDE)	邻苯二甲酸二丁酯(DBP)	邻苯二甲酸丁苄酯(BBP)	邻苯二甲酸二(2-乙基)己酯(DEHP)	邻苯二甲酸二异丁酯(DIBP)
耳机主体	X	O	O	O	O	O	O	O	O	O
电　池	O	O	O	O	O	O	O	O	O	O
耳　套	O	O	O	O	O	O	O	O	O	O
配　件	O	O	O	O	O	O	O	O	O	O
充 电 线	X	O	O	O	O	O	O	O	O	O

本表格依据SJ/T 11364的规定编制

O: 表示该有害物质在该部件所有均质材料中的含量均在GB/26572规定的限量要求以下。

X: 表示该有害物质至少在该部件的某一均质材料中的含量超出GB/26572规定的限量要求。但该部件应无或例外替代方案。

在服务范围内符合欧盟ROHS指令的环保要求。

使用年限

如本手册所述，在正常使用条件下，本产品的环保使用期限为5年。在此期间，产品不会泄露任何危险物质，本产品可以回收。必须按照当地法规处理。

提示

1. 使用产品前请仔细阅读本使用说明书并请妥善保管；
2. 首次使用时，请先将本产品充满电；
3. 如果产品长期（超过2个星期）不用，请对其充电；
4. 必须选择正规厂家生产且经过国家CCC认证的充电器；
5. 若手机无法搜索蓝牙耳机，请确认蓝牙耳机是否处于"配对模式"，若长时间未进行配对或连接，蓝牙耳机配对功能将关闭，请重新开启蓝牙耳机至"配对模式"；若手机程序出错，请重启手机；若蓝牙耳机程序出错，请重启蓝牙耳机或者恢复出厂设置。

警告

- 请勿以任何理由拆除或维修改装耳机，否则可能会导致起火，电子击穿甚至短路损坏本产品；
- 请勿将产品置于温度过低或过高（0°C以下或45°C以上的环境下）；
- 请避免靠近儿童或动物的眼睛使用产品指示灯；
- 请勿在雷暴天气下使用该产品，雷暴可导致本产品工作不正常，并增加触电的危险；
- 请勿用油及其他挥发性液体擦拭本产品；

注意：长时间使用耳机可能会造成听力损害，请合理安排使用时间。

本耳机不支持输出超过2A的充电座给耳机充电，否则会损害耳机本体。

产品认证：

CMIIT ID: XXXXXXXXXX



Overview

How to Wear



Adjust Mic toward your mouth

How to Pair

Open lid and take out two earbuds, they will auto power on and pair with each other. Left earbud will auto enter pairing mode when LED on right earbud turns off. On cellphone, search for QCY_T5 and tap it to connect both earbuds to cellphone.

(Please try the following steps, in case earbuds fail to pair with each other automatically.)

Turn off both earbuds then touch both earbuds for 5s to enter pairing mode. Double touch both earbuds to enter TWS mode, two earbuds will auto pair with each other when LED blinks red and green. Left earbud will auto enter pairing mode when LED on right earbud turns off. On cellphone, search for QCY_T5 and tap to connect both earbuds to cellphone.

Master Earbud Switch

For first time pairing, left earbud will serve as master earbud. If earbuds connected with cellphone before, either earbud can serve as master earbud(master earbud can be switched free).

TWS Mode

Power-on

Touch earbud for 2s to power on (LED turns on green for 1s)
Take out earbuds from the case to power on(LED turns on green for 1s)

Power-off

Touch earbud for 8s to power off(LED turns on red for 2s)
If earbuds are not connected with cellphone, touch either earbud for 8s to power off both earbuds.
If earbuds are connected with cellphone, touch earbud for 8s to power off that single earbud.
Push earbuds into the case to power off.

Skip Track Forward/Backward

When playing, touch right/left earbud for 2s to skip track forward/backward.

Voice Assistant

When playing or standby, triple touch left earbud to wake up voice assistant.

Gaming Mode:

When playing or gaming, triple touch right earbud to enter gaming mode(low lag mode).
Gaming mode on: two beeps; Gaming mode off: three beeps.

Removing Connectivity Records

Power off earbuds then touch earbud for 10s to remove connectivity records in earphones.

Stereo Mode

Playback/Pause

When playing, double touch either earbud to pause music and double touch again to resume playing.

Mono Mode

1. Power off earbud then touch earbud for 5s to enter pairing mode (LED blinks red and green)
2. On cellphone, search for QCY_T5
3. Connected

Mono Mode

Power-on

Touch earbud for 1s (LED turns on green for 1s)
When charging, open lid and take out earbud (LED turns on green for 1s)

Power-off

Push earbud into charging case to power off (LED glows solid red)
Touch earbud for 8s to power off(if earbud is not connected with cellphone, touching either earbud for 8s will power off both earbuds)

Answer Call

Double touch earbud to answer incoming call and double touch again to end it.

Ignore Call

Touch earbud for 2s to ignore incoming call

Charging Earbud

Push earbud into the case to charge. LED will glow solid red when charging and turn to green for 1 minute once top up.

Charging the Case

Charge the case via USB cable. LED will glow solid green when charging and turn off once top up.



Features

- Bluetooth 5.0 chipset delivers stable signal with low lag
- Crystal-clear stereo talking with noise isolation
- Easy-to-use control

Product Parameters

Model:In1933　　Bluetooth version: V5.0
Stand time: approx. 70hr　　Charging time: approx. 2hr
Music time: approx. 4 or 5hr　　Talking time: approx. 4hr
Operation range: 10m(with no obstacle)
Battery type: li-ion
Battery capacity(earbud):3.7V　40mAh
Battery capacity(charging case):3.7V　380mAh
Input parameter(charging case):5V ⎓500mA
Bluetooth profiles: HSP/HFP/A2DP/AVRCP

Hazardous substances and their contents in the item

Part Name	Hazardous Substances									
	Pb	Hg	Cd	Cr(VI)	PBB	PBDE	DIBP	DEHP	DBP	BBP
Main body	X	O	O	O	O	O	O	O	O	O
Battery	O	O	O	O	O	O	O	O	O	O
Ear tips	O	O	O	O	O	O	O	O	O	O
Accessories	O	O	O	O	O	O	O	O	O	O
Charging cable	X	O	O	O	O	O	O	O	O	O

This form is made by SJ/T 11364 regulation.

O: means that hazardous substance content in the homogeneous materials of this part is within the limits of (EU)　2015/863 regulation.

X: means that hazardous substance content in at least, one certain homogeneous material of this part is beyond the limits of (EU)　2015/863 regulation ,but there is no mature alternative in the industry at present, it still conforms to the EU ROHS Directive in the scope of exemption..

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.

Perform standard: Q/HL 1-2019 ; Q/HL 2-2017
Manufacturer: Dongguan Hele Electronics Co., Ltd.
Address: Daojiao Town, Dongguan City, Guangdong, China

Tips

1. Before using the headset, please read the manual carefully and keep it for future references.
2. The headset need to be fully charged prior to first-time use.
3. If the headset is left unused for over two weeks, please recharge it periodically.
4. Please use the chargers made by qualified manufacturer.
5. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode, please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headsetoccurs, reboot or reset it.

Caveats

1. Never disassemble or modify your headset for any reasons to avoid any damages and danger.
2. Do not store the headset in extreme temperatures (under 0°C or over 45°C).
3. Avoid using the indicator close to the eyes of children or animals.
4. Do not use this headset during a thunderstorm to avoid irregular function and increased risk of electrischock.
5. Do not use harsh chemicals or strong detergents to clean the headset.
6. Keep the headset dry.

Warranty Card

Warranty Period
12 months after you purchase this item.(or you may inquire your local shopper for more details.)
Free Service
Supposing any defects caused by quality issues occur within the warranty period, please take this warranty card and purchase receipts to your distributor for free exchange service.

Model Number:
Date of Purchasing:
User's Name:
User's Phone:
User's Address:
Shop's Name:
Shop's Address:
Comments:

Free exchange service will not be accessed under following circumstances:
1. Damages caused unauthorized disassembly.
2. Defects or physical damages caused by leaking or dropping off.
3. Damages by act of God.Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

FCC Statement

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radiocommunications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:
-- Reorient or relocate the receiving antenna.
-- Increase the separation between the equipment and receiver.
-- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
-- Consult the dealer or an experienced radio/TV technician for help.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

CMIIT ID: XXXXXXXXXX

1.尺寸要求：图面标注尺寸为必检尺寸
2.环保要求：符合和乐环保标准《HL-QP-RD-03》& 包材指令
3.可靠性要求：符合和乐物料可靠性测试规范《HL-WI-QA-026》
4.其它方面要求：

名称	公差：mm
外箱	±5.0
彩盒	±0.5
标签	±0.5
说明书	±1.0
热缩膜	宽:±3,高:±15
防爆袋	宽:±3,高:±15

东莞市和乐电子有限公司

版次说明						
	料号	30.001.001146	软件		法务	
	名称	T5原睿中英文说明书	电子		市场	
	材质工艺	70g书写纸	结构		包装	易超
	软件版本号		声学			
	物料承认书编号		品牌			