

Turning the Headset On and Off

Turning On the Headset

Press and hold the **MFB** for 2 seconds until you hear a short “beep” tone. The **LED** will flash green.

IMPORTANT Press the **MFB** again each time you turn on the headset to re-activate pairing so that the connection between the headset and the mobile handset is resumed. For pairing, please refer to “Pairing Your Headset” on page 6-7.

Turning Off the Headset

Press and hold the **MFB** for 3 seconds until you hear a long “beep” tone. The **LED** flash stops.

Adjusting the Volume

Press the **Volume Key** repeatedly until you reach the desired volume level.

Resetting the Headset

You may want to reset the headset to its default settings. This also clears all current pairings.

1. Ensure the headset is OFF.
2. Press the **Volume Key** for 20 seconds.
3. The **LED** will alternately flash green and red rapidly.
4. Release the **Volume Key**.
5. Press and hold the **Volume Key** again for 2 seconds until you hear two “beep” tones.
6. Recharge the headset for a few seconds.
7. The headset is turned off and returns to the default setting. All current pairings are cleared.

Troubleshooting

If you are unable to connect your headset and mobile handset, please try the following:

- Ensure your headset is turned on and is properly charged.
- Ensure the headset is paired with your mobile handset.
- Ensure your mobile handset’s Bluetooth feature is activated. Please refer to your mobile handset user guide for specific instruction.
- Ensure the headset is within a maximum of 10 meters of your mobile handset(s) and there are no obstructions, such as walls or other electronic devices in between.
- Ensure your headset has not reached its 8 mobile handsets limit. If the headset has reached its pairing limit, please reset it to its original settings and recharge for a few seconds.
- If the above steps do not resolve your problem, please recharge the headset and remove your mobile handset battery pack for a while.

Charging Your Headset

Connect the charger to an AC wall outlet and the charger plug to the headset’s charging socket (fig 2). The **LED** will be red while charging.

IMPORTANT Charging indication will be delayed for a few minutes if the headset has not been used for a long time or the battery is drained.

Nominal Charging Time

Charging the battery fully is normally within 3 hours. When the battery is fully charged, the **LED** will turn green. Disconnect the charger from AC wall outlet and the headset. Press and hold the **MFB** (fig 1) for 2 seconds to turn the headset on, please refer to "Turning the Headset On and Off " in the next page.

Talk & Standby Time

The fully charged battery offers up to 4 hours talk time and up to 120 hours standby time. When no calls are in progress, the headset remains turned on in standby mode.

Low Battery

When the headset is on and the battery becomes low, the **LED** flashes red and the headset emits a beep every 1 minute. Please recharge the battery as described above.