




SmoothTalker™

Maximum Power



Dual Band 15"Mag Mount Antenna



Dual Band Glass Mount 15" Antenna



Dual Band 2"Mag Mount Antenna



Dual Band Glass Mount 2" Antenna

(Optional)



Adapter Cables
(Order Separately)



AC/DC Power Supply
(Optional) Allows Use of
Booster In Home Or Office

For Use with CDMA Mobile Devices

Linear Gain Transmit & Recieve R.F. Signal Booster

Frequency: CELLULAR Band

Structure: Full Duplex

Output Power: Max 3 watt

PCS Band

Full Duplex

Antenna Gain Only

DC Input Power

Standby

DC 12V/0.2A Max

In Use

DC 12V/01.5A Max

Weight

300g

Dimensions

12.5X82X25mm

RF Connector

MCT Male



SmoothTalker™

Maximum Power

User Instruction Manual

Model BST100/150

Cellular Band Booster Amplifier

For use with:

CDMA IS95, CDMA 1X, CDMA2000, WCDMA
GSM, GPRS, TDMA, AMPS

Warning

Please note:
Antenna should be
positioned at least 8"(20cm)
from all person/persons as
per requirements necessary
to comply with the FCC MPE
rules. This is to limit the Radio
Frequency exposure to the
user or person/persons near
the antenna connected
to this device.

Contact us at: www.smoothtalker.com