

Messages

You may read, write, send and store all kinds of text messages. All kinds of its functions need network support. Please contact the network operators for details. First you need to store the number of the message center in the phone and then you can send text messages (please refer to "settings" in "Messages").

Write message

In standby mode, press  key to enter the main menu, then operate "Messages" and "Write Message" by turn to enter message editing interface. Press  key to change between input modes and choose the common expression that you want to insert. After editing the messages that you want to send, press  key for confirmation; and enter the number input interface, you may enter the number directly to send the message or press  key to spring the (Phonebook, Add to multiple send) to enter message transmission options.

-Phonebook

After entering this menu, the phonebook option list will appear, you may browse the phonebook and choose the telephone number that you want to send message. After the choice is complete, press menu to spring up the  key, you and choose all kinds of operations to send current message. If the message is not successfully transmitted, the message will be automatically stored in the Unsent.

-Add to multiple send

When entering this menu, the group message phonebook will appear, press  key to spring up the menu.

Input directly: enter the number entry mode, enter the 1st number, and a number list will appear after pressing  key for confirmation, and the list includes the number that you have just entered. Press menu to spring up the  key, you may choose relevant operations to do the entry of numbers. After the entry is

Messages 21 

complete, you may choose to send the messages. And prior to transmission, the alert frame of "sure to send?" will appear, and after choosing confirm, "please wait" and "message sent" will appear, or else "transmission fails" will appear.

Phonebook: then enter the phonebook option list, choose the number that you want to send message, press  key to spring the menu, and you may do relevant operations. Choose different transmission modes to send current message. If the transmission fails, the message will be automatically stored in Unsent.

Inbox

When you have received new text message, the phone will give out message alert tone, and "New message Read?" will appear on the display, and the message icon will also appear at the top of the display.

If the storage space in the mailbox is full, "Storage space full!" will appear. And the message icon will flash at the top of the display, and after deleting some messages in the

Inbox, you may receive the message once again.

Then directly press  key to read the most recent message, and the display will show the latest information, such as time, date of receipt and number, etc. You may also press  key to exit, and enter the Inbox to read the message later on. In standby mode, press  key to enter the main menu, select "Messages" and "Inbox" to enter the Inbox; or when in standby mode, press the right navigation key to quickly enter the Inbox.

In the message list of the Inbox, press  key to spring up the menu:

-Reply

You may provide answer for current message.

-Forward

You may transmit current message to the third-party.

-Call back

You may make a call directly to the number recorded in the message and the number displayed in the message record.

-Extract number

You may save the number sending the message or in the message.

-Delete

You may delete the message

And in the interface of message list, press the left-right navigation key you may do quick page browsing of the message list.

After reading the message, press menu to spring up:

-Forward

You may transmit the message chosen to the third party.

-Call back

You may make a call directly to the number recorded in the message and the number displayed in the message record.

-Extract number

You may save the number sending the message or in the message.

-Delete

You may delete the message.

In the message content interface, press the left-right key you may read 2 messages before and behind it.

Sent

Saving messages that you have successfully transmitted recently.

In the list of sent messages, press up-down navigation key to do corresponding scroll; press the left-right navigation key, you can the page-opening of message list. Press menu to spring up:

-Send

To do transmission for the message in different manners

-Edit

Enter the interface for editing the message, and do transmission of different manners for the message after editing.

-Delete

To realize deletion operation for the message.

Messages 23 **UIRD**

Press  key to enter the interface for reading the message, in the message content interface, press menu to spring up the  key of "edit, delete" (same operation as the above). Press the left-right navigation key you may browse the 2 messages before and behind it.

Unsent

To save the messages that you have failed to send recently

Draft

To save the message that you currently want to send

See "Sent" for specific operations of the **Unsent** and **Draft**.

Settings**-Validity period**

If you have set up validity of messages before, then your past settings will appear in the option list, or else the "Longest time" will appear. Press the up-down navigation key to choose the setting that you need: 1 day, 3

days, 7 days, 30 days, Maximum. Press  key to save the setting and give out alert information, return to the setting menu; press  key or  key to return to the setting menu.

-Service center

If you have already set the Information Center number before, enter the setting and bring the number to the edit mode, or else empty editing mode will appear, and it can be empty after the output of number. Press  key to save the Information Center number, and give out the alert information. Return to the setting menu and press  key to return to the setting menu.

-Template

To show all 15 oft-used messages, in which the first 10 cannot be edited, and the users may edit the last 5 messages. Press the up-down navigation key to scroll, press  key to spring up the menu, and choose "edit" to edit the message. Press  key to save the message after editing, and choose "delete" to delete current message, and set the message as "undefined".

UIRD 24 Messages

Delete messages

In standby mode, press  key to enter the main menu, choose "Messages" and "Delete messages" by turn to enter the interface for Delete messages. If you want to delete all messages, please choose "All", and "Delete all" will appear on the mobile phone, press  key for confirmation.

If you want to delete all messages in other message boxes, you may choose "Inbox", "Sent", "Unsent", "Draft", and "delete all?" will appear on the display, and press  key, the message will be deleted.

Cell broadcast

The Cell broadcast message is the text message provided by network operators to the users. This message may be weather forecast, traffic news and taxi information, etc.

-Inbox

To show the messages of community message, and do deletion, call, etc. to the community message.

-Channel

To show information on the signal channel of the community message, and do addition, deletion, etc. to the signal channel of the community message.

-Language

To choose between the languages of community messages, including simplified Chinese and English.

-Settings

To show the on-off setting of community message, including the modes of on and off.

Voice mail

To receive new voice mail

When you receive a new voice mail, you will receive message, alerting that you have voice message, you may enter your voice mailbox to read the voice message. If the voice message number setting is not correct, wrong number will be displayed, and the phone will directly enter standby mode when overtime.

Call records

This phone can record the telephone number of received call, missed call and dialed call, and may also record the approximate time of the call. It is only when the network supports relevant function, the phone is on and is in network service area can it record missed call and received call.

Missed calls

To show the list of telephone numbers that you have missed, press the up-down navigation key to browse the record of missed calls, press  key to spring up the menu:

-Delete

You may delete the record.

-Save

You may save the number of the call record.

-Save as rejected

You may add the number to the rejection number list in the incoming call firewall.

-Send SMS

You may send message to the number in the call record.

After choosing one of the record, press  key to enter the interface for viewing details of the record. The interface will display the "name", "number", "call time", "length of call".

Received Calls

To show the list of numbers that you have dialed recently, press the up-down navigation key, press Menu to spring up (Delete, Save, Save as rejected, Send SMS) (same operation as "**missed calls**"), press  key to enter the interface for viewing details. The interface will display the "name", "number", "call time", "length of call".

Dialed numbers

To show the list of numbers that you have dialed recently, press the up-down navigation key, press Menu to spring up (Delete, Save,

Save as rejected, Send SMS) (same operation as "Missed calls"), press  key to enter the interface for viewing details. The interface will display the "name", "number", "call time", "length of call".

All records

To show the list of telephone number of all recent calls, press the up-down navigation key to browse the record of all missed calls, press Menu to spring up the (Delete, Save, Save as rejected, Send SMS) (same operation as "Missed calls"), press  key to enter the interface for viewing details. The interface will display the "name", "number", "call time", "length of call".

Call duration

-Last call

To show the time of your most recent call

-Received calls

To show the sum of time of all received calls

-Dialed numbers

To show the sum of time of all dialed calls.

-All calls

To show the sum of time ever since your most recent clearance of the record

-Reset timer

To clear your past calls

Delete all

-Missed calls

To delete the record of all recent calls that you have dialed

-Received calls

To delete the record of all recent calls that have received

-Dialed numbers

To delete the record of all recent calls that you have missed

-All records

To delete the records of all recent dialed, received and missed calls.

Call records 27 

Phonebook

You may store the name and telephone number in the memory of the phone and SIM card. In the memory of the phone, at most 100 telephone numbers can be stored, and the capacity of SIM card is based upon different cards.

Search

-Use the function list to search the telephone number

In standby mode, press  key to enter the main menu, select "phonebook" and "Search" by turn, and the display will alert you to enter the name that you want to search, then you have the following 2 manners in searching the number that you want:

1. You may enter the full name to search the telephone number stored, or enter one character or letter to search the telephone number.
2. If you are not sure of the name that you want to search, press  directly to enter the

phonebook, and press the up-down navigation key to scroll to the telephone number needed.

-Quick search

In standby mode, press up-down navigation key to enter the phonebook, enter corresponding letter, for example: if you want search the name "Zhang San", then after entering "Z", the list will automatically search name lists starting with "Z".

After searching the name that you want in any of the above manner, press  key to dial the number and press  key to spring menu:

-Send SMS

To edit and send message to current number.

-Edit

To enter the interface of editing materials of the number, press up-down navigation key to scroll to the item that you want to edit, press  key to enter the interface for editing the item. Press  key after editing to save the modification that you have made.

-Delete

To delete current telephone number.

-Copy

To copy current telephone number to the mobile phone of the SIM card.

-Add

To add new telephone numbers.

-Search

To search for new telephone number.

-Select group

To enter group selection.

Add

In standby mode, press  key to enter the main menu, select "Phonebook", "Add" by turn to enter the interface for adding telephone number.

Press the up-down navigation key, you may scroll on corresponding items of the number.

Press  key to enter the interface for editing the item. After filling all items, press  key to save the number, and the number

will be stored when "Stored" appears on the display.

Delete

In standby mode, press  key to enter the main menu, enter "Phonebook" and "Delete" by to enter the interface for deleting telephone number. This function provides 3 manners (SIM card, mobile phone and self-defined deletion) of deleting telephone numbers in the phonebook:

-SIM

Choose SIM, "Delete all entries in SIM" will appear on the display, choose "yes", you will delete all telephone numbers on the SIM card.

-Phone

Choose Mobile phone, "Delete all entries in phone" will appear on the display, choose "yes", you will delete all telephone numbers on the mobile phone.

-Delete selected

Choose Delete selected, the list of all telephone numbers will appear on the display, you may

Phonebook 29 

press  key to select or not to select the number that you want to delete, press  key to spring up the menu:

Confirm: "delete?" will appear on the display, choose "yes", you will delete the telephone number that you have just chosen.

Select group: you may do self-defined deletion to members of the group.

Select all: you will choose all of the numbers in current list.

Cancel all: you will cancel all selections that you have just made.

Copy

In standby mode, press  key to enter the main menu, select "Phonebook" and "Copy" to enter the interface for copying the telephone number. This function provides 3 manners (from SIM card to mobile phone, from mobile phone to SIM card, self-defined copying) for copying telephone numbers.

-SIM to phone

Select this, "Copy all entries in SIM?" will appear on the display, choose "yes", you will

copy all telephone numbers of the SIM card to the mobile phone.

-Phone to SIM

Select this, "Copy all entries in phone?" will appear on the display, choose "yes", you will copy all telephone numbers of the mobile phone to the SIM card.

-Copy selected

Select this, the list of all telephone numbers will appear on the display. Choose the number that you want to copy, press  key to spring menu:

Confirm: you will copy the number that have chosen.

Select group: you will enter the group to select the numbers that you want to copy.

Select all: you will choose current list of all telephone numbers.

Cancel all: you will cancel all selections that you have just made.