

High Resolution sound with
apt-X HD & External speaker
Overhead headphone

Sound Master MFB-H7100

User Guide



MobiFren is made by dreaming for all the user's happiness.

It delivers premium sound via MSTST[™] Tuning Technology together with lossless compression codec apt-X HD & AAC codec enabling you to enjoy music with premium Hi Fi sound in wireless like as CD quality.



- MSTS™ is a Audio Technology of MobiFren Co.,Ltd.
- Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries, used with permission. aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries, used with permission.

MobiFren MFB-H7100 Features

- **Built-in stereo speaker**

You can call and listen music via speaker mode simply by switch, without wearing headphone.

- **Premium Sound**

MSTS™ Tuning Technology together with lossless compression codec apt-X codec & AAC codec enables you to listen premium Hi-Fi stereo sound.

With built-in DSP chip, it enables optimal call quality by noise reduction and echo cancellation.

- **Supporting Android & iOS App.**

You can use many kinds of useful functions like as below, if you download MobiFren_SM from the store.

※ App function may be changed due to mobile phone OS update or improving or adding function.

Caller ID TTS	If you press any button of the headset on incoming call, your mobile reads you the caller's name. (In case of iPhone, it reads caller ID together with bell sound and you can listen via earphone too)
SNS message TTS	If there's new message of SNS or Line, it reads you the message, together with vibration.
Find mobile phone	If you can not remember well where you placed mobile phone, it helps you to find out your mobile phone by pressing headset button.
Hot call	If you register the number in advance that you call frequently, you can call easily by pressing headset button.
Last Call (Available with Android)	You can call to the latest number directly.
Camera Remote control (Available with Android)	It enables to play as a remote control when you take a picture. It's helpful when you take a self picture or group picture.
Present time notice	By pressing headset button for 2 times consecutively, it notices you the present time.
Voice Memo (Available with Android)	It's to record the conversation by operating headset button simply during a call.
Anti Mobile Phone loss	If your mobile phone is out of ranges from the headset, it alarms you by vibration for 1 minute to prevent the loss of your mobile phone.

- **Vibration on incoming call**

The headset alarms you by vibration if there's incoming call.

- **Anti phone loss mode**

If your mobile phone is out of ranges from the headset, it alarms you by vibration for 1 minute to prevent the loss of your mobile phone.

- **Multi Point**

- **Supporting Bluetooth 4.2**

- **Voice prompt**

- **Firmware upgrade**

※ Features of this product depend on your mobile phone. Check your mobile's user manual for further information. Thank you for choosing MobiFren MFB-H7100. It is high quality stereo Bluetooth headset, designed to provide you convenient and easy way of using your mobile phone.

User Guide

Contents

Headset & Accessories	1
Safety Instruction	1
Turn on/off the headset	2
Charging	2
About your MobiFren MFB-H7100	3
Button Guide	4
Getting started with your MobiFren	6
1. Pairing to your mobile phone	6
2. Multi point setting	7
3. Call	7
4. Factory Reset	8
5. Firmware Upgrade.....	8
6. Changing Music Mode.....	8
7. Use speaker mode	9
8. Mobile phone Anti-loss feature.....	9
9 Using Android & iOS application	10
What does LED color mean?.....	12
FAQ & Troubleshooting	13
Handle MobiFren with care	14
Certification and safety approvals	15
Specifications.....	16
Warranty	17


Headset & Accessories




MFB-H7100



case



User Manual




Charging cable

※ The drawings and examples in manual are for better understanding to this product, so, it may be different from the real goods. Accessories and design can be changed without prior notice.

Safety Instruction

- Road safety at all times.
- Using mobile phone while driving can distract you and increase the possibility of an accident.
- Do not use mobile phones while driving. Always drive safely and follow local laws

Turn on/off the headset




<Turn on>

Press MFB for 2 seconds. It turns on and glitters blue LED.

<Turn off>

Press MFB for 4 seconds.

Charging



- ※ Make sure that your headset is fully charged before you use it.
- The LED shows 'RED' during charging and will turn 'BLUE' when fully charged.
- While using USB hub, charging may not work properly, due to low current.
- It's ok to use while charging.
- Android mobile charger (Micro 5 pin) is also workable for charging.

About your MobiFren MFB-H7100



(1) LED Light	LED guide light for headset status
(2) Microphone	Microphone
(3) Micro USB charging port	Charging port
(4) Volume up $\oplus$	Volume control, Next song etc.
(5) Multi Function button $\odot$	Turn on/off, Answer/Reject/Convert a call/Convert mode
(6) Volume down $\ominus$	Volume control, Previous song etc.
(7) Mode change switch	Selecting switch for headphone mode or speaker mode
(8) Ear cushion	Ear cushion for comfortable fit

Button Guide

You can control MFB-H7100 easily with the above 3 buttons.

⏻ MFB ⏩ Volume up ⏪ Volume down

Basic Button Control

⏻ Press MFB

Answer a call	Short press
End a call	Short press
Turn on headset	Press for 2 second (If no paired device, it moves to pairing mode automatically.) (If there's paired device, it connects to the paired device.)
Turn off headset	Press for 4 seconds
Pairing mode	Press for 4 seconds at power off
End a call	Short press (during call)
Reject a call	Press for 1 second
Convert a call	Press shortly in mobile during call
Play/Pause	Short press
Siri Voice input	Press for 1 second

⏩ Press volume down button

Volume +	Short press
Next song	Press for 1 second (during play)


⏪ Press volume down button

Volume -	Short press
Mic mute	Press for 1 second (during call)
Previous song	Press for 1 second (during play)

⏻ MFB + Volume ⏩ or ⏪ Press at the same time

Music Mode Change	Press for 1 second (during play) To move forward direction, press ⏻ button and ⏩ button simultaneously. To go backward direction, press ⏻ button and ⏪ button simultaneously.
-------------------	---

Mode change



To change mode between headphone mode and speaker mode, move thi mode change button.

Factory Reset



Press ⏩→⏪→⏩→⏪→⏩→⏪→⏻ buttons in order , then press ⏻ button till purple LED glitters. Then, you can initialize the headset

Firmware upgrade



Please connect MFB-XXXXXX to PC by charging cable while pressing ⏪ button. Then, red LED blinks and it goes to firmware upgrade mode

Operating App functions with headset

TTS caller ID	⊕ or ⊖ Press volume button	Short press for 1 times (when the bell rings)
TTS(Stop during TTS)	Press any button among Ⓞ/⊕/⊖ buttons	Press any button Short press for 1 times (during message TTS)
TTS(Manual TTS play)	Press Ⓞ MFB + Volume ⊕ or ⊖ at the same time.	Short press
Camera remote control	⊕ or ⊖ Press volume button	Short press at standby
※ You need to download additional camera application.		
Time notice	Ⓞ Press MFB button	Short press for 2 times
Voice Memo	Ⓞ Press MFB button	1 seconds and hold pressed and release
Hot call (prompt call)	⊕ Press Vol. up button	Short press for 2 times (at standby)
※ While the sound vibrations to make a call to a specified number.		
Last Call (Direct call)	⊖ Press Vol. down button	Short press for 2 times (at standby)
※ There are basic mode and exceptional mode for Hot Call/Last Call. If you choose exceptional mode, it works during playing music. You can set exceptional mode in app.		
Find my mobile phone	⊕ and ⊖ at the same time	Press for 1 second

Getting started with your MobiFren

MFB-H7100 are easy to use for everyone

1. Pairing to your mobile phone

- * Before you use MobiFren Bluetooth earphone, you need to pair it with your mobile phone or Bluetooth enabled device.

Step1 : Entering into pairing mode with Bluetooth headset

- Press  button till LED is continuously on for about 4 seconds at power-off.
(You need to pair in your mobile within 3 minutes.)

Step2 : Pairing by mobile phone

- ① Activate Bluetooth function in your mobile phone according to phone manual and search MFB-H7100 and select, then, it shows "Pairing".
(Some mobile phones need pass key(PIN), then, enter 0000.)
- ② If pairing is successful, it shows that " Connected to phone and media audio" and blue LED glitters for 5 times. Now, it's ready to use.

※ Pairing will be more easy with MobiFren_SM application.

- ① Install "MobiFren_SM" from Google play store / App store.
- ② Press the first menu "Pair (Connect) headset ", then it goes to Bluetooth setting.
- ③ Activate Bluetooth and search headset.
- ④ Select "MFB-H7100" from the searched devices, then it pairs.

※ Connecting app for iPhone

To use convenient app for iPhone, you need to connect "MobiFren_SM" app after connecting headset to iPhone.

After connecting MFB-H7100, there 's "Bluetooth connection" pop-up window after running "MobiFren_SM ." Then, connection is completed if you select "connection by pair"

(If you run app within 1 second after connection, there's "Bluetooth connection" pop-up window automatically. If it passes for 1 second, please press any button of the headset and run "MobiFren_SM." Then, there 's pop-up message to connect.)

※ Useful tip (3 ways to go Bluetooth setting)

- ① Setting, Bluetooth on wallpaper.
- ② Drag down the screen and press Bluetooth icon.
- ③ Run MobiFren_SM app. and select the menu " Pair (Connect) headset".

※ Pairing process may be different from mobile phone makers. Please refer to mobile phone's manual.

※ In case of iPhone, it connects with 2 devices, MFB-H7100 and MFB-H7100SM in Bluetooth setting.

2. Multi point setting

※ It's possible to pair up to 8 Bluetooth enabled devices and can use 2 devices simultaneously.

(App related functions which are not Bluetooth basic functions like as call or listening music shall be connected with only one device, so, we recommend to connect with one mainly used device.)

1) Setting Multi point

- Please pair MFB-H7100 to the first device according to the pairing process.
(Refer to pairing process P.6)
- Turn off MFB-H7100.
- Please pair MFB-H7100 to 2nd device according to pairing process.
- Then, turn off MFB-H7100 and turn on again, it will be connected 2 devices.

2) To use multi point

- At the status of connecting two devices, press  to answer a call if there's incoming call.
- At the status of connecting two devices, if you press  then, you can listen the music for the device that was played lately.

3. Call

1) Answering a call

- Press  button to answer a call.
- Vibration on incoming call : There's vibration in every 2 second, if there's incoming call.
You can set ON/OFF in app.

2) Ending a call

- Press  button to end a call.

3) Rejecting a call

- During call, press  button for about 1 second.

4) Converting a call

- During call by mobile, press  button to convert to headset
(To call by mobile again, use your mobile phone menu.)

5) Volume control

- With  /  button, you can control volume.

6) Microphone Mute

- During call, if you press  button for about 1 second, the mic becomes mute.
- During mute, it will be released, if you press  button for about 1 second.

7) Waiting a call and put a call on hold

- This feature allows you to put a call on hold during conversation and answer a waiting call.
- Give the ⊕ a long press (press approximately 1 second) to put an active call on hold and answer a waiting call.
- Give the ⊕ a long press to switch between two calls
- Just press ⊗ shortly to end a call.

4. Factory Reset

Press ⊕ → ⊖ → ⊕ → ⊖ buttons in order , then press ⊗ button till purple LED glitters. Then, you can initialize the headset. Please pair the headset again after factory reset

5. Firmware Upgrade

- Firmware upgrade is available at our homepage when there's performance upgrade or additional functions. Please connect MFB-H7100 to PC by charging cable while pressing ⊖ button. Then, red LED blinks and it goes to firmware upgrade mode.
- ※ Do not disconnect the headset from PC during firmware upgrading.
It may cause malfunction or damage to the headset.
- ※ After firmware upgrade, the headset becomes initialization automatically.

6. Changing Music Mode

- There are 6 kinds of music modes in MFB-H7100.
You can change mode in basic music mode.
While playing music, if you press ⊗ button and ⊕ or ⊖ button at the same time for 1 second, the Music Mode will be changed in order. (EQ is not available at speaker mode)
- MSTSTM Tuning technology together with lossless compression codec apt-X & AAC codec enables you to enjoy not only MobiFren sound but similar sound of various kinds of famous high end earphones and you can select it as your preference. Now you will enjoy the music with the optimum sound quality like as CD in wireless.

- Basic music mode

- **MOBIFREN Mode (Normal)** : MobiFren mode for optimized to listen music
- **Studio Mode** : Mastering specialist's sound for analyzing
- **Wide Mode** : Warm and grand stereophony and spacious sound
- **Crystal Mode** : Cool and refined sound with powerful bass
- **User Mode** : Self-made sound
- **Cinema Mode** : Surround sound for cinema

※ There are several kinds of bit rate even though it's the same MP3 file.

If the file source is higher bit rate(320K) for listening, you can feel the real worth for our Bluetooth earphone. And, if the speaker is not good even with good source, the sound quality will not be good, and if the speaker is good with inferior source, the sound quality can't touch to the listener. The MobiFren earphone of optimized tuning supplies you high quality sound, but, we also recommend you to use high resolution source file (320K) to enjoy touching sound.

7. Use speaker mode

- You can listen music or call with built in speaker.
 - You can listen music or call with speaker mode, like as a Bluetooth speaker, without wearing headphone.
 - Volume increases gradually for hearing protection when you change to speaker mode.
- ※ For clear call quality, only the left sided speaker works when you call in speaker mode.

8. Mobile phone Anti-loss

- If your mobile phone is out of some ranges from the headset, the headset alarms you with vibration for 1 minute to prevent phone loss.
- During alarm, press any button of  /  /  to stop vibration.

For more convenient and easy use of the headset, please download "MobiFren_SM" at Google play store or Apple App store.

(Minimum supporting specification : higher than iPhone 4S / Recommend : higher than iPhone 5)

※ Detailed operation for each function shall be different between Android and iOS app.

● TTS caller ID

If you press ⊕ or ⊖ button shortly when there's an incoming call, you can listen the caller's name via mobile phone speaker.

● Message TTS (SMS/ Line/ SNS)

After setting Message TTS, in automatic mode, it reads you message after the setting time, and in manual mode, you can hear message by using headset button. (When you set this function, it goes to mobile phone's accessibility menu automatically, then, select MobiFren_SM in accessibility service.)

Stop while playing TTS : TTS playing stop.

While reading TTS message, press ⏸ / ⊕ / ⊖ button to stop playing.

Manual mode : It reads you message by pressing headset button.

Press ⏸ button + ⊕ or ⊖ button at standby.

● Find mobile phone

If you can't remember well where you placed your mobile phone, press ⊕ or ⊖ buttons at the same time for about 1 second to find out your mobile phone. Then, the mobile phone will ring.

● Hot Call (Prompt call)

Register one frequent call number and press ⊕ button shortly for 2 times.

(In case of iPhone, it needs to press Call button in your mobile.)

● Last call (call to the latest number) (Android only)

If you press volume ⊖ button shortly for 2 times, earphone reads you the latest caller. You can move the call list by volume button and press ⏸ button for 2 times shortly to connect call. It's useful when you drive or can't see mobile phone display.

● Camera Remote control (Android only)

Press ⊕ or ⊖ button shortly to take a picture after running application.

※ It needs additional MobiFren camera application. Please install it after searching MobiFren at Google play store.

● Present time notice

⏸ You can hear present time via headset if you press ⏸ button for 2 times consecutively.

- **Voice Memo (Android only)**

It's useful to record voice memo by pressing ㊟ button for 1 seconds and releasing during a call. You can record it by pressing the same ㊟ button during a call or not.

- **Anti Mobile Phone loss**

If your mobile phone is out of some ranges from the headset, the headset alarms you with vibration for 1 minute to prevent phone loss.

< Available functions for Android or iOS app >

App function	Android	iOS
Music Mode control	○	○
Battery gauge	○	○
Message TTS	○	○ (Ref.) iPhone supporting SNS shall be different from that of Android.
Anti Mobile Phone loss	○	○
Last call (call to the latest call number)	○	X
Hot call (Prompt call)	○	○
Camera remote control	○	X
Present time notice	○	○
Find mobile phone	○	○
Caller ID TTS	○	○
Voice Memo	○	X
Factory reset	○	○

What does LED color mean?

Status	LED indication
Standby	LED OFF (If press button, blue LED blinks for 5 times)
Battery is running low	Blinks red light
Charging	Red light ON
Fully charged	Blue light ON
Pairing mode	Blue light ON

FAQ & Troubleshooting

- **I hear crackling noises.**

For the best audio quality, always locate your headset close to mobile phone.

- **I cannot hear anything**

- Increase the volume on the headset.
- Ensure that the headset is paired with the phone.
- Make sure that the phone is connected to the headset.
- If the headset fails to connect either when you pressed MFB or through your mobile phones' Bluetooth menu, follow the pairing procedure in Page 6.

- **I have problems with pairing even though my phone indicates otherwise.**

Please delete the headset paired in your mobile and pair the headset again. Please refer to set up "Pairing mode" in Page 6.

Please try to pair again.

- **Will the MobiFren MFB-N5100 work with other Bluetooth equipment?**

The MobiFren MFB-N5100 is designed to work with Bluetooth mobile, computer or portable audio devices which are built in. It can also work with other Bluetooth devices that are compliant with Bluetooth version 1.1 / 1.2 / 2.0 / 2.1+EDR / 3.0 / 4.0 / 4.1 / 4.2 and that support HSP, HFP, A2DP and AVRCP.

- **Is the enclosed charging cable for only specified device?**


Its 'compatible with all standardized micro usb charger, and in general, compatible with Android mobile phone charger.

When you use the headset in the car, the handsfree can be affected by the internal noise.

Handle MobiFren with care

OFF

Always store the MobiFren MFB-H7100 with the power off and protect safely when its' not in use.



Avoid storage at extreme temperature.
(above 60 °C / 140°F -including direct sunlight -or below -20 °C / -4 °F)
This can affect the MobiFrens 'battery life and may be the cause of malfunction.
High temperature may also degrade performance.



Do not expose the MobiFren MFB- H7100 to rain or other liquids



Prevent baby, children or pets to bite or suck this headset.



Please do not disassemble at users' option.

5V

Please make sure to use certified charger. (Rated Voltage : 5V)

Certification and safety approvals

FCC ID : UZCMFB-H7100

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

Reorient or relocate the receiving antenna.

Increase the separation between the equipment and receiver.

Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This device complies with RF exposure requirement.

Made in Korea

In accordance with the R & TTE Directive 1999 / 5 / EC of 09. March 1999

Specifications

• Model	MFB-H7100
• Talk time (Earphone)	About 22 hrs
• Talk time (Speaker)	About 20 hrs
• Music play time (Earphone)	About 19 hrs
• Music play time (Speaker)	About 16 hrs
• Standby time	About 11 days
• Charging time	About 1hr 30mins
• Size	165mm (W) x 195mm (L) x 80mm (T)
• Battery	Rechargeable Lithium Polymer
• Weight	About 350 g
• Operation range	Within 10m
• Supporting Bluetooth profile	Headset profile
	Handsfree profile
	A2DP
	AVRCP
	SPP
• Bluetooth Version	Ver. 4.2 (LE unsupported)

※ Operation time may be variable, depending on connected device or setting status.

Warranty

※ The conditions and our responsibilities under this warranty are as follows :

- The warranty is limited to the original purchaser.
 - A copy of your receipt or other proof of purchase is required.
 - The warranty is void if the serial number, date code label or product label is removed, or if the product has been subject to physical abuse, improper installation, modification, or repair by unauthorized third parties.
 - The responsibility of MobiFren products shall be limited to the repair or replacement of the product at its sole discretion.
 - Any implied warranty on MobiFren products is limited to one year from the date of purchase on all parts, including any cord and connector. But, battery warranty is limited to 6 months.
 - Specifically exempt from any warranty are limited-life consumable components subject to normal wear and tear, such as microphone windscreens, ear cushions, decorative finishes, batteries, and other accessories.
 - MobiFren is not liable for any incidental or consequential damages arising from the use or misuse of any MobiFren product.
 - This warranty gives you specific rights and you may have other rights which vary from area to area.
 - Unless otherwise instructed in the User Manual, the user may not, under any circumstances, attempt to perform service, adjustments or repairs on this unit, whether in or out of warranty. It must be returned to the purchase point, factory or authorized service agency for all such work.
 - MobiFren will not take any responsibility for any loss or damage incurred in shipping. Any repair work on MobiFren products by unauthorized third parties voids any warranty.
-

"Contribute to our communities with good technology and good product"



www.mobifren.com

MobiFren Co.,Ltd.

88, Indong 52-gil, Gumi-City, Gyeongbuk, KOREA

TEL : +82-54-474-2220 FAX : +82-54-474-2251

ISO 9001 Quality Management System Certified Company

FCC ID : UZCMFB-H7100

CE 1177 3.7V $\frac{---}{-}$, 600mA



MADE IN KOREA

