



Food Retail - Reference Guide
Electronic Shelf Labels

May 2010



Copyright 2008 Altierre Corporation--All Rights Reserved.

This document contains confidential information. Reproduction, adaptation, or translation or sharing with third party requires prior permission

Publication Number: January 2008

Applicable Product: Altierre Store Gateway Console – “Beta Version”

Trademark Credits: Symbol; Microsoft

Disclaimer

Information and specifications in this document are subject to change without notice.

Altierre Corporation may have patents, patent applications, trademarks, copyrights, or other intellectual property rights covering subject matter in this document.

Except as expressly provided in any written license agreement from Altierre Corporation, the furnishing of this document does not grant any license to the patents, trademarks, copyrights, or other intellectual property covering the subject matter enclosed herein.

The names of actual companies and products mentioned herein may be the trademarks of their respective owners.

Warranty

The version of the Altierre Store Gateway Console being released is for “Beta” testing only. In no event shall Altierre Corporation be liable for any damages suffered by you as a result of using the beta products. Altierre Corporation will not be responsible for any loss of revenue, or any indirect, special, incidental or consequential damages of any kind related to the beta product, even if advised of the possibility of such damage.

Altierre Corporation
1980 Concourse Drive
San Jose, CA 95131

Class A digital devices

“This device complies with Part 15 of the FCC rules. Operation is subject to the following conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.”

Changes or alterations to the Altierre ESL System not expressly approved by Altierre could void the user’s authority to operate the equipment.






Electronic Shelf Labels (ESLs) are designed to make the price change process more accurate and efficient...

The Store associates have an Altierre Store Gateway Console (ASGC) and an Altierre Portable Terminal handheld (APT) to access the Altierre ESL System. The APT handheld will be the most used tool at the aisles with your ESL system it will: activate new item tags to the products.

Review the basic functions of the Altierre ESL System:

	Altierre System Gateway Console (ASGC) Keying Functions	Altierre Portable Terminal (APT) Keying Functions
Process #1 Login to use the ESL System	Login into the ASGC with assigned ID and Password - Key in <Username> - Key in <Password> - Select <LOGIN> <i>Login Menu</i>  <i>Main Menu/Home Page (after Login)</i> 	Power on the APT Handheld At Start Menu Select <Altierre Store Systems Login at the Altierre Systems Login Menu ✓ Key in <Username> ✓ Key in <Password> ✓ Select <Login> <i>Power On/Off button for the APT Handheld</i> <i>Login Menu</i>  <i>Main Menu(after Login)</i> 
Process #2 Log out of the ESL System	After Logging into the system the home page's tool bar displays Logout and Quick Links to system functions: ✓ APT's Main Menu ✓ Logout Icon - located at the top right of all screens on the toolbar at the ASG Screen 	LOGOUT at the APT Handheld  Logout: Select the back Arrow key on the Handheld located at the top right corner to Logout



Altierre Portable Terminal (APT) Keying Functions		
Process #3 Activating an ESL Tag	Adding a New Item to the ESL System is referred to as Activating a tag. From the Altierre Portable Terminal Handheld (APT) Main Menu: 1) Select < Activate ESL> 2) Scan the shelf location barcode with APT Handheld –<i>This Inputs data in the <Loc. Code> & <Location> fields</i> (location barcodes are adhered to each shelf railing) 3) Scan the Product's UPC Code 4) Read the ESL tag's ID 5) Select <ACTIVATE> and /or press the handheld's trigger to finalize the change	APT - Activating New Items Activation Screen with "Verify After Activation" Selected  Activation of ESL with Electronic Keyboard "toggled"  Bottom Right Icon 'toggles' the Electronic Keyboard to be displayed
Process #4 Deactivating an ESL Tag	If an ESL is removed from the sales floor deactivate tag. 1) Login into APT Handheld Main Menu 2) Select <Deactivate ESL> 3) Select <ID> 4) Place the handheld scanner close to the tag allowing it to read the ESL ID & barcode information screen 5) Select <Deactivate> - "Deactivation Successful" message is received on the APT screen 6) Remove Discontinued ESL tag and return for reactivation	APT - Deactivating Tags  Note: Reuse the Deactivated ESL Tags. Deactivated tags can be Reactivated to new products when needed.