

尺寸: 75x100mm 120g 铜版纸/ 折页/ 双面印刷

LED of Charging Case

Touch Button - MFB

Charging Port of Charging Case

Charging Pin of Earbud

Content:

TJ28 TWS Earbuds

Type-C USB Charging Cable

Quick Guide

x1

x1

x1

Product Specification

Bluetooth: V5.4

Frequency Range: 2402-2480 MHz

Sensitivity: 117± 3dB

Impedance: 32 ohm ± 15%

Input: DC 5V / 500 mA

Earphones Battery Capacity: 25 mAh x 2

Charging Pod Battery Capacity: 250 mAh

Charge Time: 2 hours

Charging for Earbuds:

Fully charge the battery for 2 hours before using the earbuds for the first time, or when they have been unused for extended periods.

Put the earbuds into the charging case, close the lid and they will charge automatically.

Charging for Charging Case:

When the charging case is connected with charger (or computer USB port) by charging cable, the indicator will flash in orange. When the charging case is fully charged, the indicator will be lit-in orange.

NOTE:

When the charging case is out of battery, the earbuds will not turn on/off automatically when removed from or placed back into the charging case. In this case, turn the earbuds on/off manually.

First Use & Pairing

Auto Power-On & Pairing

Open the lid of the charging case, the earbuds will automatically power on and enter into pairing mode.

Connect

Turn on the device's Bluetooth setting .

Search for and choose **TJ28** to pair, your device will show "connected" .

Power-Off

Auto Power-Off

Put L&R earbuds back into charging case and close the lid, the earbuds will automatically power off .

Manual Power-Off

The earbuds will automatically turn off when without pairing for 3 mins.

Wearing

Insert the earphones directed towards your ear canal. Twist gently until the earbuds fit comfortably and get better sound experience.

Control

Calls

Tap Once

Tap Twice

Touch for 2s

Answer Call

End Call

Reject Call

Music

Tap Once

Tap Thrice

Tap Twice

Play / Pause

Earbud R- Volume Up
Earbud L- Volume Down

Earbud R- Next Track
Earbud L- Previous Track

Voice Assistant

Touch for 2s

SIRI / Voice assistant

FCC Warning

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Any Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation.

If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.

- Increase the separation between the equipment and receiver.

- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.

- Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirement. The device can be used in portable exposure condition without restriction.

Designed in France. Made in China.

CE

FC

FCC ID: 2A7J2-TWST28

True Wireless Earphones

Model: TJ28

Quick Guide