



Appendix A

RF Test Data for BT LE (Conducted Measurement)

Product Name: LED Cloud Lights

Test Model: HCD-01

Environmental Conditions

Temperature:	23.5°C
Relative Humidity:	52.2%
ATM Pressure:	100.0 kPa
Test Engineer:	 Nick Peng
Supervised by:	 Li Huan





A.1 -6dB Bandwidth


Condition	Mode	Frequency (MHz)	Antenna	-6 dB Bandwidth (MHz)	Limit -6 dB Bandwidth (MHz)	Verdict
NVNT	BLE 1M	2402	Ant1	0.734	≥ 0.5	Pass
NVNT	BLE 1M	2440	Ant1	0.73	≥ 0.5	Pass
NVNT	BLE 1M	2480	Ant1	0.725	≥ 0.5	Pass






Test Graphs

-6dB Bandwidth NVNT BLE 1M 2402MHz Ant1



-6dB Bandwidth NVNT BLE 1M 2440MHz Ant1




Shenzhen LCS Compliance Testing Laboratory Ltd.

Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China

Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com

Scan code to check authenticity





A.2 Maximum Conducted Output Power


Condition	Mode	Frequency (MHz)	Antenna	Conducted Power (dBm)	Duty Factor (dB)	Total Power (dBm)	Limit (dBm)	Verdict
NVNT	BLE 1M	2402	Ant1	-1.43	0	-1.43	30	Pass
NVNT	BLE 1M	2440	Ant1	-0.28	0	-0.28	30	Pass
NVNT	BLE 1M	2480	Ant1	-1.1	0	-1.1	30	Pass







Test Graphs

Power NVNT BLE 1M 2402MHz Ant1



Power NVNT BLE 1M 2440MHz Ant1





Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity



A.3 Maximum Power Spectral Density Level

Condition	Mode	Frequency (MHz)	Antenna	Conducted PSD (dBm/3kHz)	Duty Factor (dB)	Total PSD (dBm/3kHz)	Limit (dBm/3kHz)	Verdict
NVNT	BLE 1M	2402	Ant1	-16.94	0	-16.94	8	Pass
NVNT	BLE 1M	2440	Ant1	-17.32	0	-17.32	8	Pass
NVNT	BLE 1M	2480	Ant1	-18.06	0	-18.06	8	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity





Test Graphs

PSD NVNT BLE 1M 2402MHz Ant1



PSD NVNT BLE 1M 2440MHz Ant1







A.4 Band Edge

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-40.39	-20	Pass
NVNT	BLE 1M	2480	Ant1	-43.68	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity






Test Graphs

Band Edge NVNT BLE 1M 2402MHz Ant1 Ref



Band Edge NVNT BLE 1M 2402MHz Ant1 Emission







A.5 Conducted RF Spurious Emission

Condition	Mode	Frequency (MHz)	Antenna	Max Value (dBc)	Limit (dBc)	Verdict
NVNT	BLE 1M	2402	Ant1	-36.87	-20	Pass
NVNT	BLE 1M	2440	Ant1	-37.16	-20	Pass
NVNT	BLE 1M	2480	Ant1	-38.52	-20	Pass




Shenzhen LCS Compliance Testing Laboratory Ltd.
Add: 101, 201 Bldg A & 301 Bldg C, Juji Industrial Park Yabianxueziwei, Shajing Street, Baoan District, Shenzhen, 518000, China
Tel: +(86) 0755-82591330 | E-mail: webmaster@lcs-cert.com | Web: www.lcs-cert.com
Scan code to check authenticity




Test Graphs

Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2402MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Ref




Tx. Spurious NVNT BLE 1M 2440MHz Ant1 Emission






Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Ref



Tx. Spurious NVNT BLE 1M 2480MHz Ant1 Emission





A.6 Duty Cycle


Condition	Mode	Frequency (MHz)	Antenna	Duty Cycle (%)	Correction Factor (dB)	1/T (kHz)
NVNT	BLE 1M	2402	Ant1	64.6	1.9	2.66
NVNT	BLE 1M	2440	Ant1	64.6	1.9	2.66
NVNT	BLE 1M	2480	Ant1	64.66	1.89	2.66







Test Graphs

Duty Cycle NVNT BLE 1M 2402MHz Ant1



Duty Cycle NVNT BLE 1M 2440MHz Ant1







A.7 Restrict Band


Condition	Mode	Frequency (MHz)	Antenna	Spur Freq (MHz)	Power (dBm)	Gain (dBi)	E (dBuV/m)	Detector	Limit (dBuV/m)	Verdict
NVNT	BLE 1M	2402	Ant1	2310	-51.45	2.5	46.28	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2310	-59.6	2.5	38.13	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2389.2	-43.4	2.5	54.33	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2353.872	-56.85	2.5	40.88	Average	54	Pass
NVNT	BLE 1M	2402	Ant1	2390	-45.06	2.5	52.67	Peak	74	Pass
NVNT	BLE 1M	2402	Ant1	2390	-58.87	2.5	38.86	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-43.22	2.5	54.51	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2483.5	-54.04	2.5	43.69	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2483.56	-29.39	2.5	68.34	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2483.512	-54.04	2.5	43.69	Average	54	Pass
NVNT	BLE 1M	2480	Ant1	2500	-50.95	2.5	46.78	Peak	74	Pass
NVNT	BLE 1M	2480	Ant1	2500	-59.1	2.5	38.63	Average	54	Pass






Test Graphs

Restrict Band NVNT BLE 1M 2402MHz Ant1 Peak




Restrict Band NVNT BLE 1M 2402MHz Ant1 Average





Restrict Band NVNT BLE 1M 2480MHz Ant1 Peak



Restrict Band NVNT BLE 1M 2480MHz Ant1 Average

